COMPUTER AIDED CONTROL SYSTEM DESIGN USING FREQUENCY DOMAIN SPECIFICATIONS

Anthony J. Mancini

NAVAL POSTGRADUATE SCHOOL
Monterey, California

THESIS

COMPUTER AIDED CONTROL SYSTEM DESIGN USING
FREQUENCY DOMAIN SPECIFICATIONS

by

Anthony J. Mancini

June 1976

Thesis Advisor: Dr. G. J. Thaler

UNCLASSIFIED

SECURITY CLASSIFICATION OF THIS PAGE (When Data Entered)

REPORT DOCUMENTATION PAGE

READ INSTRUCTIONS BEFORE COMPLETING FORM

1. REPORT NUMBER
2. GOVT ACCESSION NO.
3. RECIPIENT'S CATALOG NUMBER

4. TITLE (and Subtitle)
Computer Aided Control System Design Using Frequency Domain Specifications

5. TYPE OF REPORT & PERIOD COVERED
Engineer's Thesis (June 1976)

6. PERFORMING ORG. REPORT NUMBER

7. AUTHOR(s)
Anthony J. Mancini

8. CONTRACT OR GRANT NUMBER(s)

9. PERFORMING ORGANIZATION NAME AND ADDRESS
Naval Postgraduate School
Monterey, California 93940

10. PROGRAM ELEMENT, PROJECT, TASK AREA & WORK UNIT NUMBERS

11. CONTROLLING OFFICE NAME AND ADDRESS
Naval Postgraduate School
Monterey, California 93940

12. REPORT DATE
June 1976

13. NUMBER OF PAGES

14. MONITORING AGENCY NAME & ADDRESS(if different from Controlling Office)
Naval Postgraduate School
Monterey, California 93940

15. SECURITY CLASS. (of this report)
UNCLASSIFIED

15a. DECLASSIFICATION/DOWNGRADING SCHEDULE

16. DISTRIBUTION STATEMENT (of this Report)
Approved for public release; distribution unlimited.

17. DISTRIBUTION STATEMENT (of the abstract entered in Block 20, if different from Report)

18. SUPPLEMENTARY NOTES

19. KEY WORDS (Continue on reverse side if necessary and identify by block number)
Control System Design
Computer Aided Control System Design
Series Compensation
Linear Control Systems
Computer Aided Design
Transfer Function Synthesis
Frequency Response Techniques

20. ABSTRACT (Continue on reverse side if necessary and identify by block number)

The primary intent of this work is to investigate computer aided compensator design using classical frequency response techniques in conjunction with the techniques of modern mathematical programming. A computer program to perform the automated design task is presented. This particular algorithm is based on the constrained optimization technique introduced by M. J. Box.

In particular, the desired open loop frequency response is

DD FORM 1 JAN 73 1473 EDITION OF 1 NOV 65 IS OBSOLETE
S/N 0102-014-6601 |
(Page 1)

SECURITY CLASSIFICATION OF THIS PAGE (When Data Entered)

20. specified for a number of discrete frequency points over the frequency range of interest. Then the minimization routine is used to vary the compensator parameters in such a manner as to minimize a cost functional based on the difference between the actual and desired open loop frequency response of the compensated system. To illustrate the algorithm several detailed examples using the program are presented.

COMPUTER AIDED CONTROL SYSTEM DESIGN USING FREQUENCY DOMAIN SPECIFICATIONS

by

Anthony Joseph Mancini
Lieutenant United States Navy
E.S.E.E., University of Oklahoma, 1970
M.S.E.E., Naval Postgraduate School, 1975

Submitted in partial fulfillment of the
requirements for the degree of

ELECTRICAL ENGINEER

from the

NAVAL POSTGRADUATE SCHOOL

June 1976

ABSTRACT

The primary intent of this work is to investigate computer aided compensator design using classical frequency response techniques in conjunction with the techniques of modern mathematical programming. A computer program to perform the automated design task is presented. This particular algorithm is based on the constrained optimization technique introduced by M. J. Box.

In particular, the desired open loop frequency response is specified for a number of discrete frequency points over the frequency range of interest. Then the minimization routine is used to vary the compensator parameters in such a manner as to minimize a cost functional based on the difference between the actual and desired open loop frequency response of the compensated system. To illustrate the algorithm several detailed examples using the program are presented.

TABLE OF CONTENTS

LIST OF FIGURES

ACKNOWLEDGEMENTS

The author would like to express his sincere thanks and appreciation to Dr. G. J. Thaler for his continued encouragement, advice, and unselfish sharing of professional expertise during the research and development of this thesis.

A word of thanks is also owed to three members of the Naval Postgraduate School Computer Center Operations Staff, Mr. Ed Dornellan, Mrs. Kris Butler and Mr. M. Anderson, whose professional services contributed extensively to the efficient use of the time necessary in performing the large amount of computer work associated with the development, debugging, and testing of the program presented.

Finally, to my wife and children goes a special debt of gratitude for their patience, understanding, and encouragement during the months of development and research of this thesis. It would not have been possible to accomplish this undertaking without their continued help throughout this period.

I. INTRODUCTION

Concurrent with the proliferation of the digital computer as a viable, indeed often indispensable, engineering tool, the development of state-space methods resulted in the application of the digital computer in the area of modern control theory over the past decade and a half. Initially this application was primarily of an analysis nature, but as the theory of optimal control came into wider publication and acceptance, the role of the digital computer began to take on aspects of the design function. This situation is graphically illustrated by the myriad of industrial proprietary and university developed computer programs for computer aided control system design based upon state variable and optimal control theories. However, as pointed out by Mitchell [11] comparatively little work has been done to extend and apply the computational power, speed, and accuracy of modern digital computers to the proven classical theory and methods of control system design. After this essential abandonment of the classical methods (particularly by the academic and theoretical factions of the control engineering community) in favor of the modern theory and techniques, recent publications indicate a realization of the need that both approaches to system design be used in a complimentary rather than mutually exclusive manner. In particular the works of Coffey, MacFarlane, Mitchell, Page, Rosenbrock, Stear, [5,8,11,14] and others show a renewed interest in the tried and proven classical theory of design coupled with the new techniques and approaches developed by proponents of modern control theory, as applicable to the development of usable computer aided control system design algorithms.

Control system design based on frequency domain specifications, for linear time invariant parameter systems using classical methods, has traditionally been done essentially using trial and error techniques. That is, once the form and location of the compensator has been decided upon, the design process reduces to one of iterative analysis until the specifications are met or it becomes obvious to the designer that the compensator form chosen will not satisfy the specifications. When systems of any complexity are involved this method quite often transforms into an extremely tedious and time consuming process.

The availability of a good analysis program coupled with a digital computer operating in an interactive mode, to provide minimal turn around time, can be used to somewhat minimize the tedium of this type of design procedure. By varying the compensator parameters the designer may then observe the effects upon system performance without having to expend considerable effort in repeated calculations. This design by iterative analysis may be continued allowing the computer to perform the calculations until the designer is satisfied with the response obtained. With the recent refinements in mathematical programming techniques, it is possible to relegate some of the design decisions directly to the computer program, thus even further minimizing the time and efforts required of the design engineer. The ultimate goal, which is of course at present a long way down the road, would be to input only the plant dynamics and the desired specifications and have the computer perform the design process completely, without any interaction with the design engineer.

In this thesis an investigation of the automation of the design procedure is undertaken. In particular, given the desired open loop response in the frequency domain a minimization routine is used in conjunction with an analysis

algorithm to systematically vary the compensator parameters to approximate the desired response in accordance with a performance measure which indicates the deviation of the actual open loop frequency response from the desired open loop frequency response.

II. THE AUTOMATED DESIGN PROBLEM

A. GENERAL AUTOMATED DESIGN PHILOSOPHY

The word design, as used in many engineering texts of various disciplines, runs the gamut of describing a process dealing essentially with scaling already existing configurations and components to one dealing with a highly creative activity allowing a maximum amount of freedom in satisfying a set of requirements or specifications. On a day to day basis the majority of the design work accomplished by engineers lies somewhere between these two extremes, combining elements of relatively routine, straight forward calculations with those of creativity and imagination.

The overall scope of the design process in general is indeed so formidable that it often defies complete description in other than general terms, much less quantification in precise mathematical language. This latter is unfortunately a necessity in achieving the automation of this process within the limitations of the presently available hardware and software accessable by the engineer. Largely for this reason, when considering the automatic design problem it must by necessity be viewed, for the near future at least, in terms of a limited scope. That is, such items as creativity, experience, and intuition, which are undoubtedly elements of the total design process as viewed in its entirety, cannot be achieved by a computer as the device exists at the present time.

One of the key elements of any design process is decision making. In the overall design process the engineer makes decisions based upon the information available to him at the time of the design undertaking. Quite often these decisions are based on a comparison of numerical values of various elements of the design configuration. It is in this specific area of the overall design process that the modern day computer can serve as a significant tool for the engineer involved in design, particularly when a large number of comparisons (expressable in numerical terms) are involved. In other words, the computer can be used in a combination analysis and elementary decision making role to aid the engineer in the overall design procedure. By means of analysis numerical values may be obtained, forming a basis from which comparisons can be drawn. The analysis portion is generally essential for exact design and forms the basis for any optimization. The speed available in the digital computer allows many calculations and comparisons, over a wide range of possible solutions, to be performed which would be prohibitive if peformed by hand.

The employment of the digital computer as an aid in the aggregate design process is perhaps as much an art as the design process itself. While the use of computer aided design programs can free the engineer from many burdensome and time consuming calculations, the individual engineer must still provide the framework in which to interpret the results in the hard light of physical significance. The engineer must also be capable and willing to define the problem in a form with which the computer can work. More often than not, this latter requires a much sharper, clearer definition (and subsequently understanding) of the problem than if the same problem were being designed long hand. Unlike the analysis problem, which generally possesses a specific answer, the design problem may not have a unique solution which further complicates any computer aided design

algcrithm. Ancther aspect that should not be overlocked is the fact that when using a computer aided design program the engineer cften receives, if nothing else, an indicatien of the solutions which are not feasible. This in itself is often nct a trivial result especially in dealing with systems cf any complexity.

Ancther important factor which should nct be overlooked is that cnce an answer is obtained using a computer aided design algcrithm scme type of sensitivity study will more than likely be necessary. This is largely due to the fact that ccmpcnent values in physical hardware cannot generally be contrclled to the precision with which a computer does its calculatiens. Therefore, while a particular algcrithm for use in automated design may generate what is indeed a theoretically plausible solution the implementation of such a solutien may not be possible if it is extremely sensitive tc the parameter values involved.

B. SOME ASPECTS CF COMPUTERIZING THE CLASSICAL DESIGN CF CCNTROL SYSTEMS

Classically the purpose of the design problem in feedback contrcl systems has been to make a given plant satisfy a set cf performance specifications imposed upcn the system. Design of linear, time invariant ccmpensators for the contrcl cf linear systems has formed a major portion of the design effcrts of conventional servomechanisms. In the process cf investigating the automation of this design prccedure, certain key elements were found to be generally necessary in implementing a basic practical ccmputer algcrithm for automated design, regardless cf whether it is based on time cr frequency domain approaches. These elements consisted of:

1. A complete description of the plant or process to be controlled.

2. Specifications describing the response desired from the system.

3. Some type of criterion function or performance measure relating the actual to the desired response.

4. The form or structure of the compensator or control to be implemented.

These items appear in varying degrees as a common denominator among present day automated design algorithms [1,5,11,13] regardless of the specific methods employed or systems being considered. That is to say, these elements appear in algorithms designed for time domain, transform domain, stochastic processes, and nonlinear systems. Generally items 1. and 4. are employed in some form of analysis algorithm while items 2. and 3. form the basis for a minimization (or maximization) routine that provides a foundation for some type of decision making within the algorithm. This idea of using a performance measure upon which to base some type of decision making routine is a direct carryover from developments in the computerized design of optimal control systems which relies heavily upon the idea of minimizing some criterion function. Unlike the techniques of optimal control however, the cost functional as used in this context is not necessarily a function of the states and the applied control, but rather a measure of the deviation of the actual response from some desired response which has been specified by the designer. This is perhaps a fine distinction but one that must be recognized and kept in mind. One of the many consequences of this is that there is no longer a strong motivation to restrict the performance measure to a quadratic form in order that the second method of Liapunov may be used to prove that a stable system will result. Rather, the form of the cost function in computerized design based upon classical control theory is chosen to have properties which aid in the convergence of

the numerical minimization routine used in the algorithm or which has some inherent physical significance in the design process.

C. A FORMULATION OF THE AUTOMATIC DESIGN PROBLEM IN THE FREQUENCY DOMAIN

In this thesis the automatic design problem based on theory developed for classical design methods using frequency domain procedures is investigated. Several approaches based on frequency domain techniques have been presented by various people to automate the control system design process [5,11,13,14,20]. These algorithms range from methods designed primarily for use with multivariable systems to specialized interpretations of frequency domain data such as vector frequency domain techniques and inverse Nyquist methods. The suitability of these various methods have been demonstrated by their respective authors and others working in the area of computer aided control system design. While each represents a step forward in the line of progress toward automating the design process using frequency domain techniques the suitability of each algorithm is dictated to some extent by the particular type of design problem being solved. Many of these methods require gradient calculations, and those that do not rely primarily on simplex nonlinear programming algorithms. The former methods restrict the form of the cost function to be minimized in the sense that it must be differentiable and problems inherent with numerical differentiating algorithms are obviously involved. The latter methods involving simplex algorithms have difficulty in handling constrained minimization problems, particularly when solutions exist near or on the constraint boundaries.

One of the advantages of the frequency response approach lies in the fact that it lends itself easily to the use of open-loop frequency response data in designing closed loop systems. The use of frequency response methods provides a graphical portrayal of the system response that lends itself well to quick interpretation by the designer. Also since approaches such as those developed by Bode were intended to give simple approximate methods for use in hand calculations, adaptation of these methods in a computer algorithm allows the engineer to plan his design using such techniques and then employ the aid of the computer without the requirement of significant problem restructuring in order to cast the problem in some particular format not generally familiar to the designer, but necessary for solution by a computer algorithm. With systems involving complex transfer functions such restructuring can itself become quite burdensome thus defeating one of the primary reasons for turning to computer aided design. Perhaps it should be pointed out at this point that even using a computer algorithm to aid in the design process does not totally relieve the engineer of all hand calculations. Time must be taken to carefully map out a plan of attack on a particular problem. In essence the designer must thoroughly understand the problem and this is generally achieved by some preliminary rough sketches and calculations before the computer ever makes its appearance in the design process.

Throughout this thesis, the vehicle used for presenting the automated design algorithm is the single-input single-output unity feedback system of the form shown in figure II-1.



General System, Block Diagram

figure II-1

The plant is considered to be linear, time invariant, and completely known. Thus the plant may be described by a rational transfer function in the Laplace variable s of the form

$$G(s) = \frac{\prod_{i=0}^{n} (s + z_i)}{\prod_{i=0}^{m} (s + p_i)}$$

where z_i and p_i may be complex constants. The compensator $G_c(s)$ is also considered to be a rational transfer function in s.

The specifications are given in terms of the system open loop frequency response, and the desired response is achieved by reshaping the system open loop frequency response through the use of the compensator in the feed forward path. This basic procedure is well known to most control engineers and is by no means a novel approach to the design problem [3,10,17,18], but through the years it has found extensive use in the practical design of control systems.

The method proposed and under investigation here is a relatively straight forward adaptation of this technique with a computer algorithm harnessed to do the compensator parameter variation in order to systematically reshape the system open loop frequency response with a minimum amount of calculation and iteration required on the part of the designer. The desired open loop response is specified by means of a magnitude and phase profile over the frequency range of interest. This is nothing more than a set of desired magnitude and corresponding phase values at discrete frequency points selected by the designer. In addition a specific form or structure is postulated for the compensator transfer function $G_c(s)$. At this point of the automated design process the algorithm relies heavily on the experience and intuition of the individual designer in choosing a structure or form of compensator that will have some reasonable probability of success in reshaping the frequency response curves in order to satisfy the design specification. Since no firm analytical basis exists for the determination of a specific structure for the compensator, the computer algorithm must be given this information or an iterative method based on some type of criterion must be used in order to establish the form. This latter method was felt to be much too time consuming and restrictive, because of the wide range of variations in possible structures that might have to be considered, and essentially beyond the scope of this investigation. Thus the choice of the compensator form is relegated to the program user as a design decision that must be undertaken prior to using the algorithm to determine specific values for the coefficients of the compensator transfer function that will yield the desired response. This procedure should not present a major stumbling block for the designer provided that he possesss a thorough understanding of the problem to be solved. In fact, by inputing the specific form

of the compensator the designer may investigate compensator configurations which might otherwise be considered unfeasible for the solution of the problem if some type of iterative algorithm were used in determining the structure. With these items forming the basic inputs to the algorithm a nonlinear performance measure coupled with a minimization routine is then used to minimize the difference between the desired and actual frequency response of the open loop transfer function given by,

$$T(s) = G_c(s) \cdot G(s)$$

The performance measure (or cost function) selected is of a normalized form primarily as a matter of convenience in interpreting the algorithm's results regardless of the particular problem being considered. That is , the cost function has a general form given by

$$J(j\underline{\omega}) = f(1.0 - \frac{A(j\underline{\omega})}{D(j\underline{\omega})})$$

where $D(j\underline{\omega})$ represents the desired open loop frequency response of the entire system, $A(j\underline{\omega})$ is the actual open loop response, and $\underline{\omega}$ represents the set of discrete frequency values at which the cost function is to be evaluated. As mentioned previously this general form of normalized cost function was selected primarily as a matter of convenience in that a particular cost function can be constructed in such a manner that the optimal or smallest value of $J(j\underline{\omega})$ under ideal solution of the problem will be zero.

By inputing the desired response in the form of the magnitude and phase profile described above, normal frequency domain specifications such as gain margin, phase margin, and bandwidth (here defined as the open loop gain crossover frequency) may be supplied to the algorithm in one type of format. With these specifications forming part of the gain and phase profiles they are automatically

incorporated into the overall cost function each time the algorithm evaluates the frequency response of the open loop system over the range of frequencies specified by the designer, thus also eliminating the requirement of specialized computation within the algorithm to check for satisfaction of these particular specifications as the compensator parameters are varied.

III. THE MINIMIZATION TECHNIQUE USED

A. GENERAL

A variety of functional minimization techniques have come into use in recent years are discussed in ref. [8]. The minimization algorithm used in this work was developed originally by M. J. Box, [4], and is capable of finding the minimum of a general nonlinear cost function, composed of several variables, within a constrained region. The complex method of Box has been implemented in program form as part of the standard subroutine library at the Naval Postgraduate School W. R. Church Computer Center. The subroutine (BOXPLX), was originally programmed by R. R. Hilleary of the staff of the Naval Postgraduate School Computer Center and has subsequently been modified slightly by the author in order to render it more suitable for use in the scheme of the compensator optimization program.

In addition to its availability as a standard subroutine, several other features of this particular minimization algorithm made it an attractive choice for use in minimizing a cost function based on frequency domain specifications. While admittedly more efficient and sophisticated algorithms for function minimization are available, the flexibility and ease of programming of the complex method of Box are among considerations that should not be overlooked. This method does not require that the derivatives of the cost function or implicit constraints be calculated, thus avoiding the sundry problems typically

asscciated with numerical methods for the calculation of derivatives, and eliminating the restriction that the derivative of the cost function exist over the range of interest. In implementing the minimization method the cost function need not be expressed explicitly in terms of the variables to be manipulated by the program in the minimization process. Unlike many of the other minimization programs available, BOXPLX, also provides a restart capability. That is, once a possible minimum value of the cost functional is reached the program automatically restarts from randomly generated initial values of the variables. While this method by no means guarantees that a global minimum will be achieved for every conceivable problem the restart capability does at least somewhat attempt to avoid the problem of the minimization terminating on a local minima within the search area. This method is also to some extent scale independent in that the size of the initial geometric figure used in the search for the minimum value of the objective function is roughly scaled to the order of the problem variables, through the use of the difference between the lower and upper bounds on the variables.

As is the case with other minimization algorithms, this particular one is not void of inherent disadvantages and difficulties. Present in any minimization algorithm of course is the recurring problem that no guarantee can be made of achieving a global minimum for all classes of problems. The complex method cannot handle equality constraints without modification of the algorithm. Also as the number of variables increases the method rapidly becomes inefficient. Finally the unconstrained problem is apparently more efficiently handled via gradient techniques.

B. DESCRIPTION OF THE ALGORITHM

The minimization method developed by Box has its basis in the sequential simplex techniques of linear programming, but is specifically designed to obtain solutions to problems of constrained optimization and to avoid such problems as the inability of constructing the first simplex. Thus the resulting solution of the minimization problem is a set of variables which may lie at the extreme edges or boundaries of their permissible ranges. The problems generally associated with constraints on the variables is essentially attacked by using a flexible geometric figure having n+1, or more, vertices and capable of expanding or contracting, in any or all directions. Therefore, unlike many of the simplex algorithms no provision is made to maintain a regular geometry between the various points in an n-dimensional space, but rather a changing structure (dubbed a complex), capable of flattening, rounding corners, and eventually collapsing on the point representing the minimum of the objective function, is employed rendering the method more flexible in handling constrained minimization problems. The number of independent variables in the objective function and constraint equations dictate either directly or implicitly the dimensionality of the space to be searched. The vertices making up the complex are continually rejected and generated as a search for the minimum of the objective function is carried out with each new vertex generated being required to satisfy all the imposed constraints.

The complex method searches for the minimum of an objective function $J(\underline{x})$, where the vector $\underline{x}$ represents a set of n variables, within a region of space bounded by upper and lower limits on the variables (explicit constraints) given by,

$$L_i \leq x_i \leq U_i \quad , \quad i=1,2,3,\ldots,n$$

and in addition subject to the restrictions imposed by the constraint functions (implicit constraints) of the form,

$$h_j(\underline{x}) \geq 0 \quad j=1,2,3,\ldots,m.$$

As with the simplex methods this is an iterative algorithm. It uses a set of $k \geq n+1$ points which form the vertices of the complex and simultaneously satisfy all the imposed constraints. Initially only one point or vertex must satisfy all the constraints and serves as a means of generating the other k-1 vertices through the use of pseudorandom numbers r_i, uniformly distributed over the closed interval from zero to one. The additional k-1 vertices of the first complex are established by the following formula:

$$x_i = L_i + r_i \bullet (U_i - L_i)$$

As can be seen from the formula, the vertices generated in this fashion will always satisfy the explicit constraints, however, each one must be checked to insure compliance with the implicit constraints. If an implicit constraint violation is indeed found to occur at this stage then the trial vertex is simply moved, repeatedly if necessary, halfway in toward the centroid of the other already accepted vertices, until ultimately a feasible point is found. Continued application of this procedure will result in the generation of the k-1 additional points required for the initial complex within the feasible region defined by the constraints.

Once the initial complex has been determined the iteration proceeds by evaluating the objective function $J(\underline{x})$ at each vertex. The vertex at which the objective function has the largest value is then designated as the current worst vertex and this point is reflected through the centroid of the remaining vertices establishing a new

complex. If this worst vertex is designated as $\underline{x}^W$ then the overreflection is accomplished according to the formula

$$\underline{x}^N = (1.0 + \text{alpha}) \cdot \underline{x}^{CR} - \text{alpha} \cdot \underline{x}^W$$

where alpha $\geq$ 1.0 is the overreflection coefficient, $\underline{x}^{CR}$ represents the centroid of the remaining vertices, and $\underline{x}^N$ is the new vertex. If the overreflection of the current worst vertex results in a violation of the constraints or if the new point still has the worst value in the set of vertices then the point is moved halfway toward the centroid used in the overreflection process. This retraction is repeated (if necessary) until the overreflection coefficient is reduced to some small value, delta, or a suitable new vertex is established. If the overreflection coefficient is reduced to the value delta and the objective function value at this new point is still the worst in the set of vertices then the projected vertex is replaced by its original value and the second worst vertex will be overreflected instead. This process keeps the complex moving toward the minimum of the objective function provided the figure has not collapsed into its centroid. Once assured that the new complex satisfies all the constraints and results in an improvement of the objective function, vertices of the complex are rejected and generated in a systematic manner aimed at minimization of the objective function. Thus essentially the complex moves over the feasible region eventually straddling and collapsing upon the point that renders a minimum value for the objective function.

This process continues and is eventually terminated when the complex shrinks to a predetermined acceptable small value epsilon given by:

$$\left\{ \frac{1}{k} \sum_{l=1}^{k} \left[J(\underline{x}^{C}) - J(\underline{x}^{V}) \right]^{2} \right\}^{0.5} < \text{epsilon}$$

Where $J(\underline{x}^{C})$ represents the value of the objective function at the centroid and $J(\underline{x}^{V})$ is the value at the various vertices.

As pointed out by Box [4], the exact values of the overreflection coefficient, alpha, and the exact number of vertices, k, do not appear to be critical to the functioning of the algorithm provided that they are greater than unity and n+1 respectively. The main concern here is that a value of alpha larger than unity keeps the complex from shrinking prematurely as it traverses the feasible region in search of the minimum objective function value. Values of alpha = 1.3 and k = 2n as given in ref. 4 are used here since the exact values chosen are apparently not critical and good results have been reported, by the originator of the algorithm, using these particular values. For a detailed example of the iteration process and a more sophisticated explanation of the algorithm the interested reader is directed to refs. 2, 4, and 6.

IV. PROGRAM DESCRIPTION AND UTILIZATION

A. DESCRIPTION OF ALGORITHM IMPLEMENTATION

The frequency domain algorithm described in the latter part of Chapter II has been implemented in program form using FORTRAN IV coding and configured for use on the IBM 360-67 computer system available at the Naval Postgraduate School Computer Center. With the exception of the graphing subroutine the remainder of the program is self contained and may be used on any computer system having a standard FORTRAN IV compiler. Without the overhead routines required of the graphing subroutine, the basic program requires approximately 180k bytes of core memory, and including the core requirements of the plotting routines roughly 210k bytes of memory are required by the program. While admitedly less core would be necessary if such techniques as array overlaying were employed when programming the algorithm, it was felt that for simplicity in following the flow of the program by future users these techniques were best left unused.

The computer aided linear time invariant compensator optimization program (CALICO) is essentially composed of four main parts with numerous additional small subroutines functioning in supportive roles. Since often a program user may wish to perform certain modifications to programs of this nature in order that they may better serve his particular purpose, Appendix A provides a description of the supportive subroutines used within the program to facilitate

accomplishment of any program modifications that may be desired. A block diagram of the major components of the overall program are shown in figure IV-1. The main program serves primarily to input data describing the system under consideration and to output the values of the roots and the gain of the compensator that will best achieve the desired response in accordance with the cost function selected. During program execution, the main program also serves to direct the sequence of execution of the other major sections of the CAIICC algorithm.

Since the plant and compensator are assumed to be linear time-invariant, they may be completely described by transfer functions in the independent Laplace variable s. Once the plant and assumed form of the series compensation are input along with the profiles forming the desired phase and magnitude response program control proceeds to the minimization subroutine, BOXPLX. From the point of view of computer aided control system design, associated with this subroutine are two key function sub-programs, FE(X) and KE(X). The function sub-program FE(X) performs the calculation of the system open loop frequency response, at the discrete frequencies provided in the input data, and calculates the value of the cost function based upon the difference between the actual and desired frequency response at the discrete frequency values. Six separate cost functions, from which the program user may select one, are incorporated into this function sub-program. The value of the cost function is used by the minimization routine to vary the compensator parameters in order to minimize this quantity. The function sub-program KE(X) checks for any violation of the implicit constraints, which in this particular case are concerned mainly with the presence of right half plane roots. The implicit constraints used, also impose limits on the real and imaginary parts of the numerator and denominator polynomials evaluated at any



Program Block Diagram

Figure IV-1

particular frequency. These latter limits are a direct result of the finite computer word size and the particular method used to represent numerical values within the machine's memory. Both of these factors have an effect in determining the maximum and minimum size numerical value that may be represented within any particular computer. While the coefficient values determined by the minimization routine will not exceed these maximum or minimum values, the real and imaginary parts of the numerator and denominator polynomials evaluated at a particular frequency are squared during the process of determining the magnitude of the frequency response. Without the implicit constraints these squared values can exceed the size of the numerical capability of the machine, particularly in the case of high order systems, causing premature termination of the algorithm and hence failure in obtaining a solution. Once the minimization subroutine determines the coefficients that result in a minimum value of the cost function or the minimization process is terminated for other reasons, program control is transfered back to the main program. Here the roots and gain of the compensator which resulted in a minimum cost function are calculated and output. The open loop frequency response of the sytem is then calculated using a more densely distributed number of frequency values than would normally be selected by the designer for use in the minimization process. This is done largely to show the existence of any resonant peaks which might otherwise be straddled and not apparent if only the discrete frequencies selected by the designer were used in the plotting routines. The stability of the entire system is then checked by adding the open loop numerator and denominator polynomials and applying the Routh stability criterion to the resulting polynomial which is the system characteristic equation. Finally the results at the discrete frequencies specified by the designer and the "continuous" curve generated by the SIMULA subroutine are output on Bode and gain versus phase

plots. In addition, plots of the difference between the desired and actual results at the discrete frequencies specified by the designer are output in order to aid the designer in making any modifications to the form of the compensator that may be necessary in order to better satisfy the system specifications.

As stated in the previous paragraph six separate cost functions have been incorporated into the function sub-program FE(X). The first three of these are of the error squared type and the latter three are of the absolute error type. These six cost functions represent various combinations of one minus the actual response divided by the desired response at the discrete frequencies under consideration. These pre-defined cost functions are provided as a matter of convenience in using the program and certainly do not prevent the user from defining his own cost function provided this is placed within the FE(X) function sub-program. The first cost function combines the deviation of both the desired magnitude and phase responses from the actual magnitude and phase responses of the open loop system. That is the first cost function is of the form

$$J(\omega) = \sum \left\{ \left(1.0 - \frac{AMAG(\omega)}{DMAG(\omega)} \right)^2 + \left(1.0 - \frac{APHASE(\omega)}{DPHASE(\omega)} \right)^2 \right\}$$

where AMAG and APHASE are the actual magnitude and phase response of the open loop system and DMAG and DPHASE are the desired magnitude and phase respectively. These quantities are evaluated in the cost function and summed over the discrete frequency values in the specified range. The second cost function which the user may choose, uses solely the deviation of the actual magnitude response desired magnitude response evaluated at the discrete frequency values. Thus this cost function is of the general form

$$J(\omega) = \sum \left(1.0 - \frac{AMAG(\omega)}{DMAG(\omega)}\right)^2$$

If a minimum phase system is being considered the magnitude and phase plots as a function of frequency are uniquely related by the Bode theorems [3]. That is, determining the magnitude ratio of a system over a given frequency range will also result in a unique phase relationship for the system. Thus if the system design being considered is of the minimum phase type the use of the type two cost function described should result in both the magnitude and phase specifications being satisfied. The third pre-defined cost function uses the deviation of the actual open loop phase response from the desired phase response in a function of the form

$$J(\omega) = \sum \left(1.0 - \frac{APHASE(\omega)}{DPHASE(\omega)}\right)^2$$

While for minimum phase systems the magnitude and phase responses are uniquely related, it should be noted that the fixed loss or gain of the system cannot be determined from the phase characteristics alone. Consequently the use of the type three cost function may result in a constant gain error for the magnitude response of the system. This error however is readily observable from the output produced by the program and correction of this may be accomplished by adjustment of the compensator gain value accordingly. The other three pre-defined cost functions are of the same general form as those just presented with the exception that the squared differences are replaced by the absolute value of the differences. The general rationale in selecting this latter type of cost function was that on occasion the squared type cost function will have a tendency to flatten near the minimum. With the absolute value cost function the user may avoid the excessive time required in finding the

minimum values when the case arises where the squared cost function becomes flat.

In utilizing this design program the user should also be aware that the need for frequency scaling of the problem may arise. This is particularly true when high order systems involving high frequencies are being considered. The need for frequency scaling is primarily a result of the finite word size available in the computer system. It must be kept in mind that the magnitude response of the system is computed as the ratio of two complex numbers and while the resulting magnitude may be relatively small the value of the magnitudes of the individual complex numbers forming this ratio may be large. The situation is further complicated by the fact that in computing the magnitudes of the complex numbers involved the real and imaginary parts must be squared, thus effectively reducing the maximum power of the numbers which can be allowed by a factor of two. If the magnitudes of the resulting numbers become too large an error message will be printed recommending that the problem be frequency scaled.

B. DATA INPUT AND OUTPUT

In order to simplify use of the program, an attempt has been made to maintain the input information necessary for execution of the algorithm to a minimum, and at the same time preserve a certain amount of flexibility within the program which may be controlled by the user. In so doing some of the program control variables for various options have been set internal to the program and may not be manipulated by the user in the input data deck. These internally set variables do not detract from the general functioning of the program, but mention of this is made to

bring it to the user's attention in the event that specialized problems might more effectively be investigated by resetting some of these normally preset program variables. Many of the preset items are concerned with control of the minimization routine. Such items as the upper and lower bounds of the search area, the integer programming option, and the seed for the random number generator are set to specific values within the main program just prior to calling the minimization subroutine. For example for the minimum phase case, the lower and upper bounds on the search areas of the compensator numerator and denominator polynomial coefficients are set at 0.0 and 1.6×10^{6} respectively. For the non-minimum phase case the bounds on the search areas of the numerator polynomial coefficients only are extended to -1.6×10^{6} and 1.6×10^{6} and the implicit constraints are adjusted to allow right half plane roots for the numerator polynomial. The integer programming option for BOXPLX is also preset to a value of zero indicating that values for the polynomial coefficients need not be integers. In general, selection of the integer programming option results in considerably more execution time for the program and for the purpose of varying the compensator parameters the selection of this option provided nothing to enhance the solution of problems.

The input data required for program execution and control may be divided into general areas as follows: 1.) a title card; 2.) a series of cards giving the gain and coefficients of the plant transfer function; 3.) a series of cards giving the assumed gain and coefficient values of the compensator transfer function; 4.) a control card describing the plots desired, the type of cost function to be used, whether the system contains a zero order hold, and the number and range of the discrete frequency points being

considered; 5.) cards containing the discrete frequency values, the desired magnitude, and the desired phase; 6.) finally a card describing the number of iterative trials to be allowed in the minimization and whether any output is desired from the minimization routine in order to keep track of the manner in which the coefficients are being varied. The specific input formats of the above necessary data are described in detail in the following paragraphs. These paragraphs are numbered so as to indicate into which of the six general areas a particular data card belongs. This description coupled with the program listing given in Appendix B should provide sufficient information for setting up the data deck necessary for execution of the program. Figure IV-2 illustrates the data deck used in executing the first example problem presented in section C of this chapter. In this figure each line of data represents an individual data card. The column numbers for the data cards are also shown above and below the data deck section of the figure.

1. Title card.

This must be the first card of the data deck and provides a means of problem identification if several separate problems are run under one job name. Columns 1 through 48 may be used to input whatever alpha-numeric characters the user desires for identifying any particular problem. This title will also be printed on the graphical output requested by the user.

2A. Plant gain

The second card contains the gain of the plant in columns 1 through 10. If the gain is not explicitly present in the plant transfer function then the value input on this

card should be unity. The format used to read the plant gain is an E10.0 type format. Thus, the gain may be input in either floating point or scientific notation type formats.

2E. Input form and order of the plant transfer function numerator.

This card specifies whether the numerator of the plant transfer function is to be read in factored or polynomial form and what the order of the numerator is. A P or an F in column 1 indicates whether the plant numerator data is to be read in polynomial or factored form respectively. Columns 2 and 3 contain the order of the numerator. Thus an input of the form FC3 starting in column 1 indicates that the polynomial is of third order and is to be read in factored form.

2C. Plant transfer function numerator.

The following card(s) contain either the polynomial coefficients or the factors of the plant transfer function numerator, depending on which form has been chosen for input. If the polynomial form of input has been selected then the polynomial coefficients are input in ascending powers of s using an 8E10.0 format. If more than eight coefficients are needed they are simply continued on successive cards. The coefficient of the highest order term is assumed to be normalized to unity and is not read in explicity. Thus the number of coefficients actually read corresponds to the order of the numerator polynomial. If the factored form of input is chosen then each factor is read in on a separate card with columns 1 through 10 being used for the real part of the factor and columns 11 through 20 for the imaginary part. Again the format used is E10.0,

thus allowing the factors to be input in either floating point or scientific notation form. Since complex factors will occur in conjugate pairs the values of these factors need only be input once. Thus the number of cards used will vary depending upon how many purely real and how many complex factors are involved.

2D. Input form and order of the plant transfer function denominator.

Again the form of input is specified as in card number 2B along with the order of the plant transfer function denominator.

2E. Plant transfer function deromінator.

The format used to input the denominator is identical to that used for input of the numerator, contingent upon the desired form specified for the input. That is to say, it is possible to input the numerator in polynomial form and the denominator in factored form, or vice versa, since each time a polynomial is input as data the input form is uniquely specified.

3A. Assumed compensator transfer function gain.

Following the input of the information about the plant the description of the form of the compensator must be supplied. This is begun by inputing an assumed compersator gain using the same format as was used to specify the plant gain. Due to the manner in which the compensator transfer function numerator coefficients are handled within the program, if the assumed compensator gain is set to zero, for lack of any better value, whis will result in the starting

guess of all the numerator coefficients being zero. This will not cause the program to terminate prematurely, but the initial guess of zero for all the coefficients may not be what is desired by the user. If doubt exists as to what value gain should be assumed, a value of 1 is suggested as a convinient arbitrary starting point.

3B. Input form and order of the assumed compensator numerator.

The method for specifying the form of the input for the compensator initial numerator parameters is identical as that used in specifying the plant numerator. A P indicates polynomial form and an F indicates factored form.

3C. Assumed initial values of compensator numerator parameters.

In order to maintain continuity in the input format the scheme and format used to input the compensator numerator parameters is identical to that used in specifying the plant transfer function numerator.

3D. Input form and order of the assumed compensator denominator.

As in previous cases either polynomial or factored form is specified along with the order of the compensator denominator.

3E. Assumed initial values of compensator denominator parameters.

Once again the same format as used to input the plant

data is used in order to maintain the continuity of the input formating.

4A. Program control card.

The program control card is used to input various quantities controlling both the range and number of discrete points used in the minimization of the cost function, the output desired from the program, and also whether a zero order hold is present in the error channel of the system. As many as twelve separate quantities may be input on this single control card in order to direct execution of the program. Columns 1 through 10 specify the minimum frequency (WMIN), in radians, of the total range being considered. Columns 11 through 20 specify the maximum value (WMAX), in radians, of the range of frequencies being considered. Both of these values are read using a 2E10.0 format. Following the maximum and minimum frequency values, up to ten input quantities are read using a 10I3 format. Columns 21 through 23 specify the number of discrete frequency points (NOMEG) over the given range at which the open loop frequency response is to be determined and the cost function evaluated. The next input quantity (KNOW), in columns 24 through 26 specifies whether the discrete frequencies of interest are to be read from data cards or automatically computed. Normally this quantity is set to unity indicating that the discrete frequency points of interest will be read from data cards. A value of zero indicates that the discrete frequency values are to be incremented linearly by the program starting at the minimum frequency value. A value of two indicates that the discrete frequency points will be incremented logarithmically begining with the minimum frequency value. Columns 27 through 29 indicate whether a Bode plot of the results is desired. If this variable (NBODE) is set equal to one no Bode plot will be

output. A value of zero for NBODE will result in both magnitude and phase plots. Columns 30 through 32 control the output of the Nyquist plot. If NYQST is set to unity then the Nyquist plot will be suppressed. A value of zero for NYQST will result in a Nyquist plot output, however this is plotted only over the range of frequencies between WMIN and WMAX. Columns 33 through 35 indicate the presence of a zero order hold (IZOH) in the error channel of the unity feedback system. With IZOH set to zero the system is treated as being of a continuous nature. With IZOH set equal to one a zero order hold is considered to be present in the error channel and the open loop magnitude and phase computations are modified accordingly. Columns 36 through 38 (NICHOL) specify whether a magnitude versus phase plot of the results are desired. As with the other plot options, a value of zero will result in a plot being produced while a value of one will suppress the magnitude versus phase plot as part of the output. Columns 39 through 41 contain the variable indicating whether non-minimum phase solutions are to be considered. With this variable (NMINFS) set equal to zero only minimum phase solutions will be allowed. A value of one indicates that a non-minimum phase solution will be allowed provided that it is the one which minimizes the cost function. Columns 42 through 44 indicate if the desired magnitude profile values to be input are in decibels. If this variable (IDB) is zero the magnitude values to be read are dimensionless gain values, while a value of one indicates that the magnitude values to be input will be in decibels. Columns 45 through 47 contain the variable IPLOT. This quantity is used to choose between printer plots or Calcomp plots for the graphical output. A value of zero will result in printer plots and a value of unity will provide Calcomp output of the graphs desired. It is recommended that the printer plot option be used in initially solving a particular problem since this type of output requires less turn around time than the Calcomp

output. Finally columns 48 through 50 specify the type of cost function (ICOST) the user wishes to choose among the six preprogrammed functions available in subroutine FE(X). The value specified should be between 1 and 6 corresponding to the particular cost function desired. If this value is zero the program will default to the type one cost function.

4E. Sampling period.

This card must be inserted only if a zero order hold is specified in the error signal channel. The sampling period T, in seconds, is specified in columns 1 through 10. If the system being considered is of the continuous type then this card must be omitted.

5A. Discrete frequency values considered.

Next follows a set of data cards specifying the values in radians per second of the frequencies at which the desired gain and phase values of the open loop frequency response are specified and at which the cost function is to be calculated. These values are input in an 8E10.0 format using as many cards as necessary to specify all the frequency values at which the program is to execute the algorithm.

5E. Gain profile of the desired open loop response.

This set of data cards contains the desired open loop gain response at the discrete frequency values previously specified. The same 8E10.0 format is used here as was the case in reading the discrete frequency values. The same number of cards should be used as was used in specifying the

discrete frequency values.

5C. Phase profile of the desired response.

Here follows a series of cards specifying the desired open loop phase response, in degrees, at the discrete frequency values being considered.

6. Minimization trials card.

Here both the number of trials to be allowed in the minimization process and the print interval for diagnostic purposes are specified. These quantities are input using a 2I5 format. If the number of trials is zero then a default value of 2000 is assumed. If the print interval is specified as zero then no output from the minimization routine will result. Caution should be exercised in specifying the print interval in that if this interval is made too small an excessive amount of printed output may result. The program user is referred to the comment section of subroutine BOXPLX in Appendix A for guidelines in selection of the print interval.

EXAMPLE DATA DECK

```
(COLUMN NUMBERS, READ VERTICALLY)
         1111111111222222222233333333334444444444555555555566666666667777777778
12345678901234567890123456789012345678901234567890123456789012345678901234567890
||||||||||||||||||||||||||||||||||||||||||||||||||||||||||||||||||||||||||||||||||



COMP. OPT. EXAMP. ONE  LEAD COMP. 10PTS
 4.0
P00
F02
 0.0
 1.0
 2.0
 1.0
F01
 0.0
F01
 1.0
  0.2       20.0        010  1                              1  1
 0.200E 00 0.334E 00 0.557E 00 0.928E 00 0.155E 01 0.258E 01 0.431E 01 0.719E 01
 0.120E 02 0.200E 02
 0.335E 01 0.591E 01 0.346E 01 0.195E 01 0.101E 01 0.459E 00 0.179E 00 0.606E-01
 0.176E-01 0.445E-02
-0.969E 02-0.101E 03-0.109E 03-0.120E 03-0.137E 03-0.157E 03-0.178E 03-0.200E 03
-0.221E 03-0.238E 03
 5000



||||||||||||||||||||||||||||||||||||||||||||||||||||||||||||||||||||||||||||||||||
         1111111111222222222233333333334444444444555555555566666666667777777778
12345678901234567890123456789012345678901234567890123456789012345678901234567890
(COLUMN NUMBERS, READ VERTICALLY)
```

Figure IV-2

C. SERIES COMPENSATOR DESIGN EXAMPLE PROBLEMS

In this section a number of example problems are presented and discussed in order to illustrate the use of the computer aided compensator design algorithm. In the hope of presenting a clear, concise illustration of the algorithm and its use the example problems begin with relatively simple straight forward text book examples and gradually progress to problems of a slightly more difficult nature. Also included are problems that are intended to illustrate some limitations of the program in that these problems were not completely solved by the algorithm or they may have required a certain amount of manipulation of the input data in order to obtain a solution. These latter types of problems have been included since it is important that the designer using any computer aided design algorithm understand the algorithm's limitations and peculiarities as well as its intended capabilities. It is not intended to mislead the reader by implying that the example problems presented here provide a comprehensive presentation of all possible limitations of this automated design program. Rather they represent those limitations which were encountered in the process of verifying the program over a necessarily limited period of time. With this in mind the first example problem which deals with a relatively simple lead compensator is presented.

1. Compensator Design, Example 1.

Consider the uncompensated system shown in figure IV-3.



Design Example 1, Block Diagram

Figure IV-3

The asymptotic Bode diagram for the open loop system is shown in ir figure IV-3A. As can be seen from the open loop Bode plot, even though the system is stable it is lightly damped. A single section lead compensator is to be used to increase the phase margin. A complete discussion of the reasons for selection of the lead compensator and a detailed discussion of this particular example is presented by Thaler and Brown [18]. The transfer function form of the single section lead compensator consists of a first order numerator and a first order denominator. A desired magnitude and phase profile, consisting of ten discrete frequency points over the range from 0.2 to 20.0 radians, was selected to give a phase margin of approximately 45 degrees in order to increase the damping of the system. As an initial guess the compensator was assumed to have a gain of 1.0, a zero at the origin and a pole at -1.0. This information was supplied to the program in the prescribed format and the optimized results in the form of magnitude and phase plots are shown in figure IV-3B. Here, as throughout the remainder of the example problems, the diamond shaped symbols represent the desired values specified by the program user, the X symbols represent the values computed by the program at the discrete

frequency values specified using the compensator parameters returned as the solution from the minimization routine, and the continuous curve represents the response computed by the program again using the parameters returned as a solution but with a more dense set of frequency values used in order to show any resonant peaks or anomalies in the magnitude and phase curves which might be difficult to visualize from a sparsely selected set of discrete values. As can be seen in figure IV-3B the results match the desired response well over the range of interest. Figure IV-3C shows the same results using the magnitude versus phase plot to portray the open loop frequency response. The numerical values of the compensator parameters returned from the program as a solution along with the starting values used are shown in figures IV-3D, IV-3E, and IV-3F. A comparison with the solution values given in ref. 18 will show that they agree. Figure IV-3G shows plots of the differences between the actual and desired open loop frequency response of the resulting system at the discrete frequencies considered in the minimization process.

This problem as described required approximately 500 iterations within the minimization routine to achieve the solution shown. This however includes two restarts to attempt insuring that a global minimum had been achieved and that termination was not due to a local minimum. From the begining to the first restart required approximately 250 trials with the cost function being reduced from a value of 6.33 to a value of 0.00711 (recall that the minimum achievable under ideal condition is zero which due to machine errors alone in representing numbers would not likely ever be achieved). The entire solution required 32.5 seconds of CPU time, a good 10 seconds of which was used in the production of Calcomp plots. These numbers concerning the time required for solution are presented for what they are worth in that extrapolation of these numbers to more

complicated problems is not a straight forward task. As mentioned in Chapt III the minimization routine does become inefficient when the number of variable parameters is allowed to become large. It was felt that a detailed investigation of the efficiency and time required for solution of problems as a function of the number of variable parameters and the number of discrete frequency values to be considered was beyond the scope of the basic development of the program. However, the amount of time required for solution of some of the example problems that follow will be given in order to give the user an "intuitive feel" for the approximate amount of time that may be need to handle certain types of problems.

In order to illustrate that the starting point chosen should have reasonable values, but that the exact values chosen should not effect the final results significantly, the same problem was run a second time with the pole and zero of the compensator both chosen to be at the origin. Again an assumed initial gain of one was chosen for the compensator. The graphical results of the solution are shown in figures IV-3H through IV-3J. The numerical results returned using these new starting values are not shown here since they were identical to within three decimal places with those values shown previously.



Figure IV-3A
Uncompensated Open Loop System Bode Plot





Compensated System Magnitude and Phase Responses

Figure IV-3B



Magnitude vs. Phase

Figure IV-3C

```
TITLE --- COMP. OPT. EX. CL: 1 AD COMP IOPTS

UNCOMPENSATED TRANSFER FUNCTION GAIN =  4.000000E 00

UNCOMPENSATED TRANSFER FUNCTION NUMERATOR
COEFFICIENTS IN ASCENDING POWERS OF S

 1.000000E 00

UNCOMPENSATED TRANSFER FUNCTION DENOMINATOR
COEFFICIENTS IN ASCENDING POWERS OF S

 0.0            2.000000E 00    3.000000E 00    1.000000E 00

UNCOMPENSATED TRANSFER FUNCTION DENOMINATOR ROOTS
ARE:    REAL PART          IMAGINARY PART

        0.0                0.0

       -1.000000E 00       0.0

       -2.000000E 00       0.0

COMPENSATOR TRANSFER FUNCTION GAIN =  1.000000E 00

COMPENSATOR TRANSFER FUNCTION NUMERATOR
COEFFICIENTS IN ASCENDING POWERS OF S

 0.0            1.000000E 00

COMPENSATOR TRANSFER FUNCTION NUMERATOR ROOTS
ARE:    REAL PART          IMAGINARY PART

        0.0                0.0

COMPENSATOR TRANSFER FUNCTION DENOMINATOR
COEFFICIENTS IN ASCENDING POWERS OF S

 1.000000E 00    1.000000E 00
```

Computer Numerical Output Example 1

Figure IV-3D

```
     COMPENSATOR TRANSFER FUNCTION DENOMINATOR ROOTS
ARE:      REAL PART          IMAGINARY PART

          -1.000000E 00          0.0
-------------------------------------------------------------------------------
-------------------------------------------------------------------------------

     THE COMPENSATOR TRANSFER FUNCTION IS OF THE MINIMUM PHASE
TYPE, THEREFORE NO RIGHT HALF PLANE ZEROS WILL BE ALLOWED IN
THE SOLUTION FOR THE COMPENSATOR TRANSFER FUNCTION

-------------------------------------------------------------------------------
-------------------------------------------------------------------------------

     THE TOTAL NUMBER OF TRIALS CALLED FOR =  5000

-------------------------------------------------------------------------------
-------------------------------------------------------------------------------

     THE COST FUNCTION TO BE USED IS THE TYPE    1

-------------------------------------------------------------------------------

THE MINIMUM COST FUNCTION VALUE =  7.8100320E-05

THE ERROR RETURN CODE FROM BOXPLX =  0

-------------------------------------------------------------------------------
-------------------------------------------------------------------------------

     OPTIMIZED COMPENSATOR TRANSFER FUNCTION NUMERATOR
COEFFICIENTS IN ASCENDING POWERS OF S

   9.999060E 05     9.984820E 05

     OPTIMIZED COMPENSATOR TRANSFER FUNCTION NUMERATOR
ROOTS ARE:      REAL PART          IMAGINARY PART

               -1.001420E 00          0.0
-------------------------------------------------------------------------------

     OPTIMIZED COMPENSATOR TRANSFER FUNCTION DENOMINATOR
COEFFICIENTS IN ASCENDING POWERS OF S

   9.985400E-05    9.988900E 04
```

Computer Numerical Output Example 1

Figure IV-3E

OPTIMIZED COMPENSATOR TRANSFER FUNCTION DENOMINATOR

ROOTS ARE:	REAL PART	IMAGINARY PART
	-1.001554E 01	0.0

OPTIMIZED COMPENSATOR TRANSFER FUNCTION GAIN = 1.001596E 01

FREQUENCY	MAGNITUDE(DB)	DESIRED MAG(DB)	PHASE(DEG)	DESIRED PHASE
2.000000E-01	1.999645E 01	1.999645E 01	-9.687019E 01	-9.689999E 01
3.340000E-01	1.54 2J1 01	1.543175E 01	-1.014153E 02	-1.010000E 02
5.570000E-01	1.077461E 01	1.078182E 01	-1.088801E 02	-1.090000E 02
9.280000E-01	5.751e51 00	5.800692E 00	-1.202251E 02	-1.200000E 02
1.549999E 00	7.141e80E-02	8.642113E-02	-1.366093E 02	-1.370000E 02
2.580000E 00	-4.743145E 00	-5.753740E 00	-1.568889E 02	-1.570000E 02
4.309999E 00	-1.49 242E 01	-1.434294E 01	-1.786066E 02	-1.780000E 02
7.190000E 00	-2.439672E 01	-2.439052E 01	-2.001377E 02	-2.000000E 02
1.200000E 01	-3.511089E 01	-3.503974E 01	-2.206923E 02	-2.210000E 02
2.000000E 01	-4.702190E 01	-4.703277E 01	-2.376905E 02	-2.380000E 02

THE ROUTH TEST OF THE CHARACTERISTIC EQUATION INDICATES
THAT THE SYSTEM IS STABLE.

Computer Numerical Output Example 1
Figure IV-3F



Magnitude Difference vs. Frequency



Phase Difference vs. Frequency
Figure IV-3G





Example 1, Run #2

Figure IV-3H



Magnitude vs. Phase

Example 1, Run#2

Figure IV-3I



Magnitude Difference vs. Frequency



Phase Difference vs. Frequency

Example 1, Run #2

△ Figure IV-3J

2. Compensator Design, Example 2.

This example problem (discussed in detail in ref.10) has been chosen not only to familiarize the reader with the use of the program, but also to illustrate one of the shortcomings of the design program. In particular, while the program was successful in finding the correct solution, difficulties were encountered in the root finding subroutines. In this particular problem, during the final phases of execution the roots of a fourth order polynomial must be found in order to calculate the phase response using subroutine SIMULA which does these calculations using a more densely spaced set of discrete frequencies than in the minimization routine. Since numerical root finding routines have difficulty in finding roots for fourth order polynomials, the lack of good convergence for the roots of the system in both root finding subroutines caused the phase calculations normally done by subroutine SIMULA to be aborted. It should be emphasized that failure of the root finding subroutines in this case only effects the generation of the "continuous" phase response and in no way created any problems for the minimization part of the program as evidenced by the resulting correct values for the compensator parameters. The original uncompensated system being considered is shown in figure IV-4. A Bode diagram of the uncompensated system (figure IV-4A) reveals that the system as it exists is unstable. If stability were the only consideration, a simple attenuation of the plant gain would be sufficient to provide adequate phase margin to insure this. However, as with many series compensation problems, here we must effectively strike a compromise between effectiveness of control (generally associated with a higher gain) and stability of the system (generally associated with a lower gain). As discussed in ref. 10 a simple gain

attenuation would result in stability being achieved, but also has an undesirable effect upon the velocity error constant. Thus as discussed in detail in ref. 10, a lag compensation network appears as the best candidate to accomplish the job.



Design Example 2, Block Diagram

Figure IV-4

In this particular problem twenty discrete frequency values over the range from 0.005 to 50.0 radians were selected and the desired magnitude and phase values specified at these frequencies. As in the previous example problem the form of the compensator is selected as having a first order numerator and first order denominator, that is in this case a single section lag compensator is to be used. A type one form of the cost function was selected for the minimization process. The magnitude and phase profiles of the desired response along with the resulting response with the compensator included in the open loop system are shown in figures IV-4B, IV-4C, and IV-4D. As mentioned, the continuous curve for the phase response was not computed because of the failure of the root finding routines to find the open loop system roots. It can be seen in figure IV-4C that the phase response does agree well at the discrete

frequencies specified. Since we are dealing with a minimum phase system and figure IV-4B shows that there exists no resonant peaks in the magnitude curve the user may conclude that the phase response will also be well behaved for the various frequency values between the explicitly specified discrete values plotted. This case should serve to illustrate that the program requires that the user still provide an interpretation of the results. The computer output of figures IV-4E, IV-4F, and IV-4G shows that the compensator parameters are in agreement with the problem solution as presented in ref. 10 if the reader wishes to make the comparison. Figures Iv-4H and IV-4I show plots of the differences between the actual and desired magnitude and phase at the discrete frequencies selected for the minimization process.



Uncompensated Open Loop System Bode Plot

Figure IV-4A



Magnitude vs. Frequency

Figure IV-4B



Phase vs. Frequency

Figure IV-4C



Magnitude vs. Phase

Figure IV-4D

```
TITLE --- COMP. OPTIMIZ. EXAMPLE 2 LAG COMP. 20PT

UNCOMPENSATED TRANSFER FUNCTION GAIN = 1.0000000E 04

UNCOMPENSATED TRANSFER FUNCTION NUMERATOR
COEFFICIENTS IN ASCENDING POWERS OF S

1.0000000E 00

UNCOMPENSATED TRANSFER FUNCTION DENOMINATOR
COEFFICIENTS IN ASCENDING POWERS OF S

0.0              1.0000000E 02    2.0000000E 01    1.0000000E 00

UNCOMPENSATED TRANSFER FUNCTION DENOMINATOR ROOTS
ARE:     REAL PART          IMAGINARY PART

          0.0                0.0

         -1.0000000E-01      0.0

         -1.0000000E 01      0.0

COMPENSATOR TRANSFER FUNCTION GAIN = 1.0000000E 00

COMPENSATOR TRANSFER FUNCTION NUMERATOR
COEFFICIENTS IN ASCENDING POWERS OF S

1.0000000E 00    1.0000000E 00

COMPENSATOR TRANSFER FUNCTION DENOMINATOR ROOTS
ARE:     REAL PART          IMAGINARY PART

         -1.0000000E 00      0.0

COMPENSATOR TRANSFER FUNCTION DENOMINATOR
COEFFICIENTS IN ASCENDING POWERS OF S

1.0000000E 00    1.0000000E 00
```

Computer Numerical Output Example 2

Figure IV-4E

COMPENSATOR TRANSFER FUNCTION DENOMINATOR ROOTS

ARE:	REAL PART	IMAGINARY PART
	-1.000000E 00	0.0

THE COMPENSATOR TRANSFER FUNCTION IS OF THE MINIMUM PHASE TYPE. THEREFORE NO RIGHT-HALF PLANE ZEROS WILL BE ALLOWED IN THE SOLUTION FOR THE COMPENSATOR TRANSFER FUNCTION

THE TOTAL NUMBER OF TRIALS CALLED FOR = 10000

THE COST FUNCTION TO BE USED IS THE TYPE 1

THE MINIMUM COST FUNCTION VALUE = 2.210733E-04

THE ERROR RETURN CODE FROM BOXPLX = 0

OPTIMIZED COMPENSATOR TRANSFER FUNCTION NUMERATOR COEFFICIENTS IN ASCENDING POWERS OF S

8.830318E 01 2.247341E 02

OPTIMIZED COMPENSATOR TRANSFER FUNCTION NUMERATOR

ROOTS ARE:	REAL PART	IMAGINARY PART
	-3.929228E-01	0.0

OPTIMIZED COMPENSATOR TRANSFER FUNCTION DENOMINATOR COEFFICIENTS IN ASCENDING POWERS OF S

8.836658E 01 5.727121E 03

Computer Numerical Output Example 2

Figure IV-4F

```
OPTIMIZED COMPENSATOR TRANSFER FUNCTION DENOMINATOR
ROOTS ARE:      REAL PART          IMAGINARY PART

                -1.542545E-02      0.0

OPTIMIZED COMPENSATOR TRANSFER FUNCTION GAIN =  3.924033E-02

*WARNING**WARNING**WARNING**WARNING**WARNING**WARNING**WARNING**WARNING*

THE PHASE SIMULATION OF THE SYSTEM WAS ABANDONED
SINCE THE CALLS TO THE SEPARATE ROOT FINDING SUBROUTINES
FAILED TO FIND THE SYSTEM DENOMINATOR ROOTS

*WARNING**WARNING**WARNING**WARNING**WARNING**WARNING**WARNING**WARNING*
```

FREQUENCY	MAGNITUDE(DB)	DESIRED MAG(DB)	PHASE(DEG)	DESIRED PHASE
4.999999E-03	2.551130E 01	2.557506E 01	-1.072834E 02	-1.070000E 02
8.119997E-03	8.011274E 01	8.024354E 01	-1.166654E 02	-1.170000E 02
1.320000E-02	7.220178E 01	7.522351E 01	-1.267743E 02	-1.290000E 02
2.140000E-02	6.813600E 01	6.872325E 01	-1.413359E 02	-1.410000E 02
3.480000E-02	6.115204E 01	6.135471E 01	-1.514261E 02	-1.510000E 02
5.640000E-02	5.346447E 01	5.340042E 01	-1.571777E 02	-1.570000E 02
9.159994E-02	4.539258E 01	4.533026E 01	-1.583655E 02	-1.580000E 02
1.490000E-01	3.733859E 01	3.738461E 01	-1.550280E 02	-1.550000E 02
2.420000E-01	2.976214E 01	2.979915E 01	-1.474957E 02	-1.480000E 02
3.920000E-01	2.386538E 01	2.393436E 01	-1.376030E 02	-1.370000E 02
6.370000E-01	1.715145E 01	1.714669E 01	-1.272698E 02	-1.280000E 02
1.030000E 00	1.211532E 01	1.206287E 01	-1.217818E 02	-1.220000E 02
1.679999E 00	7.857044E 00	7.847118E 00	-1.217110E 02	-1.220000E 02
2.720000E 00	2.815950E 00	2.666670E 00	-1.284057E 02	-1.280000E 02
4.429999E 00	-2.575265E 00	-2.580223E 00	-1.425557E 02	-1.430000E 02
7.190000E 00	-8.320469E 00	-8.375950E 00	-1.643736E 02	-1.640000E 02
1.170000E 01	-1.697510E 01	-1.692422E 01	-1.908068E 02	-1.910000E 02
1.900000E 01	-2.697255E 01	-2.693573E 01	-2.156210E 02	-2.160000E 02
3.079999E 01	-3.830315E 01	-3.827280E 01	-2.347276E 02	-2.350000E 02
5.000000E 01	-5.040993E 01	-5.039986E 01	-2.476126E 02	-2.480000E 02

```
THE ROUTH TEST OF THE CHARACTERISTIC EQUATION INDICATES
THAT THE SYSTEM IS STABLE
```

Computer Numerical Output Example 2

Figure IV-4G



Magnitude Difference vs. Frequency

Figure IV-4H



Phase Difference vs. Frequency

Figure IV-4I

3. Compensator Design, Example 3.

Another lag type compensation problem is presented in this example. This time, however, the existence of a fourth order polynomial for either the open loop system transfer function numerator or denominator has purposely been avoided to insure that the program will run to completion. The uncompensated system block diagram is shown in figure IV-5.



Design Example 3, Block Diagram

Figure IV-5

A Bode diagram for the uncompensated system along with a detailed discussion of the problem may be found in ref. 17. The uncompensated system does not possess an adequate phase margin to insure proper system performance. Thus, a single section lag compensator is to be used in order to achieve the desired open loop frequency response. Desired gain and phase profiles are selected for the compensated open loop frequency response using 20 discrete frequency points over the range from 0.01 to 100.0 radians. The profiles

selected along with the results achieved are shown in figures IV-5A, IV-5B, and IV-5C. The numerical values assumed as initial estimates of the compensator parameters and the numerical results of the output are shown in figures IV-5D, IV-5E, and IV-5F. Plots of the differences between the actual magnitude and phase, and the desired magnitude and phase are shown in figures IV-5G and IV-5H. In this particular problem approximately 1200 iterations of the minimization routine and 1 minute and 25 seconds were required for solution of the problem. In order to illustrate the idea that for minimum phase systems the compensator parameters may be determined to within only a fixed loss or gain when using only the phase profile, this same problem was solved again using the type 3 cost function which considers only the difference between the desired and actual phase at the discrete frequencies. The results are shown in figures IV-5I, IV-5J, and IV-5K. As can be seen from the magnitude plot in figure IV-5I, there is a constant gain error in the resulting magnitude curve. The numerical values assumed at the start and those returned after the minimization of the cost function are shown in the computer output of figures IV-5L, IV-5M, and IV-5N. The resultant magnitude response is higher than desired. The necessary correction that must be applied to obtain the desired response may be read directly from figure IV-5O, which shows the difference between the actual and desired magnitude response. That is, as can be seen from figure IV-5C, the resultant magnitude of the open loop system after compensation is approximately 36.8 db higher than what is desired. Since the program does not alter any of the plant parameters this means that the compensator gain value returned from the program when the type 3 cost function was used must be decreased by approximately a factor of 69.2. A comparison of the compensator gain values shown in figures IV-5F and IV-5N will show that they due indeed differ by this value. Also the astute observer may notice that there

is a slight difference in the compensator pole value returned as the solution when the problem was solved using the type 3 cost function. While the difference in values is small it is suspected that in this particular case it is due to the fact that only a finite frequency range has been considered and the lower frequencies have been "slighted" somewhat in that the nonlinear phase curve has not yet flattened out at 0.1 radians. This is also the same situation that existed the first time the program was executed, but in this case the magnitude profile was also taken into account in the cost function and any deviations of the resultant magnitude values dominated the cost function value. In other words, it appears that in this particular problem the cost function is more sensitive to variations in the magnitude values than in the variations in the phase values.



Magnitude vs. Frequency

Figure IV-5A



Phase vs. Frequency

Figure IV-5B



Magnitude vs. Phase

Figure IV-5C

```
      TITLE --- COMPEN. OPTIMIZ. EXAMPLE 3   20PTS

      UNCOMPENSATED TRANSFER FUNCTION GAIN =  1.000000E 02

      UNCOMPENSATED TRANSFER FUNCTION NUMERATOR
 COEFFICIENTS IN ASCENDING POWERS OF S

   1.000000E 00

      UNCOMPENSATED TRANSFER FUNCTION DENOMINATOR
 COEFFICIENTS IN ASCENDING POWERS OF S

   0.0              1.000000E 00    1.000000E 00

      UNCOMPENSATED TRANSFER FUNCTION DENOMINATOR ROOTS
  ARE:     REAL PART          IMAGINARY PART

          0.0                 0.0

         -1.000000E 00        0.0

      COMPENSATOR TRANSFER FUNCTION GAIN =  1.000000E 00

      COMPENSATOR TRANSFER FUNCTION NUMERATOR
 COEFFICIENTS IN ASCENDING POWERS OF S

   1.000000E 00    1.000000E 00

      COMPENSATOR TRANSFER FUNCTION NUMERATOR ROOTS
  ARE:     REAL PART          IMAGINARY PART

         -1.000000E 00        0.0

      COMPENSATOR TRANSFER FUNCTION DENOMINATOR
 COEFFICIENTS IN ASCENDING POWERS OF S

   1.000000E 00    1.000000E 00
```

Computer Numerical Output Example 3, Run #1

Figure IV-5D

```
      COMPENSATOR TRANSFER FUNCTION DENOMINATOR ROOTS
   ARE:      REAL PART          IMAGINARY PART

          -1.CCCCCCE 00        0.0
 ------------------------------------------------------------------------
 ------------------------------------------------------------------------

      THE COMPENSATOR TRANSFER FUNCTION IS OF THE MINIMUM PHASE
TYPE, THEREFORE NO RIGHT HALF PLANE ZEROS WILL BE ALLOWED IN
THE SOLUTION FOR THE COMPENSATOR TRANSFER FUNCTION
 ------------------------------------------------------------------------
 ------------------------------------------------------------------------

      THE TOTAL NUMBER OF TRIALS CALLED FOR = 10000
 ------------------------------------------------------------------------
 ------------------------------------------------------------------------

      THE COST FUNCTION TO BE USED IS THE TYPE    1
 ------------------------------------------------------------------------

THE MINIMUM COST FUNCTION VALUE =  2.522382E-04

THE ERROR RETURN CODE FROM ECXPLX =    0
 ------------------------------------------------------------------------
 ------------------------------------------------------------------------

      OPTIMIZED COMPENSATOR TRANSFER FUNCTION NUMERATOR
 COEFFICIENTS IN ASCENDING POWERS OF S

    1.832424E 00    3.058981E 01

      OPTIMIZED COMPENSATOR TRANSFER FUNCTION NUMERATOR
   ROOTS ARE:      REAL PART          IMAGINARY PART

               -5.990308E-02        0.0
 ------------------------------------------------------------------------

      OPTIMIZED COMPENSATOR TRANSFER FUNCTION DENOMINATOR
 COEFFICIENTS IN ASCENDING POWERS OF S

    2.086647E 00    4.892434E 03
```

Computer Numerical Output Example 3, Run #1
Figure IV-5E

OPTIMIZED COMPENSATOR TRANSFER FUNCTION DENOMINATOR

ROOTS ARE:	REAL PART	IMAGINARY PART
	-4.265048E-04	0.0

OPTIMIZED COMPENSATOR TRANSFER FUNCTION GAIN = 6.252471E-03

FREQUENCY	MAGNITUDE(DB)	DESIRED MAG(DB)	PHASE(DEG)	DESIRED PHASE
9.999998E-03	5.158107E 01	5.159566E 01	-1.686534E 02	-1.690000E 02
1.620000E-02	4.339182E 01	4.334634E 01	-1.642871E 02	-1.640000E 02
2.640000E-02	3.537256E 01	3.540230E 01	-1.568031E 02	-1.570000E 02
4.280000E-02	2.795507E 01	2.799347E 01	-1.463345E 02	-1.460000E 02
6.949997E-02	2.147256E 01	2.151093E 01	-1.343827E 02	-1.340000E 02
1.130000E-01	1.587987E 01	1.588976E 01	-1.241597E 02	-1.240000E 02
1.830000E-01	1.097100E 01	1.095549E 01	-1.183622E 02	-1.180000E 02
2.980000E-01	6.239247E 00	6.235075E 00	-1.178781E 02	-1.180000E 02
4.830000E-01	1.397734E 00	1.363709E 00	-1.227599E 02	-1.230000E 02
7.850000E-01	-4.026157E 00	-4.026987E 00	-1.324646E 02	-1.320000E 02
1.270000E 00	-1.031660E 01	-1.037114E 01	-1.444644E 02	-1.450000E 02
2.070000E 00	-1.762509E 01	-1.758852E 01	-1.558016E 02	-1.560000E 02
3.360000E 00	-2.545972E 01	-2.549839E 01	-1.644401E 02	-1.640000E 02
5.459999E 00	-3.370943E 01	-3.368059E 01	-1.702453E 02	-1.700000E 02
8.860000E 00	-4.203107E 01	-4.203645E 01	-1.739451E 02	-1.740000E 02
1.440000E 01	-5.043427E 01	-5.042867E 01	-1.762640E 02	-1.760000E 02
2.339999E 01	-5.885547E 01	-5.886189E 01	-1.776985E 02	-1.780000E 02
3.789999E 01	-6.727755E 01	-6.725021E 01	-1.785784E 02	-1.790000E 02
6.159999E 01	-7.566331E 01	-7.565030E 01	-1.791251E 02	-1.790000E 02
1.000000E 02	-8.407938E 01	-8.408238E 01	-1.794612E 02	-1.790000E 02

THE ROUTH TEST OF THE CHARACTERISTIC EQUATION INDICATES
THAT THE SYSTEM IS STABLE

Computer Numerical Output Example 3, Run #1

Figure IV-5F



Magnitude Difference vs. Frequency

Figure IV-5G



Phase Difference vs. Frequency

Figure IV-5H



Magnitude vs. Frequency

Figure IV-5I



Phase vs. Frequency

Figure IV-5J


(db)
80.0
60.0
40.0
20.0
0
-20.0
-40.0
-60.0
-80.0
-240
-210
-180
-150
-120
-090
(degs.)
◇ --- desired response
X --- actual response
— --- "continuous" actual response
Magnitude vs. Phase

Figure IV-5K

```
      TITLE --- COMPEN. OPTIMIZ. EXAMPLE 3B  20PTS

      UNCOMPENSATED TRANSFER FUNCTION GAIN =  1.000000E 02

      UNCOMPENSATED TRANSFER FUNCTION NUMERATOR
 COEFFICIENTS IN ASCENDING POWERS OF S

    1.000000E 00

      UNCOMPENSATED TRANSFER FUNCTION DENOMINATOR
 COEFFICIENTS IN ASCENDING POWERS OF S

    0.0              1.000000E 00     1.000000E 00

      UNCOMPENSATED TRANSFER FUNCTION DENOMINATOR ROOTS
  ARE:      REAL PART          IMAGINARY PART

          0.0                  0.0

         -1.000000E 00         0.0

      COMPENSATOR TRANSFER FUNCTION GAIN =  1.000000E 00

      COMPENSATOR TRANSFER FUNCTION NUMERATOR
 COEFFICIENTS IN ASCENDING POWERS OF S

    1.000000E 00     1.000000E 00

      COMPENSATOR TRANSFER FUNCTION NUMERATOR ROOTS
  ARE:      REAL PART          IMAGINARY PART

         -1.000000E 00         0.0

      COMPENSATOR TRANSFER FUNCTION DENOMINATOR
 COEFFICIENTS IN ASCENDING POWERS OF S

    1.000000E 00     1.000000E 00
```

Computer Numerical Output Example 3, Run #2

Figure IV-5L

COMPENSATOR TRANSFER FUNCTION DENOMINATOR ROOTS
ARE: REAL PART IMAGINARY PART

-1.CCCCCCE 00 0.0

THE COMPENSATOR TRANSFER FUNCTION IS OF THE MINIMUM PHASE TYPE, THEREFORE NO RIGHT HALF PLANE ZEROS WILL BE ALLOWED IN THE SOLUTION FOR THE COMPENSATOR TRANSFER FUNCTION

THE TOTAL NUMBER OF TRIALS CALLED FOR = 10000

THE COST FUNCTION TO BE USED IS THE TYPE 3

THE MINIMUM COST FUNCTION VALUE = 7.442613E-05

THE ERROR RETURN CODE FROM BCXPLX = 0

OPTIMIZED COMPENSATOR TRANSFER FUNCTION NUMERATOR COEFFICIENTS IN ASCENDING POWERS OF S

7.943527E 03 1.341418E 05

OPTIMIZED COMPENSATOR TRANSFER FUNCTION NUMERATOR
ROOTS ARE: REAL PART IMAGINARY PART

-5.921741E-02 0.0

OPTIMIZED COMPENSATOR TRANSFER FUNCTION DENOMINATOR COEFFICIENTS IN ASCENDING POWERS OF S

1.132473E 02 3.089048E 05

Computer Numerical Output Example 3, Run #2
Figure IV-5M

OPTIMIZED COMPENSATOR TRANSFER FUNCTION DENOMINATOR
ROOTS ARE: REAL PART IMAGINARY PART

-3.666091E-04 0.0

OPTIMIZED COMPENSATOR TRANSFER FUNCTION GAIN = 4.342495E-01

FREQUENCY	MAGNITUDE(DB)	DESIRED MAG(DB)	PHASE(DEG)	DESIRED PHASE
5.999998E-03	8.831963E 01	5.159566E 01	-1.688882E 02	-1.690000E 02
1.620000E-02	8.013324E 01	4.334634E 01	-1.643218E 02	-1.640000E 02
2.640000E-02	7.212305E 01	3.540230E 01	-1.566887E 02	-1.570000E 02
4.280000E-02	6.476300E 01	2.799347E 01	-1.461021E 02	-1.460000E 02
6.999997E-02	5.826442E 01	2.151093E 01	-1.341061E 02	-1.340000E 02
1.130000E-01	5.269189E 01	1.588976E 01	-1.239180E 02	-1.240000E 02
1.830000E-01	4.775518E 01	1.095549E 01	-1.181869E 02	-1.180000E 02
2.980000E-01	4.306915E 01	6.235075E 00	-1.177628E 02	-1.180000E 02
4.830000E-01	3.823000E 01	1.363709E 00	-1.227269E 02	-1.230000E 02
7.850000E-01	3.279701E 01	-4.026987E 00	-1.324192E 02	-1.320000E 02
1.270000E 00	2.651669E 01	-1.037114E 01	-1.444262E 02	-1.450000E 02
2.070000E 00	1.920857E 01	-1.758852E 01	-1.558436E 02	-1.560000E 02
3.360000E 00	1.133397E 01	-2.549809E 01	-1.644255E 02	-1.640000E 02
5.459999E 00	3.124302E 00	-3.363059E 01	-1.702387E 02	-1.700000E 02
8.860000E 00	-5.197330E 00	-4.203645E 01	-1.739409E 02	-1.740000E 02
1.440000E 01	-1.360093E 01	-5.042867E 01	-1.762615E 02	-1.760000E 02
2.339999E 01	-2.202173E 01	-5.886189E 01	-1.776968E 02	-1.780000E 02
3.789999E 01	-3.039377E 01	-6.725021E 01	-1.785774E 02	-1.790000E 02
6.159999E 01	-3.882957E 01	-7.565030E 01	-1.791245E 02	-1.790000E 02
1.000000E 02	-4.724564E 01	-8.403238E 01	-1.794607E 02	-1.790000E 02

THE ROUTH TEST OF THE CHARACTERISTIC EQUATION INDICATES THAT THE SYSTEM IS STABLE

Computer Numerical Output Example 3, Run #2

Figure IV-5N



Magnitude Difference vs. Frequency

Figure IV-50



Phase Difference vs. Frequency

Figure IV-5P

4. Compensator Design, Example 4

In this example a slightly more complicated problem is presented, in that the final solution requires a double section compensator of the form of a notch filter. A block diagram of the uncompensated system is shown in figure IV-6. As discussed by Thaler and Brown [18], from whom this example was taken, the uncompensated system is unstable and the Bode diagram of the uncompensated system shown in figure IV-6A indicates a phase margin of approximately -30 degrees. With such a large negative phase margin for the uncompensated system and the rapid drop in slope of both the gain and phase curves the designer might suspect that compensation using only a single section compensator will be difficult to accomplish. Again desired magnitude and phase profiles are selected and initially a single section of compensation is assumed to observe how close to the desired response the system will perform. As can be seen in the resultant graphical output of figures IV-6A, IV-6B, and IV-6C, the single section compensator fails to meet the required frequency specifications. In fact, while it is possible to stabilize ths system with a single section compensator the bandwidth will be excessively large and the desired magnitude profile prevents the program from accomplishing this. The numerical results returned from the single section compensator run are shown in figures IV-6D, IV-6E, and IV-6F. As can be seen in figure IV-6F, the Routh test of the characteristic equation also indicates system instability which is to be expected. The magnitude and phase difference curves of figures IV-6G and IV-6H, which indicate the difference between the specified magnitude and phase profiles and the values actually achieved, indicate that additional compensation may be needed at the higher frequency ranges. Thus a double section compensator was assumed and the results achieved are illustrated in figures

IV-6I, IV-6J, and IV-6K. The program is able to satisfy the specifications with a double section of compensation and the parameters required to accomplish this are shown in figures IV-6I, IV-6M, and IV-6N. The differences between the desired and specified magnitude and phase values for the double section of compensation inserted in the system are shown in figures IV-6O and IV-6P.



Design Example 4, Block Diagram

Figure IV-6

Uncompensated System Bode Plot
Figure IV-6A



Magnitude vs. Frequency, Single Section Compensator
Figure IV-6B



Phase vs. Frequency, Single Section Compensator

Figure IV-6C



Computer Numerical Output
Figure IV-6D

COMPENSATOR TRANSFER FUNCTION DENOMINATOR ROOTS

	REAL PART	IMAGINARY PART
	-1.000000E 00	0.0

THE COMPENSATOR TRANSFER FUNCTION IS OF THE MINIMUM PHASE TYPE, THEREFORE NO RIGHT HALF PLANE ZEROS WILL BE ALLOWED IN THE SOLUTION OF THE COMPENSATOR TRANSFER FUNCTION

THE TOTAL NUMBER OF TRIALS CALLED FOR = 10000

THE COST FUNCTION TO BE USED IS THE TYPE 1

THE FIRST VERTEX VALUES ARE:

3.396385 05 1.086201 05 3.292767 05 1.081525 05

THE MINIMUM COST FUNCTION VALUE = 3.921601 00

THE ERROR RETURN CODE FROM DCXPLX = 2

OPTIMIZED COMPENSATOR TRANSFER FUNCTION NUMERATOR COEFFICIENTS IN ASCENDING POWERS OF S

3.396385 05 1.086201 05

Computer Numerical Output
Figure IV-6E

```
      OPTIMIZED COMPENSATOR TRANSFER FUNCTION NUMERATOR
 ROOTS ARE:        REAL PART              IMAGINARY PART

                  -3.128681E 00            0.0

      OPTIMIZED COMPENSATOR TRANSFER FUNCTION DENOMINATOR
 COEFFICIENTS IN ASCENDING POWERS OF S.

  3.292767E 05    1.001555E 05

      OPTIMIZED COMPENSATOR TRANSFER FUNCTION DENOMINATOR
 ROOTS ARE:        REAL PART              IMAGINARY PART

                  -4.223654E 01            0.0

      OPTIMIZED COMPENSATOR TRANSFER FUNCTION GAIN =  1.392288E-01

********** W A R N I N G ********** ********** W A R N I N G **********

THE SOUTH TEST OF THE CHARACTERISTIC EQUATION INDICATES SYSTEM
INSTABILITY

********** W A R N I N G ********** ********** W A R N I N G **********
```

Computer Numerical Output
Figure IV-6F



Magnitude Difference vs. Frequency, Single Section Compensator

Figure IV-6G



Phase Difference vs. Frequency, Single Section Compensator
Figure IV-6H



Magnitude vs. Frequency, Double Section Compensator

Figure IV-6I



Phase vs. Frequency, Double Section Compensator

Figure IV-6J



Magnitude vs. Phase, Double Section Compensator

Figure IV-6K

TITLE --- COMP. OPT. EX2. 4 POLES. TYPE I CSF.

UNCOMPENSATED TRANSFER FUNCTION GAIN = 4.000000E 07

UNCOMPENSATED TRANSFER FUNCTION NUMERATOR
COEFFICIENTS IN ASCENDING POWERS OF S

1.000000E 00

UNCOMPENSATED TRANSFER FUNCTION DENOMINATOR
COEFFICIENTS IN ASCENDING POWERS OF S

0.0 2.300000E 03 5.045999E 02 1.000000E 00

UNCOMPENSATED TRANSFER FUNCTION DENOMINATOR ROOTS

ARE:	REAL PART	IMAGINARY PART
	0.0	0.0
	-4.599999E 00	0.0
	-5.000000E 02	0.0

COMPENSATOR TRANSFER FUNCTION GAIN = 1.000000E 00

COMPENSATOR TRANSFER FUNCTION NUMERATOR
COEFFICIENTS IN ASCENDING POWERS OF S

1.000000E 00 2.000000E 00 1.000000E 00

COMPENSATOR TRANSFER FUNCTION NUMERATOR ROOTS

ARE:	REAL PART	IMAGINARY PART
	-1.000000E 00	0.0
	-1.000000E 00	0.0

COMPENSATOR TRANSFER FUNCTION DENOMINATOR
COEFFICIENTS IN ASCENDING POWERS OF S

1.000000E 00 2.000000E 00 1.000000E 00

Computer Numerical Output
Figure IV-6L

COMPENSATOR TRANSFER FUNCTION'S DENOMINATOR ROOTS

ARE:	REAL PART	IMAGINARY PART
	-1.000000E 00	0.0
	-1.000000E-09	0.0

THE COMPENSATOR TRANSFER FUNCTION IS OF THE MINIMUM PHASE TYPE, THEREFORE NO RIGHT-HALF PLANE ZEROS WILL BE ALLOWED IN THE SOLUTION FOR THE COMPENSATOR TRANSFER FUNCTION

THE TOTAL NUMBER OF TRIALS CALLED FOR = 10000

THE COST FUNCTION TO BE USED IS THE TYPE 1

THE BEST VERTEX VALUES ARE:

4.906714E 05 1.082894E 05 1.964592E 03 4.907928E 05 9.853190E 05
1.963274E 03

THE MINIMUM COST FUNCTION VALUE = 1.532074E-04

THE ERROR RETURN CODE FROM BOXPIX = 0

OPTIMIZED COMPENSATOR TRANSFER FUNCTION NUMERATOR COEFFICIENTS IN ASCENDING POWERS OF S

4.906714E 05 1.082894E 05 1.964592E 03

Computer Numerical Output
Figure IV-6M

OPTIMIZED COMPENSATOR TRANSFER FUNCTION NUMERATOR

ROOTS ARE:	REAL PART	IMAGINARY PART
	-5.013924E 01	0.0
	-4.981477E 00	0.0

OPTIMIZED COMPENSATOR TRANSFER FUNCTION DENOMINATOR
COEFFICIENTS IN ASCENDING POWERS OF S

4.907928E 05 9.856190 05 1.963274 04

OPTIMIZED COMPENSATOR TRANSFER FUNCTION DENOMINATOR

ROOTS ARE:	REAL PART	IMAGINARY PART
	-5.013762E 02	0.0
	-4.985962E-01	0.0

OPTIMIZED COMPENSATOR TRANSFER FUNCTION GAIN = 1.000670E 00

FREQUENCY	MAGNITUDE(DB)	DESIRED MAG(DB)	PHASE(DEG)	DESIRED PHASE
9.999996E-02	1.058469E-02	1.058451E-02	-1.013448E 02	-1.010000E 02
1.640000E-01	1.012747E 02	1.012892E 02	-1.082134E 02	-1.080000E 02
2.690000E-01	9.631134E 01	9.632481E 01	-1.183541E 02	-1.180000E 02
4.410000E-01	9.331336E 01	9.332963E 01	-1.315053E 02	-1.310000E 02
7.219999E-01	8.952277E 01	8.953300E 01	-1.453940E 02	-1.450000E 02
1.179999E 00	7.534747E 01	7.531154E 01	-1.570761E 02	-1.570000E 02
1.940000E 00	6.059238E 01	6.089665E 01	-1.654027E 02	-1.650000E 02
3.179999E 00	5.957620E 01	5.957272E 01	-1.702902E 02	-1.700000E 02
5.219999E 00	5.089742E 01	5.090614E 01	-1.720060E 02	-1.720000E 02
8.559999E 00	4.225528E 01	4.227885E 01	-1.708202E 02	-1.710000E 02
1.400000E 01	3.382205E 01	3.378616E 01	-1.669595E 02	-1.670000E 02
2.300000E 01	2.565051E 01	2.566600E 01	-1.602865E 02	-1.600000E 02
3.770000E 01	1.813513E 01	1.813747E 01	-1.514848E 02	-1.510000E 02
6.179999E 01	1.152750E 01	1.152682E 01	-1.430150E 02	-1.430000E 02
1.010000E 02	5.806660E 00	5.800692E 00	-1.391436E 02	-1.390000E 02
1.660000E 02	3.499663E-01	3.491665E-01	-1.434512E 02	-1.430000E 02
2.720000E 02	-5.513681E 00	-5.514433E 00	-1.574466E 02	-1.580000E 02
4.460000E 02	-1.277772E 01	-1.277776E 01	-1.737863E 02	-1.800000E 02
7.320000E 02	-2.192239E 01	-2.191659E 01	-2.051648E 02	-2.050000E 02
1.200000E 03	-3.287621E 01	-3.287945E 01	-2.260611E 02	-2.270000E 02

THE FOURTH TEST OF THE CHARACTERISTIC EQUATION INDICATES
THAT THE SYSTEM IS STABLE

Figure IV-6N



Magnitude Difference vs. Frequency, Double Section Compensator

Figure IV-60



Phase Difference vs. Frequency, Double Section Compensator

Figure IV-6P

5. Compensator Design, Example 5.

This final compensator design example represents a problem of a slightly different nature than those presented to this point. The servo system under consideration here has a zero order hold present in the error channel and in addition, due to the large coefficient values that result in the plant transfer function, the problem requires frequency scaling in order to insure that the numerical limitations of the particular computer that was being used would not be exceeded. The original single loop system is shown in the block diagram of figure IV-7. Series compensation of this system was desired in order to meet the following specifications; 1.) the open loop magnitude at 377 radians/second ≥ 30db, 2.) the gain crossover frequency ≥ 1885 radians/second, and 3.) the phase margin at gain crossover ≥ 45 degrees. These specifications were to be met using only a series compensator and the parameters of that part of the system shown in figure IV-7, other than the compensator, was to remain unchanged. An initial attempt at using the CALICO program to design a compensator resulted in a warning of excessive number size during computation and recommended frequency scaling of the problem. Thus a scale factor of 1000 was selected as a convenient value and the entire system, including the sampling frequency of the zero order hold, was scaled down in frequency by the value of this scale factor. Using Laplace transform notation, this was accomplished by a straight-forward substitution of $s = 1000S$, where S represents the new scaled frequency values. A block diagram showing the values of the system parameters after scaling is given in figure IV-7A. When this type of scaling is performed the resultant numerical values of the program need only be multiplied by the appropriate constant value in order to be corrected for use

in the unscaled system.

Originally, work on this particular system indicated that a fifth order compensator could provide the necessary phase margin and gain crossover frequency, but that the 30 db specification at 377 radians/second was not satisfied. Thus, with this information as a starting point the magnitude profile of the system with the fifth order compensator in the loop was adjusted at the low frequency end to satisfy the 30 db requirement at the scaled frequency value of 0.377 radians/second. The phase profile was left unchanged. The results of the program can be seen in figures IV-7E through IV-7I. As can be seen from the graphical output the desired specifications have been satisfied by the resulting compensated system.



$$G_1 = \frac{558.6}{s(.00125s + 1)}$$

$$G_2 = \frac{4.51638 \times 10^{12}}{(s^2 + 5.0265 \times 10^3 s + 1.01064 \times 10^8)}$$

$$G_5 = 0.5$$

ZOH $T = \frac{1}{1560}$ seconds

Unscaled System Block Diagram
Figure IV-7



$$G_1 = \frac{4.4688 \times 10^{-1}}{S(S + 8.0 \times 10^{-4})}$$

ZOH $T = -\frac{1}{1.560}$ seconds

$$G_2 = \frac{8.085179 \times 10^{3}}{S^2 + 5.02654S + 101.0647}$$

$G_5 = 0.5$

Scaled System Block Diagram
Figure IV-7A



Magnitude vs. Frequency

Figure IV-7B



Phase vs. Frequency

Figure IV-7C



Magnitude vs. Phase
Figure IV-7D

```
      TITLE --- COMPENSATOR OPTIMIZATION TEST RUN 9 SCALED 1000S

      UNCOMPENSATED TRANSFER FUNCTION GAIN =  3.523400E 04

      UNCOMPENSATED TRANSFER FUNCTION NUMERATOR
COEFFICIENTS IN ASCENDING POWERS OF S

   1.000000E 00

      UNCOMPENSATED TRANSFER FUNCTION DENOMINATOR
COEFFICIENTS IN ASCENDING POWERS OF S

   0.0            3.685179E 01    1.050380E 02    5.825546E 00    1.000000E 00

      UNCOMPENSATED TRANSFER FUNCTION DENOMINATOR ROOTS
 ARY:     REAL PART          IMAGINARY PART

          0.0                0.0
         -8.000000E-01       0.0
         -2.513273E 00      -9.733870E 00
         -2.513273E 00       9.733870E 00

      COMPENSATOR TRANSFER FUNCTION GAIN =  1.000000E 00

      COMPENSATOR TRANSFER FUNCTION NUMERATOR
COEFFICIENTS IN ASCENDING POWERS OF S

   1.000000E 00    5.000000E 00    1.000000E 01    1.000000E 01    5.000000E 00
   1.000000E 00
```

Computer Numerical Output
Figure IV-7E

COMPENSATOR TRANSFER FUNCTION NUMERATOR ROOTS

APE:	REAL PART	IMAGINARY PART
	-1.0000000E-00	0.0
	-1.0000000E 00	0.0
	-1.0000000 00	0.0
	-1.0000000 00	0.0
	-1.0000000E-00	0.0

COMPENSATOR TRANSFER FUNCTION DENOMINATOR
COEFFICIENTS IN ASCENDING POWERS OF S

1.0000000E 05 5.0000000E 04 1.0000000E 04 1.0000000E 03 5.0000000E 01
1.0000000E 00

COMPENSATOR TRANSFER FUNCTION DENOMINATOR ROOTS

APE:	REAL PART	IMAGINARY PART
	-1.0000000E 01	0.0
	-1.0000000E 01	0.0
	-1.0000000E-01	0.0
	-1.0000000E 01	0.0
	-1.0000000E 01	0.0

THE COMPENSATOR TRANSFER FUNCTION IS OF THE MINIMUM PHASE TYPE, THEREFORE NO RIGHT HALF PLANE ZEROS WILL BE ALLOWED IN THE SOLUTION FOR THE COMPENSATOR TRANSFER FUNCTION

THE SYSTEM HAS A ZERO ORDER HOLD IN THE LOOP.

THE SAMPLING PERIOD T = 6.4102000E-01 (SECS)

THE SAMPLING FREQUENCY WS = 9.8018630E 00 (RADIANS)

Computer Numerical Output
Figure IV-7F

THE MINIMUM COST FUNCTION VALUE = 2.973146E 00

THE ERROR RETURN CODE FROM BOXPLX = 2

OPTIMIZED COMPENSATOR TRANSFER FUNCTION NUMERATOR COEFFICIENTS IN ASCENDING POWERS OF S

2.144453E-06 3.712168E-00 4.494462E-00 3.196418E-00 8.601346E-01
6.835622E-02

OPTIMIZED COMPENSATOR TRANSFER FUNCTION NUMERATOR ROOTS ARE:

REAL PART	IMAGINARY PART
-7.228979E 00	0.0
-3.735962E-00	0.0
-8.090903E-01	1.164690E 00
-8.090903E-01	-1.164690E 00
-5.776758E-07	0.0

OPTIMIZED COMPENSATOR TRANSFER FUNCTION DENOMINATOR COEFFICIENTS IN ASCENDING POWERS OF S

3.275204E 00 3.180759E 01 6.194180E 02 3.866127E 01 3.137374E-02
1.956992E-03

OPTIMIZED COMPENSATOR TRANSFER FUNCTION DENOMINATOR ROOTS ARE:

REAL PART	IMAGINARY PART
-2.559161E-02	6.813771E-02
-2.559161E-02	-6.813771E-02
-4.581697E-03	1.405507E-02
-4.581697E-03	-1.405507E 02
-1.597125E 01	0.0

OPTIMIZED COMPENSATOR TRANSFER FUNCTION GAIN = 3.492921E 01

Computer Numerical Output
Figure IV-7G



Magnitude Difference vs. Frequency

Figure IV-7H



Phase Difference vs. Frequency

Figure IV-7I

V. SYNTHESIS OF TRANSFER FUNCTIONS FROM FREQUENCY RESPONSE DATA

A. GENERAL DISCUSSION

In the process of running various test problems to exercise and verify the algorithm presented in the preceding chapters, it was found that in addition to its use as a compensator design program, the basic method could also be applied to the synthesis of transfer functions from frequency response data. That is, if the magnitude and phase measurements of some system are obtained it is possible to use the program (CALICO) in order to obtain an approximate linear analytical expression for the transfer function of the system from which the measurements were obtained. This type of problem is quite often encountered in the modeling process of dynamic systems. That is, the engineer may have measured input-output data of the system in the form of a frequency response and is confronted with obtaining a transfer function which will model this system. This may be the result of the process being too complex to be analyzed and the pertinent equations written on the basis of physical laws or the governing physical laws may not be completely understood in the case of systems involving new technologies or reasearch efforts. Quite often the procedure followed in synthesizing or determining an approximate linear transfer function from frequency response data is to construct a Bode plot for the measured data and to fit the measured characteristic with straight line asymptotic approximations where possible and quadratic

factors where sharp peaks in the measured data occur. As in compensator design by classical frequency domain techniques, this procedure for synthesizing transfer functions can involve a considerable amount of time consuming and tedious "cut and try" on the part of the engineer.

The algorithm previously presented is so structured that the use of the program for this type of transfer function synthesis is possible with no modifications to the coding itself. Since the algorithm was not originally developed for the specific purpose of transfer function synthesis there are several precautions that must be taken in order to insure that the transfer function obtained does indeed adequately represent the system from which the measurements were obtained. In particular when using the program in order to synthesize a transfer function, a separate simulation program for time domain response should be used to verify the transfer function obtained. This procedure of checking the time domain response should be followed for any transfer function obtained from frequency response data. The primary concern here is that it is possible to accurately represent the frequency response of some systems, over a finite frequency range, by a transfer function of higher order than the true transfer function, but in some cases the dominant response to standard time domain inputs will be considerably different than that of the actual system. Also, while there is a direct relationship between the time domain and frequency domain responses through the inverse Fourier transform integral, this integration, strictly speaking, is taken over the entire frequency range from $-\infty$ to $+\infty$. In practical applications it is obviously necessary to limit the range of frequencies to be measured to some firite region. If, however, this region is not sufficiently large for a particular system the resulting transfer function obtained from the frequency response data may not accurately describe the system. If this is the

case, it should become readily apparent in a time domain simulation of the equation obtained from the frequency response data. The possible pitfalls in the use of this algorithm to accomplish transfer function synthesis, such as the one just mentioned, will be discussed later when some example problems will also be presented.

A linear time invariant system may be expressed as a ratio of two frequency dependent polynomials of the form

$$H(s) = \frac{a_n s^n + a_{n-1} s^{n-1} + \ldots + a_1 s + a_0}{b_m s^m + b_{m-1} s^{m-1} + \ldots + b_1 s + b_0} = \frac{N(s)}{D(s)}$$

where s is the frequency dependent complex variable of the Laplace transform. Thus the value of this transfer function is dependent upon the value of s and the unknown coefficients of the numerator and denominator. Note that this is analogous to the situation that occurs in the design of a cascade compensator for a unity feedback system with the plant represented by a unity gain block. Thus for the purposes of using the program, if we imagine the measured frequency response data to represent some desired system's open loop frequency response profile, and represent the plant of that system by a constant gain of unity, then the transfer function H(s) to be synthesized may be considered the same as a cascade compensator in the system. Thus by representing the problem in this manner the CALICO program may be used to approximate the transfer function of the actual system by varying the parameters of this pseudo compensator (actually the transfer function of the system) in order to minimize the cost function. The cost function, here represents the error between the measured frequency response data (entered as the desired profile) and the frequency response simulation calculated by the program.

Thus in effect the program minimizes the error between the transfer function approximating the system and the measured frequency response of the system at the discrete frequency points which form the profile input into the program.

As is the case when using the program to design compensators the user must assume a specific order for the numerator and denominator representing, in this case, the transfer function to be synthesized. While unfortunately the program will not vary the order of the numerator and denominator polynomials in order to obtain the best match to the measured frequency response, the user can employ the measured data in order to make an initial guess, as it were, of the form of the transfer function. After this, one may scrutinize the results from the program, which graphs the measured and simulated responses, to make a decision if the form of the transfer function should be adjusted in order to more closely represent the system. Here also, a time domain simulation might be extremely useful in guiding decisions regarding the particular form or modification that should be tried in order to obtain a "good" model for the system under investigation. The fact that the user selects the specific orders of the transfer function numerator and denominator and the minimization routine varies the parameters to obtain a minimum cost function while leaving the orders unchanged presents the potential of obtaining a low order model of a higher order system. While for linear systems, with known transfer functions, there are numerous analytical techniques available for accomplishing this, the capability exists here of essentially obtaining a reduced order transfer function without a priori knowledge of the higher order transfer function describing the system. The only data required by the program is the frequency response of the higher order system and nothing concerning the parameters of the high order transfer function is required.

Since some transfer functions may contain roots of the numerator polynomial in the right half of the s-plane (nonminimum phase systems) this type of transfer function should not be overlooked when attempting to model a system. To this end a nonminimum phase option may be chosen in the CALICO computer algorithm. When this option is selected the search area for the numerator coefficients is expanded to include both positive and negative values and the implicit constraints requiring left half plane roots for the numerator polynomial are eliminated. Selection of this option does not guarantee that a nonminimum phase transfer function will result from the CALICO program but it does allow this type of transfer function to be considered as a feasible solution of the problem.

B. TRANSFER FUNCTION SYNTHESIS: EXAMPLE PROBLEMS

In this section several example problems are presented to illustrate the use of the CALICO program in determining transfer functions from frequency response data. These examples illustrate the validity of the basic concept of using the minimization algorithm to determine the transfer function, but they are by no means an exhaustive presentation of all possible variations of cost functions and frequency ranges that may be employed in determining a transfer function representation of a system. For example, as will be shown in the example problems, different transfer function representations may be obtained by considering different ranges of the measured frequency response. That is, while the order of the numerator and denominator are fixed by the user, the parameter values returned from the program may vary depending upon the frequency range being considered. This may be desirable if seperate low frequency and high frequency representations are being determined.

Also in using the type one cost function, which includes both phase and magnitude, the cost surface is different than if the magnitude difference alone were used in the cost function. This has an effect on the resulting parameter values, particularly when lower order transfer functions are chosen to represent higher order systems.

The necessary data and the input format employed are almost identical to those used when the program functions in its originally designed compensator design mode. Figure V-1 illustrates the input data deck used for the first synthesis example problem. As can be seen the only significant change is that the plant has been represented by a unity gain transfer function. This has the effect that the resulting "compensator" represents the transfer function modeling the entire system.

```
(COLLMN NUMBERS, READ VERTICALLY)
         1111111111222222222233333333344444444445555555555666666666677777777778
12345678901234567890123456789012345678901234567890123456789012345678901234567890
!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!



TRANSFER FUNCTION SYNTHESIS EXAMP 1 20PT
1.0
P00
P00
1.0
P00
F04
1.0
1.0
1.0
1.0
  0.1          30.0      020  1                                  1  1
 0.100E 00 0.135E 00 0.182E 00 0.246E 00 0.332E 00 0.449E 00 0.606E 00 0.818E 00
 0.110E 01 0.149E 01 0.201E 01 0.272E 01 0.367E 01 0.495E 01 0.669E 01 0.903E 01
 0.122E 02 0.165E 02 0.222E 02 0.300E 02
 0.125E 01 0.125E 01 0.123E 01 0.121E 01 0.118E 01 0.112E 01 0.102E 01 0.888E 00
 0.719E 00 0.533E 00 0.359E 00 0.219E 00 0.120E 00 0.594E-01 0.266E-01 0.108E-01
 0.401E-02 0.139E-02 0.458E-03 0.145E-03
-0.103E 02-0.139E 02-0.187E 02-0.251E 02-0.335E 02-0.445E 02-0.584E 02-0.755E 02
-0.955E 02-0.118E 03-0.142E 03-0.167E 03-0.193E 03-0.218E 03-0.242E 03-0.264E 03
-0.284E 03-0.301E 03-0.315E 03-0.326E 03
10000



!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!
         1111111111222222222233333333344444444445555555555666666666677777777778
12345678901234567890123456789012345678901234567890123456789012345678901234567890
(COLUMN NUMBERS, READ VERTICALLY)
```

Transfer Function Synthesis, Data Deck
Figure V-1

1. Synthesis Example 1.

The frequency response data, shown graphically in figure V-2, was generated from a known transfer function using a computer frequency response program. As can be seen, twerty magnitude and phase values were selected at discrete frequencies over the range from 0.1 radians/second to 30 radians/second. Examination of the frequency response data suggests a transfer function of the form of a constant gain over a polynomial of some unknown order. This form will yield a constant magnitude at low frequencies and a decreasing magnitude as the frequency increases. Closer examination of the magnitude curve in the range between 2 and 20 radians/second indicates a slope of approximately 60 db/decade, implying a polynomial of at least third order in the denominator. The phase curve extends from 10 degrees to 330 degrees over the range of frequencies considered. This indicates that the denominator may be of fourth order or higher. As a first guess a third order denominator is assumed. The results from the CALICO program are shown in figure V-2A through V-2H. The initial guess for the denominator roots and the system gain were chosen as 1, as can be seen in figure V-2F. Figures V-2A and V-2D show that the resulting magnitude curve approximates the measured response well at the lower frequencies with a slight deviation begining to appear at the higher frequencies. The phase plot of figure V-2B and the plot of the difference between the actual phase and desired phase shown in figure V-2E indicate a significant amount of deviation from the measured values in the higher frequency region. This suggests that another pole in the transfer function is necessary to more accurately model the system. Thus, the program was again executed, this time using a fourth order denominator. The results illustrated in figures V-2I

through V-2F indicate that this second form of the transfer function more accurately represents the system. Since the original transfer function is known in this case, an opportunity exists to evaluate the performance of the program in terms of the accuracy of the transfer function returned after minimization of the cost function based on the input frequency response data. This of course would generally not be the case when trying to determine the transfer function of an actual system that was to be modeled. The parameter values returned from the CALICO program shown in figure V-20 may be compared with the original transfer function given below.

$$T(s) = \frac{126.0}{(s + 1)(s + 2)(s + 5)(s + 10)}$$

As can be seen, the values of the transfer function roots returned from the program for the fourth order denominator are in agreement with the values of the original transfer function used to generate the frequency response data. If for the system under consideration only the magnitude response were of interest, the transfer function consisting of a constant gain over a third order denominator might be of sufficient accuracy to model the system. This judgement, of course, rests with the user who is familiar with the intended use of the transfer function modeling the system.

Input Frequency Response Data
Figure V-2



Magnitude vs. Frequency, Run #1

Figure V-2A



Phase vs. Frequency, Run #1

Figure V-2B



Magnitude vs. Phase, Run #1
Figure V-2C



Magnitude Difference vs. Frequency, Run #1

Figure V-2D



Phase Difference vs. Frequency, Run #1
Figure V-2E

```
      TITLE --- TRANSFER FUNCTION SYNTHESIS EXAMP 1 20PT
-----------------------------------------------------------------

      UNCOMPENSATED TRANSFER FUNCTION GAIN =  1.000000E 00

      UNCOMPENSATED TRANSFER FUNCTION NUMERATOR
 COEFFICIENTS IN ASCENDING POWERS OF S

    1.CCOOCOE 00

      UNCOMPENSATED TRANSFER FUNCTION DENOMINATOR
 COEFFICIENTS IN ASCENDING POWERS OF S

    1.CCOOCOE 00
-----------------------------------------------------------------

      COMPENSATOR TRANSFER FUNCTION GAIN =  1.000000E 00

      COMPENSATOR TRANSFER FUNCTION NUMERATOR
 COEFFICIENTS IN ASCENDING POWERS OF S

    1.CCOOCOE 00

      COMPENSATOR TRANSFER FUNCTION DENOMINATOR
 COEFFICIENTS IN ASCENDING POWERS OF S

    1.0000000E 00    3.CCC000E 00    3.0000000E 00    1.000000E 00

      COMPENSATOR TRANSFER FUNCTION DENOMINATOR ROOTS
  ARE:      REAL PART          IMAGINARY PART

          -1.0C00000E 00          0.0

          -1.000000E 00           0.0

          -1.0L00CCE 00           0.0
-----------------------------------------------------------------

     THE COMPENSATOR TRANSFER FUNCTION IS OF THE MINIMUM PHASE
 TYPE, THEREFORE NO RIGHT HALF PLANE ZEROS WILL BE ALLOWED IN
 THE SOLUTION FOR THE COMPENSATOR TRANSFER FUNCTION
```

Computer Numerical Output, Run #1

Figure V-2F

THE TOTAL NUMBER OF TRIALS CALLED FOR = 10000

THE COST FUNCTION TO BE USED IS THE TYPE 1

THE MINIMUM COST FUNCTION VALUE = 6.255069E-01

THE ERROR RETURN CODE FROM BOXPLX = 2

OPTIMIZED COMPENSATOR TRANSFER FUNCTION NUMERATOR COEFFICIENTS IN ASCENDING POWERS OF S

2.005749E 05

OPTIMIZED COMPENSATOR TRANSFER FUNCTION DENOMINATOR COEFFICIENTS IN ASCENDING POWERS OF S

1.590744E 05 3.000009E 05 1.352915E 05 3.551281E 04

OPTIMIZED COMPENSATOR TRANSFER FUNCTION DENOMINATOR ROOTS ARE:

REAL PART	IMAGINARY PART
-1.544968E 00	1.958797E 00
-1.544968E 00	-1.958797E 00
-7.197119E-01	0.0

OPTIMIZED COMPENSATOR TRANSFER FUNCTION GAIN = 5.647960E 00

Computer Numerical Output, Run #1

Figure V-2G

FREQUENCY	MAGNITUDE(DB)	DESIRED MAG(DB)	PHASE(DEG)	DESIRED PHASE
9.999996E-02	1.933724E 00	1.938200E 00	-1.075708E 01	-1.030000E 01
1.350000E-01	1.869240E 00	1.938200E 00	-1.446946E 01	-1.390000E 01
1.820000E-01	1.754977E 00	1.798098E 00	-1.938194E 01	-1.870000E 01
2.460000E-01	1.552960E 00	1.655700E 00	-2.590143E 01	-2.509999E 01
3.320000E-01	1.210264E 00	1.457634E 00	-3.239145E 01	-3.350000E 01
4.489999E-01	6.472952E-01	9.843595E-01	-4.493173E 01	-4.450000E 01
6.059999E-01	-2.082647E-01	1.719992E-01	-5.782795E 01	-5.839999E 01
8.180000E-01	-1.417542E 00	-1.031741E 00	-7.312437E 01	-7.550000E 01
1.099999E 00	-2.983166E 00	-2.865421E 00	-9.093784E 01	-9.550000E 01
1.490000E 00	-5.045173E 00	-5.465456E 00	-1.132075E 02	-1.180000E 02
2.009999E 00	-7.919121E 00	-8.881066E 00	-1.409275E 02	-1.420000E 02
2.719999E 00	-1.252182E 01	-1.319112E 01	-1.731349E 02	-1.670000E 02
3.669999E 00	-1.899828E 01	-1.841637E 01	-2.014789E 02	-1.930000E 02
4.950000E 00	-2.648900E 01	-2.452426E 01	-2.218055E 02	-2.180000E 02
6.690000E 00	-3.433565E 01	-3.150235E 01	-2.356471E 02	-2.420000E 02
9.030000E 00	-4.219980E 01	-3.933153E 01	-2.451152E 02	-2.640000E 02
1.220000E 01	-5.008112E 01	-4.793710E 01	-2.518177E 02	-2.840000E 02
1.650000E 01	-5.797523E 01	-5.713969E 01	-2.566531E 02	-3.010000E 02
2.220000E 01	-6.572296E 01	-6.678268E 01	-2.601191E 02	-3.150000E 02
3.000000E 01	-7.357813E 01	-7.677264E 01	-2.627043E 02	-3.260000E 02

THE ROUTH TEST OF THE CHARACTERISTIC EQUATION INDICATES
THAT THE SYSTEM IS STABLE

Computer Numerical Output, Run #1

Figure V-2H



Magnitude vs. Frequency, Run #2

Figure V-2I



Phase vs. Frequency, Run #2

Figure V-2J



Magnitude vs. Phase, Run #2

Figure V-2K



Magnitude Difference vs. Frequency, Run #2

Figure V-2L



Phase Difference vs. Frequency, Run #2

Figure V-2M

```
      TITLE --- TRANSFER FUNCTION SYNTHESIS EXAMP 1 20PT
-------------------------------------------------------------------------------

      UNCOMPENSATED TRANSFER FUNCTION GAIN =  1.000000E 00

      UNCOMPENSATED TRANSFER FUNCTION NUMERATOR
COEFFICIENTS IN ASCENDING POWERS OF S

   1.000000E 00

      UNCOMPENSATED TRANSFER FUNCTION DENOMINATOR
COEFFICIENTS IN ASCENDING POWERS OF S

   1.000000E 00
-------------------------------------------------------------------------------

      COMPENSATOR TRANSFER FUNCTION GAIN =  1.000000E 00

      COMPENSATOR TRANSFER FUNCTION NUMERATOR
COEFFICIENTS IN ASCENDING POWERS OF S

   1.000000E 00

      COMPENSATOR TRANSFER FUNCTION DENOMINATOR
COEFFICIENTS IN ASCENDING POWERS OF S

   1.000000E 00   4.000000E 00   6.000000E 00   4.000000E-00   1.000000E-00

      COMPENSATOR TRANSFER FUNCTION DENOMINATOR ROOTS
 ARE:      REAL PART          IMAGINARY PART

          -1.000000E 00        0.0

          -1.000000E 00        0.0

          -1.000000E 00        0.0

          -1.000000E 00        0.0
-------------------------------------------------------------------------------
-------------------------------------------------------------------------------

    THE COMPENSATOR TRANSFER FUNCTION IS OF THE MINIMUM PHASE
TYPE, THEREFORE NO RIGHT HALF PLANE ZEROS WILL BE ALLOWED IN
THE SOLUTION FOR THE COMPENSATOR TRANSFER FUNCTION
```

Computer Numerical Output, Run #2

Figure V-2N

```
THE TOTAL NUMBER OF TRIALS CALLED FOR = 10000

THE COST FUNCTION TO BE USED IS THE TYPE   1

THE MINIMUM COST FUNCTION VALUE =  1.9110338E-04
THE ERROR RETURN CODE FROM BOXPLX = -1

     OPTIMIZED COMPENSATOR TRANSFER FUNCTION NUMERATOR
COEFFICIENTS IN ASCENDING POWERS OF S

   7.718595E 00

     OPTIMIZED COMPENSATOR TRANSFER FUNCTION DENOMINATOR
COEFFICIENTS IN ASCENDING POWERS OF S

   6.122410E 00    1.103352E 01    5.943789E 00    1.100959E 00    6.122756E-02

     OPTIMIZED COMPENSATOR TRANSFER FUNCTION DENOMINATOR
ROOTS ARE:      REAL PART          IMAGINARY PART

                -9.931983E 00       0.0
                -5.054280E 00       0.0
                -1.998310E 00       0.0
                -9.968116E-01       0.0

     OPTIMIZED COMPENSATOR TRANSFER FUNCTION GAIN =  1.260640E 02
```

Computer Numerical Output, Run #2

Figure V-20

FREQUENCY	MAGNITUDE(DB)	DESIRED MAG(DB)	PHASE(DEG)	DESIRED PHASE
9.999996E-02	1.555822E 00	1.938200E 00	-1.030384E 01	-1.030000E 01
1.350000E-01	1.9C57C4E 00	1.933200E 00	-1.388632E 01	-1.390000E 01
1.820000E-01	1.8226536 00	1.738C93E 00	-1.866319E 01	-1.870000E 01
2.460000E-01	1.677252E 00	1.655700E 00	-2.508612E 01	-2.509999E 01
3.320000E-01	1.413649E 00	1.437634 00	-3.352655E 01	-3.350000E 01
4.489999E-01	9.531442E-01	9.843595E-01	-4.457687E 01	-4.450000E 01
6.059999E-01	1.862C76E-01	1.719992E-01	-5.849570E 01	-5.839999E 01
8.180000E-01	-1.038156E 0C	-1.031741E 00	-7.553554E 01	-7.550000E 01
1.099999E 00	-2.8502C9E 00	-2.865421E 00	-9.524660E 01	-9.550000E 01
1.490000E 00	-5.464C69E C0	-5.465456E 00	-1.178E40E 02	-1.180000E 02
2.009999E 00	-8.881952E 00	-8.891106E 00	-1.419164 02	-1.420000E 02
2.719999E 00	-1.322533E 01	-1.319112E 01	-1.671723E 02	-1.670000E 02
3.669999E 00	-1.842046E 01	-1.841637E 01	-1.925000E 02	-1.930000E 02
4.950000E 00	-2.449834E 01	-2.452426E 01	-2.175242E 02	-2.180000E 02
6.690000E 00	-3.150651E 01	-3.158235E 01	-2.417866E 02	-2.420000E 02
9.030000E 00	-3.933C47E 01	-3.933153E 01	-2.642E20E 02	-2.640000E 02
1.220000E 01	-4.793704E 01	-4.793710E 01	-2.843740E 02	-2.840000E 02
1.650000E 01	-5.719827E 01	-5.713969E 01	-3.015610E 02	-3.010000E 02
2.220000E 01	-6.675203E 01	-6.678268E 01	-3.153562E 02	-3.150000E 02
3.000000E 01	-7.675511E 01	-7.677264E 01	-3.264048E 02	-3.260000E 02

THE ROUTH TEST OF THE CHARACTERISTIC EQUATION INDICATES
THAT THE SYSTEM IS STABLE

Computer Numerical Output, Run #2

Figure V-2P

2. Synthesis Example 2.

As a second synthesis example, consider the frequency response data shown in figure V-3. Here the magnitude and phase response for a system are shown at twenty distinct frequency values over the range from 0.1 to 1000.0 radians/second. As can be seen from this figure the positive slope of 20 db/decade of the magnitude curve at the lower frequencies suggests a transfer function with at least one zero. This is also confirmed by the phase response, which at the lower frequencies initially has a value of 90 degrees. At the higher frequencies inspection of the magnitude plot shows a negative slope of approximately 40 db/decade, indicating the dominance of a third order denominator in this area. The phase plot approaching -180 degrees at these higher frequencies also suggests this. Thus, initially a form for the transfer function consisting of a first order numerator and a third order denominator was selected to model the system from which the frequency response data was obtained. The results are shown in figures V-3A through V-3H. As can be seen from the graphical output presented in the figures, this particular form of transfer function appears to match the measured frequency response quite well over the entire range of frequencies considered. The roots and gain of the transfer function returned from the program are shown in figures V-3G and V-3H. As in the previous example it happens that the exact transfer function used to generate the measured data input to the CAIICO program is known. This transfer function is given below in order that the reader may compare the values of the original transfer function parameters with those returned from the program.

$$T(s) = \frac{9000s}{(s + 2.4)(s + 5)(s + 150)}$$

As can be seen from the data presented in figures V-3G and V-3H, the parameter values returned from the program are in close agreement with the original transfer function values. While it is unlikely that they will ever be exactly the same as the original values there is certainly not a significant difference between the two sets of values for most engineering purposes.



Input Frequency Response Data
Figure V-3



Magnitude vs. Frequency

Figure V-3A



Phase vs. Frequency

Figure V-3B



Magnitude vs. Phase

Figure V-3C



Magnitude Difference vs. Frequency

Figure V-3D



Phase Difference vs. Frequency

Figure V-3E

```
      TITLE --- SYNTHESIS EXAMPLE TWO
-------------------------------------------------------------------

      UNCOMPENSATED TRANSFER FUNCTION GAIN =  1.000000E 00

      UNCOMPENSATED TRANSFER FUNCTION NUMERATOR
 COEFFICIENTS IN ASCENDING POWERS OF S

    1.0000C0E 00

      UNCOMPENSATED TRANSFER FUNCTION DENOMINATOR
 COEFFICIENTS IN ASCENDING POWERS OF S

    1.0000C0E 00
-------------------------------------------------------------------

      COMPENSATOR TRANSFER FUNCTION GAIN =  1.000000E 00

      COMPENSATOR TRANSFER FUNCTION NUMERATOR
 COEFFICIENTS IN ASCENDING POWERS OF S

    1.0000C0E 00     1.CC0CC0E 0C

      COMPENSATOR TRANSFER FUNCTION NUMERATOR ROOTS
  ARE:      REAL PART          IMAGINARY PART

         -1.0CC0C0E 00          0.C

      COMPENSATOR TRANSFER FUNCTION DENOMINATOR
 COEFFICIENTS IN ASCENDING POWERS OF S

    1.C000C0E 00     3.CC0CC0E 00     3.C00000E 00     1.000000E 00

      COMPENSATOR TRANSFER FUNCTION DENOMINATOR ROOTS
  ARE:      REAL PART          IMAGINARY PART

         -1.0CC0C0E 00          0.0

         -1.0C0000E 00          0.C

         -1.0C0C0CE 00          0.0
-------------------------------------------------------------------
```

Computer Numerical Output

Figure V-3F

```
---------------------------------------------------------------------

     THE COMPENSATOR TRANSFER FUNCTION IS OF THE MINIMUM PHASE
TYPE, THEREFORE NO RIGHT HALF PLANE ZEROS WILL BE ALLOWED IN
THE SOLUTION FOR THE COMPENSATOR TRANSFER FUNCTION

---------------------------------------------------------------------
---------------------------------------------------------------------

     THE TOTAL NUMBER OF TRIALS CALLED FOR = 10000

---------------------------------------------------------------------
---------------------------------------------------------------------

     THE COST FUNCTION TO BE USED IS THE TYPE   1

---------------------------------------------------------------------

THE MINIMUM COST FUNCTION VALUE =  1.506277E-04

THE ERROR RETURN CODE FROM BOXPLX =   0

---------------------------------------------------------------------
---------------------------------------------------------------------

     OPTIMIZED COMPENSATOR TRANSFER FUNCTION NUMERATOR
 COEFFICIENTS IN ASCENDING POWERS OF S

   2.618764E 01     2.443936E 05

     OPTIMIZED COMPENSATOR TRANSFER FUNCTION NUMERATOR
  ROOTS ARE:      REAL PART          IMAGINARY PART

               -1.071535E-04          0.0

---------------------------------------------------------------------
```

Computer Numerical Output

Figure V-3G

OPTIMIZED COMPENSATOR TRANSFER FUNCTION DENOMINATOR
COEFFICIENTS IN ASCENDING POWERS OF S

4.891628E 04 3.042503E 04 4.272676E 03 2.710205E 01

OPTIMIZED COMPENSATOR TRANSFER FUNCTION DENOMINATOR

ROOTS ARE:	REAL PART	IMAGINARY PART
	-1.502601E 02	0.0
	-4.978378E 00	0.0
	-2.412790E 00	0.0

OPTIMIZED COMPENSATOR TRANSFER FUNCTION GAIN = 9.017527E 03

FREQUENCY	MAGNITUDE(DB)	DESIRED MAG(DB)	PHASE(DEG)	DESIRED PHASE
9.999996E-02	-6.036484E 00	-6.037990E 00	8.637637E 01	8.639999E 01
1.619999E-01	-1.861110E 00	-1.830299E 00	8.419530E 01	8.420000E 01
2.640000E-01	2.340905E 00	2.345422E 00	8.059622E 01	8.059999E 01
4.280000E-01	6.435040E 00	6.444384E 00	7.484970E 01	7.479999E 01
6.950000E-01	1.031233E 01	1.039656E 01	6.570982E 01	6.570000E 01
1.129999E 00	1.395462E 01	1.394458E 01	5.167982E 01	5.170000E 01
1.830000E 00	1.667714E 01	1.670111E 01	3.193719E 01	3.179999E 01
2.980000E 00	1.810199E 01	1.809430E 01	6.953293E 00	6.980000E 00
4.830000E 00	1.777023E 01	1.775233E 01	-1.943172E 01	-1.950000E 01
7.849999E 00	1.575552E 01	1.579161E 01	-4.352361E 01	-4.350000E 01
1.270000E 01	1.268311E 01	1.264914E 01	-6.266949E 01	-6.279999E 01
2.070000E 01	8.861003E 00	8.845588E 00	-7.767279E 01	-7.770000E 01
3.359999E 01	4.709544E 00	4.710566E 00	-9.006964E 01	-9.009999E 01
5.459999E 01	2.379835E-01	2.557422E-01	-1.022297E 02	-1.020000E 02
8.859999E 01	-4.696572E 00	-4.701540E 00	-1.157497E 02	-1.160000E 02
1.440000E 02	-1.043819E 01	-1.042867E 01	-1.308414E 02	-1.310000E 02
2.340000E 02	-1.716870E 01	-1.713969E 01	-1.454845E 02	-1.450000E 02
3.790000E 02	-2.467876E 01	-2.470154E 01	-1.572561E 02	-1.570000E 02
6.160000E 02	-3.273282E 01	-3.272775E 01	-1.656042E 02	-1.660000E 02
1.000000E 03	-4.099533E 01	-4.101219E 01	-1.710311E 02	-1.710000E 02

THE ROUTH TEST OF THE CHARACTERISTIC EQUATION INDICATES
THAT THE SYSTEM IS STABLE

Computer Numerical Output

Figure V-3H

3. Synthesis Example 3.

A frequency response of a system with resonant peaks, shown in figure V-4, is considered in this example. The same example is considered in ref. 19, where a combination of graphical and analytical techniques are used to determine the transfer function. Initially a transfer function consisting of a first order numerator and second order denominator was assumed in trying to model the system. This choice was based on the low and high frequency magnitude curve slopes of approximately +20 db/decade and -20 db/decade respectively and the low and high frequency phase values of approximately +90 degrees and -90 degrees. This form failed to match the dip in the magnitude curve in the region of 10 radians/second and the jump in the phase curve in the same frequency area. After increasing the order of the numerator and denominator, a transfer function consisting of a third order numerator and fourth order denominator was found to provide a phase and gain curve that closely approximates the measured frequency response. The results of this are shown in figures V-4A through V-4H. The numerical values of the transfer function parameters returned from the program closely approximate those of the actual system from which the frequency response measurements were obtained. The interested reader may verify this fact by comparing the values shown in figures V-4G and V-4E with those of the actual system given in ref. 19.



Input Frequency Response Data

Figure V-4



Magnitude vs. Frequency
Figure V-4A



Phase vs. Frequency

Figure V-4B



Magnitude vs. Phase

Figure V-4C



Magnitude Difference vs. Frequency

Figure V-4D



Phase Difference vs. Frequency

Figure V-4E

```
      TITLE --- SYNTHESIS EXAMPLE THREE 50 PTS
-------------------------------------------------------------------------

      UNCOMPENSATED TRANSFER FUNCTION GAIN =  1.000000E 00

      UNCOMPENSATED TRANSFER FUNCTION NUMERATOR
COEFFICIENTS IN ASCENDING POWERS OF S

    1.000000E 00

      UNCOMPENSATED TRANSFER FUNCTION DENOMINATOR
COEFFICIENTS IN ASCENDING POWERS OF S

    1.000000E 00
-------------------------------------------------------------------------

      COMPENSATOR TRANSFER FUNCTION GAIN =  1.000000E 00

      COMPENSATOR TRANSFER FUNCTION NUMERATOR
COEFFICIENTS IN ASCENDING POWERS OF S

    1.000000E 00    3.000000E 00    3.000000E 00    1.000000E 00

      COMPENSATOR TRANSFER FUNCTION NUMERATOR ROOTS
ARE:      REAL PART          IMAGINARY PART

         -1.000000E 00        0.0

         -1.000000E 00        0.0

         -1.000000E 00        0.0

      COMPENSATOR TRANSFER FUNCTION DENOMINATOR
COEFFICIENTS IN ASCENDING POWERS OF S

    1.000000E 00    4.000000E 00    6.000000E 00    4.000000E 00    1.000000E 00
```

Computer Numerical Output

Figure V-4F

```
      COMPENSATOR TRANSFER FUNCTION DENOMINATOR ROOTS
ARE:      REAL PART          IMAGINARY PART
          -1.000000E 00          0.0
          -1.000000E 00          0.0
          -1.000000E 00          0.0
          -1.000000E 00          0.0
-------------------------------------------------------------------------------
-------------------------------------------------------------------------------

     THE COMPENSATOR TRANSFER FUNCTION IS OF THE MINIMUM PHASE
TYPE, THEREFORE NO RIGHT HALF PLANE ZEROS WILL BE ALLOWED IN
THE SOLUTION FOR THE COMPENSATOR TRANSFER FUNCTION
-------------------------------------------------------------------------------
-------------------------------------------------------------------------------

     THE TOTAL NUMBER OF TRIALS CALLED FOR = 10000
-------------------------------------------------------------------------------
-------------------------------------------------------------------------------

     THE COST FUNCTION TO BE USED IS THE TYPE.. 0
-------------------------------------------------------------------------------

THE MINIMUM COST FUNCTION VALUE =  4.754462E-04

THE ERROR RETURN CODE FROM BOXRLX =  -1
-------------------------------------------------------------------------------
-------------------------------------------------------------------------------

     OPTIMIZED COMPENSATOR TRANSFER FUNCTION NUMERATOR
COEFFICIENTS IN ASCENDING POWERS OF S

   6.788290E 00    2.365316E 05    4.754176E 03    2.362180E 03
```

Computer Numerical Output

Figure V-4G

OPTIMIZED COMPENSATOR TRANSFER FUNCTION NUMERATOR

ROOTS ARE:	REAL PART	IMAGINARY PART
	-1.006292E 00	9.955896E 00
	-1.006292E-00	-9.955896E 00
	-2.869929E-05	0.0

OPTIMIZED COMPENSATOR TRANSFER FUNCTION DENOMINATOR
COEFFICIENTS IN ASCENDING POWERS OF S

4.726638E 04 4.021491E 04 9.944633E 03 8.747952E 02 2.364240E 01

OPTIMIZED COMPENSATOR TRANSFER FUNCTION DENOMINATOR

ROOTS ARE:	REAL PART	IMAGINARY PART
	-1.991656E 01	0.0
	-1.012778E 01	0.0
	-4.956751E 00	0.0
	-1.999504E 00	0.0

OPTIMIZED COMPENSATOR TRANSFER FUNCTION GAIN = 9.991287E 01

THE ROUTH TEST OF THE CHARACTERISTIC EQUATION INDICATES
THAT THE SYSTEM IS STABLE

Computer Numerical Output

Figure V-4H

4. Synthesis Example 4.

In this final example problem a low order approximation to a known higher order system is illustrated. The original system transfer function under consideration consists of a seventh order numerator and an eight order denominator given by

$$\frac{16s^7 + 483s^6 + 6010s^5 + 36380s^4 + 122664s^3 + 222088s^2 + 185760s + 40320}{s^8 + 36s^7 + 546s^6 + 4536s^5 + 22449s^4 + 67284s^3 + 118124s^2 + 109584s + 40320}$$

An analytical method of approximating this high order transfer function is discussed in ref. 21. Initially 40 discrete points, representing the frequency response of the high order transfer function were selected over the frequency range from 0.01 radians/second to 100.0 radians/second. In order to be able to form a comparison with the reduced order model obtained in ref. 21, a transfer function consisting of a first order numerator and a second order denominator was assumed. The results returned from the program using this form of transfer function are shown in figures V-5A through V-5H. It is not surprising that there is a significant amount of deviation in the magnitude curve in the vicinity of the resonant effects of the higher order system nor that the phase response of this reduced order model does not match the higher order phase response in the higher frequency range. In order to compare these results with analytical methods for forming reduced order models, the frequency response for the reduced order model of ref. 21 is shown in figures V-5I through V-5M. The numerical values returned from the CALICO program are of the same order of magnitude as those found by the analytical technique, but as can be seen from the magnitude curves of

the two approaches (figuresV-5A and V-5I), the analytical method matches the higher order transfer function extremely well at the lower and higher frequencies and makes little attempt to match the higher order system in the range of frequencies at which the resonant peaks occur. The results returned from the program, on the other hand because they are a function of the deviation of the response from the desired values over the entire range of frequencies, tend to distribute any error between the responses over the entire range of frequencies being considered. A slightly different representation of the system may be obtained by varying the frequency range under consideration and the type of cost function used in the program. For example, figures V-5N through V-5U illustrate the effects of using a type two cost function and limiting the frequency range from 0.1 to 100.0 radians/second. Again the decision as to which model is best must be made by the user in light of the intended use of the reduced order representation.



Magnitude vs. Frequency, Run #1

Figure V-5A



Phase vs. Frequency, Run #1

Figure V-5B



Magnitude vs. Phase, Run #1

Figure V-5C



Magnitude Difference vs. Frequency, Run #1

Figure V-5D



Phase Difference vs. Frequency, Run #1

Figure V-5E

```
      TITLE --- LOW ORD APPROX EXAMP 40PTS
-------------------------------------------------------------------------

      UNCOMPENSATED TRANSFER FUNCTION GAIN =  1.000000E 00

      UNCOMPENSATED TRANSFER FUNCTION NUMERATOR
COEFFICIENTS IN ASCENDING POWERS OF S

    1.000000E 00

      UNCOMPENSATED TRANSFER FUNCTION DENOMINATOR
COEFFICIENTS IN ASCENDING POWERS OF S

    1.000000E 00
-------------------------------------------------------------------------

      COMPENSATOR TRANSFER FUNCTION GAIN =  1.000000E 00

      COMPENSATOR TRANSFER FUNCTION NUMERATOR
COEFFICIENTS IN ASCENDING POWERS OF S

    1.000000E 00    1.000000E 00

      COMPENSATOR TRANSFER FUNCTION NUMERATOR ROOTS
ARE:      REAL PART          IMAGINARY PART

         -1.000000E 00        0.0

      COMPENSATOR TRANSFER FUNCTION DENOMINATOR
COEFFICIENTS IN ASCENDING POWERS OF S

    1.000000E 00    2.000000E 00    1.000000E 00

      COMPENSATOR TRANSFER FUNCTION DENOMINATOR ROOTS
ARE:      REAL PART          IMAGINARY PART

         -1.000000E 00        0.0

         -1.000000E 00        0.0
-------------------------------------------------------------------------
```

Computer Numerical Output, Run #1
Figure V-5F

THE COMPENSATOR TRANSFER FUNCTION IS OF THE MINIMUM PHASE TYPE, THEREFORE NO RIGHT HALF PLANE ZEROS WILL BE ALLOWED IN THE SOLUTION FOR THE COMPENSATOR TRANSFER FUNCTION

THE TOTAL NUMBER OF TRIALS CALLED FOR = 10000

THE COST FUNCTION TO BE USED IS THE TYPE 1

THE MINIMUM COST FUNCTION VALUE = 1.321693E 01

THE ERROR RETURN CODE FROM BOXFLX = 0

OPTIMIZED COMPENSATOR TRANSFER FUNCTION NUMERATOR COEFFICIENTS IN ASCENDING POWERS OF S

2.146659E 05 6.417439E 05

OPTIMIZED COMPENSATOR TRANSFER FUNCTION NUMERATOR ROOTS ARE:

REAL PART	IMAGINARY PART
-3.348156E-01	0.0

OPTIMIZED COMPENSATOR TRANSFER FUNCTION DENOMINATOR COEFFICIENTS IN ASCENDING POWERS OF S

1.876209E 05 1.869405E 05 5.706169E 04

OPTIMIZED COMPENSATOR TRANSFER FUNCTION DENOMINATOR ROOTS ARE:

REAL PART	IMAGINARY PART
-1.638056E 00	7.776945E-01
-1.638056E 00	-7.776945E-01

Computer Numerical Output, Run #1
Figure V-5G

OPTIMIZED COMPENSATOR TRANSFER FUNCTION GAIN = 1.124649E 01

FREQUENCY	MAGNITUCE(DB)	DESIRED MAG(DB)	PHASE(DEG)	DESIRED PHASE
9.999998E-03	1.181429E 00	0.0	1.139874E 00	1.080000E 00
1.270000E-02	1.183669E 00	0.0	1.447248E 00	1.370000E 00
1.600000E-02	1.187197E 00	0.0	1.822537E 00	1.730000E 00
2.030000E-02	1.192967E 00	0.0	2.310744E 00	2.190000E 00
2.570000E-02	1.202132E 00	0.0	2.922201E 00	2.770000E 00
3.260000E-02	1.216921E 00	0.0	3.700172E 00	3.509999E 00
4.120000E-02	1.240154E 00	8.642113E-02	4.663218E 00	4.429999E 00
5.220000E-02	1.277468E 00	8.642113E-02	5.881681E 00	5.580000E 00
6.609994E-02	1.336473E 00	1.719992E-01	7.394758E 00	7.000000E 00
8.379996E-02	1.425868E 00	2.567422E-01	9.268644E 00	8.750000E 00
1.059999E-01	1.573788E 00	4.237797E-01	1.151788E 01	1.090000E 01
1.339999E-01	1.792952E 00	5.876731E-01	1.416620E 01	1.380000E 01
1.700000E-01	2.125519E 00	9.064573E-01	1.722145E 01	1.609999E 01
2.150000E-01	2.595750E 00	1.363709E 00	2.044739E 01	1.889999E 01
2.729999E-01	3.266556E 00	2.007405E 00	2.364001E 01	2.170000E 01
3.460000E-01	4.132125E 00	2.797576E 00	2.625536E 01	2.389999E 01
4.380000E-01	5.186727E 00	3.750413E 00	2.773952E 01	2.529999E 01
5.540000E-01	6.385768E 00	4.810984E 00	2.751895E 01	2.559999E 01
7.020000E-01	7.663657E 00	6.063919E 00	2.505437E 01	2.459999E 01
8.890000E-01	8.955056E 00	7.531536E 00	1.997882E 01	2.159999E 01
1.129999E 00	9.955495E 00	9.277854E 00	1.200836E 01	1.470000E 01
1.429999E 00	1.064944E 01	1.110188E 01	1.683441E 00	1.549999E 00
1.799999E 00	1.066059E 01	1.254731E 01	-1.007033E 01	-1.979999E 01
2.290000E 00	1.051939E 01	1.304492E 01	-2.293156E 01	-5.000000E 01
2.899999E 00	9.678394E 00	1.214909E 01	-3.474916E 01	-9.039999E 01
3.669999E 00	8.401459E 00	9.635990E 00	-4.546928E 01	-1.450000E 02
4.639999E 00	6.861783E 00	7.676304E 00	-5.432191E 01	-2.210000E 02
5.879999E 00	5.118869E 00	8.530223E 00	-6.163776E 01	-2.930000E 02
7.440000E 00	3.268962E 00	9.127317E 00	-6.749031E 01	-3.430000E 02
9.429999E 00	1.331501E 00	8.130801E 00	-7.219646E 01	-3.800000E 02
1.190000E 01	-6.150827E-01	5.889321E 00	-7.587126E 01	-4.070000E 02
1.510000E 01	-2.626412E 00	2.984381E 00	-7.895545E 01	-4.240000E 02
1.909999E 01	-4.648530E 00	-4.353984E-02	-8.118462E 01	-4.340000E 02
2.420000E 01	-6.685574E 00	-2.865421E 00	-8.304007E 01	-4.390000E 02
3.070000E 01	-8.741075E 00	-5.352125E 00	-8.451234E 01	-4.420000E 02
3.889999E 01	-1.079027E 01	-7.618134E 00	-8.566870E 01	-4.430000E 02
4.920000E 01	-1.282622E 01	-9.762332E 00	-8.657521E 01	-4.440000E 02
6.239999E 01	-1.488786E 01	-1.183520E 01	-8.729959E 01	-4.450000E 02
7.900000E 01	-1.693501E 01	-1.389297E 01	-8.786689E 01	-4.460000E 02
1.000000E 02	-1.898141E 01	-1.591760E 01	-8.831483E 01	-4.470000E 02

THE ROUTH TEST OF THE CHARACTERISTIC EQUATION INDICATES
THAT THE SYSTEM IS STABLE

Computer Numerical Output, Run #1
Figure V-5H



Magnitude vs. Frequency, Analytical Transfer Function

Figure V-5I



Phase vs. Frequency, Analytical Transfer Function

Figure V-5J



Magnitude vs. Phase, Analytical Transfer Function

Figure V-5K



Magnitude Difference vs. Frequency, Analytical Transfer Function

Figure V-5L



Phase Difference vs. Frequency, Analytical Transfer Function

Figure V-5M



Magnitude vs. Frequency, Run #2

Figure V-5N



Phase vs. Frequency, Run #2

Figure V-50



Magnitude vs. Phase, Run #2

Figure V-5P



Magnitude Difference vs. Frequency, Run #2

Figure V-5Q



Phase Difference vs. Frequency, Run #2

Figure V-5R

```
      TITLE --- LOW ORD APPROX EXAMP 3RDTS
-------------------------------------------------------------------------

      UNCOMPENSATED TRANSFER FUNCTION GAIN =  1.000000E 00

      UNCOMPENSATED TRANSFER FUNCTION NUMERATOR
 COEFFICIENTS IN ASCENDING POWERS OF S

    1.000000E 00

      UNCOMPENSATED TRANSFER FUNCTION DENOMINATOR
 COEFFICIENTS IN ASCENDING POWERS OF S

    1.000000E 00
-------------------------------------------------------------------------

      COMPENSATOR TRANSFER FUNCTION GAIN =  1.000000E 00

      COMPENSATOR TRANSFER FUNCTION NUMERATOR
 COEFFICIENTS IN ASCENDING POWERS OF S

    1.000000E 00    1.000000E 00

      COMPENSATOR TRANSFER FUNCTION NUMERATOR ROOTS
 ARE:       REAL PART              IMAGINARY PART

         -1.000000E 00              0.0

      COMPENSATOR TRANSFER FUNCTION DENOMINATOR
 COEFFICIENTS IN ASCENDING POWERS OF S

    1.000000E 00    2.000000E 00    1.000000E 00

      COMPENSATOR TRANSFER FUNCTION DENOMINATOR ROOTS
 ARE:       REAL PART              IMAGINARY PART

         -1.000000E 00              0.0

         -1.000000E 00              0.0
-------------------------------------------------------------------------
```

Computer Numerical Output, Run #2

Figure V-5S

```
     THE COMPENSATOR TRANSFER FUNCTION IS OF THE MINIMUM PHASE
TYPE, THEREFORE NO RIGHT HALF PLANE ZEROS WILL BE ALLOWED IN
THE SOLUTION FOR THE COMPENSATOR TRANSFER FUNCTION

-------------------------------------------------------------------------------
-------------------------------------------------------------------------------

     THE TOTAL NUMBER OF TRIALS CALLED FOR = 10000

-------------------------------------------------------------------------------
-------------------------------------------------------------------------------

     THE COST FUNCTION TO BE USED IS THE TYPE   2

-------------------------------------------------------------------------------

THE MINIMUM COST FUNCTION VALUE =  4.723737E-01

THE ERROR RETURN CODE FROM BCXFLX =   2

-------------------------------------------------------------------------------
-------------------------------------------------------------------------------

     OPTIMIZED COMPENSATOR TRANSFER FUNCTION NUMERATOR
COEFFICIENTS IN ASCENDING POWERS OF S

   3.427296E 05     9.702700E 05

     OPTIMIZED COMPENSATOR TRANSFER FUNCTION NUMERATOR
 ROOTS ARE:      REAL PART          IMAGINARY PART

               -3.532414E-01          0.0
-------------------------------------------------------------------------------

     OPTIMIZED COMPENSATOR TRANSFER FUNCTION DENOMINATOR
COEFFICIENTS IN ASCENDING POWERS OF S

   3.429794E 05     2.906541E 05     5.576810E 04

     OPTIMIZED COMPENSATOR TRANSFER FUNCTION DENOMINATOR
 ROOTS ARE:      REAL PART          IMAGINARY PART

               -2.241913E 00          1.060160E 00

               -2.241913E 00         -1.060160E 00
-------------------------------------------------------------------------------
```

Computer Numerical Output, Run #2

Figure V-5T

OPTIMIZED COMPENSATOR TRANSFER FUNCTION GAIN = 1.7398325 01

FREQUENCY	MAGNITUDE(DB)	DESIRED MAG(DB)	PHASE(DEG)	DESIRED PHASE
9.999999E-02	3.197853E-01	3.416665E-01	1.162579E 01	1.333333E 01
1.270000E-01	5.074022E-01	5.876731E-01	1.447106E 01	1.270000E 01
1.610000E-01	7.943212E-01	8.278436E-01	1.777969E 01	1.533333E 01
2.040000E-01	1.206514E 00	1.208516E 00	2.149046E 01	1.833333E 01
2.589999E-01	1.812137E 00	1.858431E 00	2.544092E 01	2.100000E 01
3.290000E-01	2.669186E 00	2.606677E 00	2.924418E 01	2.366667E 01
4.180000E-01	3.639215E 00	3.521825E 00	3.285130E 01	2.633333E 01
5.300000E-01	4.801715E 00	4.608976E 00	3.627591E 01	2.900000E 01
6.720000E-01	6.231117E 00	5.800662E 00	3.946308E 01	3.166667E 01
8.530000E-01	7.678854E 00	7.272227E 00	4.230791E 01	3.433333E 01
1.080000E 00	9.681695E 00	9.004979E 00	4.477144E 01	3.700000E 01
1.370000E 00	1.034261E 01	1.083156E 01	2.036575E 01	4.000000E 01
1.740000E 00	1.137931E 01	1.238186E 01	1.033685E 01	-1.000000E 01
2.209999E 00	1.101641E 01	1.304493E 01	-1.800449E 00	-4.529999E 01
2.809999E 00	1.176266E 01	1.236096E 01	-1.505461E 01	-8.450000E 01
3.559999E 00	1.114854E 01	1.004354E 01	-2.789554E 01	-1.230000E 02
4.520000E 00	1.005291E 01	7.747795E 00	-3.963762E 01	-1.620000E 02
5.740000E 00	8.604420E 00	8.399112E 00	-4.567783E 01	-2.010000E 02
7.280000E 00	6.930445E 00	9.127317E 00	-5.791054E 01	-2.400000E 02
9.240000E 00	5.102574E 00	8.265952E 00	-6.455826E 01	-2.790000E 02
1.170000E 01	3.201303E 00	6.107025E 00	-6.986574E 01	-3.180000E 02
1.490000E 01	1.199599E 00	3.227356E 00	-7.416071E 01	-3.570000E 02
1.889999E 01	-8.126724E-01	1.719992E-01	-7.749542E 01	-3.960000E 02
2.400000E 01	-2.852705E 00	-2.721653E 00	-8.014937E 01	-4.350000E 02
3.029999E 01	-4.883443E 00	-5.256147E 00	-8.222666E 01	-4.740000E 02
3.859999E 01	-6.943999E 00	-7.535015E 00	-8.387128E 01	-5.130000E 02
4.889999E 01	-8.999788E 00	-9.735044E 00	-8.516147E 01	-5.520000E 02
6.209999E 01	-1.106022E 01	-1.180122E 01	-8.618961E 01	-5.910000E 02
7.879999E 01	-1.312514E 01	-1.385009E 01	-8.699653E 01	-6.300000E 02
1.000000E 02	-1.519218E 01	-1.591760E 01	-8.763351E 01	-6.690000E 02

THE ROUTH TEST OF THE CHARACTERISTIC EQUATION INDICATES
THAT THE SYSTEM IS STABLE

Computer Numerical Output, Run #2
Figure V-5U

VI. CONCLUSION AND SUGGESTED FUTURE STUDIES

The investigations carried out in this thesis illustrate the feasibility of automating the classical design of compensators by specifying a set of desired values for the magnitude and phase response of the open loop system at a number of discrete frequency values over the range of interest. The results achieved show that the complex minimization method of M. J. Box is quite capable of handling the constrained minimization problem and conveniently provides a means of avoiding the numerical differentiation of the cost function, required with gradient search techniques. The incorporation of stability criterion in the implicit constraints of the minimization algorithm also insures that the program will not design an unstable compensator. By specifying the desired response in terms of the magnitude and phase profiles, common frequency domain specifications such as open loop bandwidth, phase margin, and gain margin have been incorporated into one common format and the necessity for specialized routines to check these specifications have been avoided. Those example problems presented for which known results had been established by other techniques show that the algorithm presented provides accuracy that is certainly within the necessary tolerances for most engineering applications of compensator design.

Also, while not specifically designed for the purpose, the basic premise of the algorithm's minimizing the difference between some desired frequency response and the frequency response of the system as calculated by the computer program while the transfer function parameters are

varied has been shown to be effective in both determining a transfer function from measured frequency response data and in forming low order models of known higher order linear systems. In the formulation of low order models the choice of cost function and the frequency range specified may be used to emphasize different aspects of the frequency response which the low order model is to approximate.

While this work has shown that the basic algorithm presented can be used to effectively design series compensators based on frequency response specifications, considerable work remains to be done in this area. Specifically, an option to select that only real poles and zeros be considered as viable solutions to the compensator design algorithm would not be a difficult addition to the program and should prove quite useful. Also, the incorporation of a provision for handling pure time delays would not require significant modification of the program coding and would extend the capability of the algorithm to the solution of problems involving transport delays. Investigation of the method presented should be further pursued in terms of multiloop systems and systems involving compensation in the feedback loop. It may also prove worthwhile to investigate extending this method to nonlinear components using describing function techniques.

In the areas of transfer function synthesis and reduced order modeling, a more detailed investigation of both the effects of different cost functions and considering different frequency ranges should be conducted. In addition, it appears feasible to weight the cost function over a particular frequency range by varying the density of the discrete frequencies at which the desired magnitude and phase profiles are specified. Time did not permit a detailed investigation of this idea and further investigation into this area may be applicable to the

program utilization in both the areas of compensator design and transfer function synthesis.

APPENDIX A

DESCRIPTION OF SUBROUTINES

In this section a brief description and backgrourd of various subroutines is presented to aid the interested reader in better understanding the internal logic of the prcgram. Also these descriptions are intended to facilitate the task of anycne desiring to make mcdificatiors or additions tc the program in order to handle systems cf a configuratien cther than the unity feedback form assumed thrcughout this work.

SUBROUTINE CONORM

The purpose of this subroutine sub-program is to normalize the coefficient of the highest order term to unity. This is accomplished in a simple, straight forward manner by dividing all the coefficients of the polynomial by the coefficient of the highest order term. Thus a polynomial given by

$$P(s) = \sum_{i=0}^{n} a_i \cdot s^i$$

becomes on return from this subroutine

$$P(s) = \sum_{i=0}^{n} \frac{a_i}{a_n} \cdot s^i$$

where a_n is the coefficient of the s^n term. The normalizing factor a_n is also returned to the calling program.

It should be noted that the coefficients of the normalized polynomial are returned under the same variable name as the input coefficients.

Definitions of the input and output parameters are:

Input Variables

V ---------- A real one-dimensional array containing the coefficients of the polynomial whose highest order coefficient is to be normalized to unity. Upon return from the subroutine this array will contain the normalized coefficients of the polynomial.

N ---------- The dimension of the array containing the coefficients to be normalized.

VNORM ------- The normalizing factor, returned to the calling program, by which all coefficients have been divided.

SUBROUTINE PHASE

This subroutine sub-program is used to calculate the phase angle of a polynomial at a particular frequency. In order to circumvent the difficulty associated with standard arctangent routines, which return values limited to the range $-\pi \leq \theta \geq \pi$, the phase contributions from the individual factors are calculated and then summed to form the total phase angle at a particular frequency. That is, if the polynomial is factored and represented as the product of first order terms of the form

$$P(s) = \prod_{i=0}^{n} (s + z_i)$$

where in general z_i may be a complex number of the form $z_i = a_i + jb_i$, then at a particular frequency $s = j\omega$ the phase contribution of the individual factors may be evaluated as

$$\phi_i = \tan^{-1} \frac{(b_i + \omega)}{a_i}$$

and the total phase angle at the particular frequency is the sum of these individual phase contributions. The phase contribution of each of these first order terms will be within the principal values of the arctangent routine of the computer and the problems generally associated with determination of the phase for higher than first order terms are avoided.

Definitions of the input and output parameters are:

Input Variables

RR ---------- A real one-dimensional array containing the real parts of the roots of the polynomial.

RI ---------- A real one-dimensional array containing the imaginary parts of the roots of the polynomial.

N ---------- An integer value specifying the number of roots of the polynomial.

OMEGA ------- The frequency in radians/sec at which the value of the phase is to be computed.

Output Variables

TANGD ------- The total phase contribution of the polynomial given in degrees.

SUBROUTINE PINVRT

The purpose of this subroutine sub-program is to rearrange the coefficients of a polynomial in inverse order from that fed into the subroutine. Consider for example a polynomial arranged in descending powers of s

$$P(s) = a_n s^n + a_{n-1} s^{n-1} + \ldots + a_1 s + a_0$$

Upon return from this subroutine the coefficients would be arranged in ascending powers of s. That is the polynomial would be arranged as follows

$$P(s) = a_0 + a_1 s + \ldots + a_{n-1} s^{n-1} + a_n s^n$$

While both representations are mathematically equivalent the sequence of the coefficients must be taken into account when using various polynomial manipulation techniques within the computer. The method used in reversing the sequence of the input coefficients consists of temporarily storing the first coefficient and sequentially shifting the remaining coefficients. The coefficient in temporary storage is then placed in the last coefficient location. This process is continued with the use of nested do loops and each time the shifting operation occurs the coefficient in temporary storage is placed one location lower than the previous number retrieved from temporary storage.

This subroutine requires no other subroutines or functions to carray out the procedure. The size of the one dimensional array of coefficients that may be rearranged is determined by the dimension of the array in the calling program.

Definitions of the input and output parameters are:

Input Variables

X(I) -------- A real one dimensional array containing the coefficients to be rearranged. Upon return from the subroutine this array contains the input coefficients in reverse sequence from that entered.

N ---------- The dimension of the array containing the coefficients to be rearranged.

SUBROUTINE PMPY

The purpose of this subroutine sub-program is to multiply the coefficients of one polynomial X(s) times the coefficients of another polynomial Y(s) to obtain the coefficients of the resulting polynomial Z(s). That is, if it is desired to multiply two polynomials of the form

$$P_1(s) = a_0 + a_1 s + a_2 s^2 + \ldots + a_{n-1} s^{n-1} + a_n s^n$$

and

$$P_2(s) = b_0 + b_1 s + b_2 s^2 + \ldots + b_{m-1} s^{m-1} + b_m s^m$$

together in order to obtain a third resultant polynomial of the general form

$$P_3(s) = c_0 + c_1 s + c_2 s^2 + \ldots + c_{i-1} s^{i-1} + c_i s^i$$

this subroutine is used in accomplishing this. The order of the resulting polynomial is calculated by forming the sum of the orders of the two input polynomials as

$$i = n + m$$

The various coefficients of the resulting polynomial, which are returned in ascending powers of the independent variable, are calculated as the sums of products of the input coefficients by means of two nested do-loops. The arrangement of the two do-loops is such that the appropriate product terms are summed in forming the respective coefficients of the resultant polynomial. All input and output coefficients must be real numbers. The size of the polynomials that may be multiplied are controlled by their respective dimension statements within the calling program.

Definitions of the input and output parameters are:

Input Variables

X ---------- A real one dimensional array containing the coefficients of the first polynomial to be multiplied. These must be arranged in ascending powers of the independent variable.

IDIMX ------- The dimension of the array X containing the coefficients of the first polynomial.

Y ---------- A real one dimensional array containing the coefficients of the second polynomial to be multiplied. These must be arranged in ascending powers of the independent variable.

IDIMY ------- The dimension of the array Y containing the coefficients of the second polynomial.

Output Variables

Z ---------- A real one dimensional array containing the coefficients of the resultant polynomial. These coefficients are arranged in ascending powers of the independent variable.

IDIMZ ------- The calculated dimension of the array Z containing the coefficients of the resultant polynomial.

SUBROUTINE PVAL

The purpose of this subroutine sub-program is to evaluate a polynomial having the complex variable $s = \sigma + j\omega$ and real coefficients a_i. For a given polynomial of order n of the form

$$P(s) = \sum_{i=0}^{n} a_i \cdot s^i$$

s is declared as a complex variable within the subroutine and the indicated operations of summation and multiplication are carried out by a simple loop operation taking advantage of the associative and distributive laws of multiplication and addition. This subroutine requires no other sub-programs to perform its function.

Definitions of the input and output parameters are:

Input Variables

A(I) -------- A real one-dimensional array containing the coefficients of the polynomial that is to be evaluated. The coefficients are assumed to be arranged in ascending order according to the powers of s with zero explicitly input for the coefficient of any missing powers of s occuring in the polynomial. The maximum size of this array is controlled by the dimension of the array within the main program. The values of the coefficients in this array remain unchanged after execution of the subroutine.

NN ---------- The order of the polynomial tc be evaluated. This value is one less than the dimension of A(I).

PR ---------- The value of the real part cf the ccmplex variable s at which the polyncmial is to be evaluated.

PI ---------- The value of the imaginary part cf the ccmplex variable s at which the polynomial is to be evaluated.

Output Variables

VR ---------- The real part of the complex resultant value of the polynomial evaluated at $s = \sigma + j\omega$.

VI ---------- The imaginary part of the complex resultant value cf the polynomial evaluated at $s = \sigma + j\omega$.

SUBROUTINE ROUTH

The purpose of this subroutine sub-program is to determine if a given input polynomial possesses right half plane roots by using the Routh stability criterion. The polynomial coefficients are input in descending powers of the independent variable. From these coefficients the Routh array is calculated and the first column of this array is searched for an indication of the existence of right half plane roots. Thus from an input polynomial of the form

$$F(s) = b_n s^n + b_{n-1} s^{n-1} + \ldots + b_1 s + b_0$$

the Routh array

1^{st} row	b_n	b_{n-2}	b_{n-4} .....
2^{nd} row	b_{n-1}	b_{n-3}	b_{n-5} .....
3^{rd} row	a_{31}	a_{32}	a_{33} .....
4^{th} row	a_{41}	a_{42}	a_{43} .....
	.	.	.
	.	.	.
	.	.	.
	.	.	.
	.	.	.
	.	.	.
	.	.	.
n^{th} row	a_{n1}	a_{n2}	a_{n3} .....
$(n+1)^{st}$ row	$a_{(n+1)1}$	$a_{(n+1)2}$	$a_{(n+1)3}$ ...

is formed, where in general the entries from the third row onward are given by

$$a_{ri} = \frac{\left[a_{(n-1)\,1}\right]\left[a_{(n-2)\,(i+1)}\right] - \left[a_{(n-2)\,1}\right]\left[a_{(n-1)\,(i+1)}\right]}{a_{(n-1)\,1}}$$

The first column of this array is then tested to determine if any of the elements are less than zero. Note that since all coefficients are limited to positive values by the search area restrictions in other parts of the program no provision has been made to handle the case of the coefficients of the polynomial being all negative. Thus a polynomial with all negative coefficients should be multiplied by -1.0 prior to using this particular subroutine for testing for right half plane roots.

Definitions of input and output parameters are:

Input Variables

Y ---------- A real one dimensional array containing the coefficients of the polynomial in descending powers of the independent variable.

N ---------- The dimension of the array Y.

Output Variables

ISTABL ------ Integer output indicating the absence or presence of right half plane roots

0---Indicates the polynomial has no right half plane roots.

1---Indicates the polynomial has right half plane roots.

SUBROUTINE SEMEL

The purpose of this subroutine sub-program is to calculate the coefficients of a polynomial from the roots of the polynomial. The calculation is done using complex arithmetic in order to be able to compute the polynomial coefficients when complex roots are present. The resulting polynomial coefficients are, however assumed to be real. Thus, if complex roots are present they must be in conjugate pairs. Also the coefficient of the highest order term is set equal to unity. Consider a polynomial of degree n having n roots. This may be expressed as

$$P(s) = \prod_{i=0}^{n} (s + z_i)$$

where in general the z_i's may be complex. The coefficients of the polynomial that results when the above indicated multiplication is performed may be computed by the formula

$$A_i = (-1)^{n-i} \cdot \sum (\text{product of roots taken n-i at a time})$$

Thus the coefficients of the polynomial are given by

$$a_0 = z_1 \cdot z_2 \cdot z_3 \cdot z_4 \cdot \ldots \cdot z_n$$

$$a_1 = z_1 \cdot z_2 \cdot z_3 \cdot \ldots \cdot z_{n-1} + z_2 \cdot z_3 \cdot z_4 \cdot \ldots \cdot z_n$$

$$\vdots$$

$$a_{n-1} = z_1 + z_2 + z_3 + z_4 + z_5 + \ldots + z_n$$

$$a_n = 1$$

The largest order polynomial that this particular subroutine will handle is a 20^{th} order. If larger polynomials are to be considered the dimension of R within the subroutine must be changed.

Definitions of the input and output parameters are:

Input Variables

RR ---------- A real one-dimensional array containing the real parts of the polynomial roots.

RI ---------- A real one-dimensional array containing the imaginary parts of the polynomial roots.

N ---------- An integer specifying the order of the polynomial or equivalently the dimension of the arrays containing the real and imaginary parts of the roots.

Output Variables

CF ---------- A real one-dimensional array containing the

resulting coefficients of the polynomial arranged in ascending powers of the independent variable. The dimension of this array must be one larger than the dimensions of the arrays containing the real and imaginary parts of the roots.

APPENDIX B

PROGRAM LISTING

```
C COMPUTER AIDED COMPENSATOR OPTIMIZATION PROGRAM                                MAIN  10
C                                                                                MAIN  20
C                                                                                MAIN  30
      REAL *4NTITLE                                                              MAIN  40
      DIMENSION CO(20), RTR(20), RTI(20), X(24), C(12), D(12), CCF(20),          MAIN  50
     1XS(24), XL(27), XU(24)                                                     MAIN  60
      COMMON NCN,NCD,NTFN,NTFD,NOMEG,A(20),B(20),CMAG(500),DOPHSD(500),WMAIN  70
     1FREQ(500),NSN,NSD,COFASN(40),COFASD(40),QMAG(500),QR(500),QI(500),MAIN  80
     2QPHSR(500),QPHSD(500),N1,N2,N3,N4,PI,T,WS,IZCF,ADMAG(500),NTITLE(1MAIN  90
     32),FREQ(500),AMAG(500),NMINFS,COFWRK(40),IPLOT,WFREQS(500),SAPHSD(MAIN 100
     45C0),SAMAG(500),DIFF1(500),DIFF2(500),ICOST,CFWRK1(40)                     MAIN 110
      DATA IPP/1HP/                                                              MAIN 120
      PI = 3.1415926                                                             MAIN 130
      PHICHK = 0.0                                                               MAIN 140
      IDELNU = 0                                                                 MAIN 150
      IDELDE = 0                                                                 MAIN 160
      PHI = 0.0                                                                  MAIN 170
      IPHI = 0                                                                   MAIN 180
      PSICHK = 0.0                                                               MAIN 190
      PSI = 0.0                                                                  MAIN 200
      IPSI = 0                                                                   MAIN 210
      IEREXP = 0                                                                 MAIN 220
C                                                                                MAIN 230
CC  READ IN PROBLEM TITLE                                                        MAIN 240
C                                                                                MAIN 250
      READ (5,60,END=59) (NTITLE(I),I=1,12)                                      MAIN 260
      WRITE (6,61) NTITLE                                                        MAIN 270
      WRITE (6,62)                                                               MAIN 280
      READ (5,64) GAIN                                                           MAIN 290
      WRITE (6,65) GAIN                                                          MAIN 300
      KOUNT = 0                                                                  MAIN 310
    1 KOUNT = KOUNT+1                                                            MAIN 320
C                                                                                MAIN 330
CC  BEGIN SECTION TO READ IN COEFFICIENTS IN FACTORED OR POLYNOMIAL              MAIN 340
CC  FORM.  IF POLYNOMIAL FORM IS USED COEFFICIENT OF HIGHEST                     MAIN 350
CC  ORDER TERM IS ASSUMED TO BE UNITY, AND ROOTS ARE CALCULATED.                 MAIN 360
C                                                                                MAIN 370
      READ (5,66) INFORM,N                                                       MAIN 380
      NP = N+1                                                                   MAIN 390
      IF (N.EQ.0) GO TO 6                                                        MAIN 400
      IF (INFORM.EQ.IPP) GO TO 5                                                 MAIN 410
      I = 0                                                                      MAIN 420
    2 I = I+1                                                                    MAIN 430
      READ (5,64) RR,RI                                                          MAIN 440
      RTR(I) = -RR                                                               MAIN 450
      RTI(I) = RI                                                                MAIN 460
C                                                                                MAIN 470
C  IF ROOTS OCCUR IN COMPLEX CONJUGATE PAIRS THE REAL AND IMAGINARY              MAIN 480
```

```
C   VALUES OF THE FACTORS NEED BE ENTERED ONLY ONCE                    MAIN 490
C                                                                      MAIN 500
      IF (RI) 3,4,3                                                    MAIN 510
    3 I = I+1                                                          MAIN 520
      RTR(I) = -RR                                                     MAIN 530
      RTI(I) = -RI                                                     MAIN 540
    4 IF (I.LT.N) GO TO 2                                              MAIN 550
      CALL SEMBL (N,RTR,RTI,CO)                                        MAIN 560
      GO TO 8                                                          MAIN 570
    5 READ (5,64) (CO(I),I=1,N)                                        MAIN 580
    6 CO(NP) = 1.0                                                     MAIN 590
      IF (N) 8,8,7                                                     MAIN 600
    7 CALL PROD (CO,NP,RTR,RTI,COF,NROOT1,IERRT1)                      MAIN 610
      WRITE (6,67) NROOT1,IERRT1                                       MAIN 620
      IF (IERRT1.EQ.0) GO TO 8                                         MAIN 630
      CALL PROM (CO,NP,RTR,RTI,COF,NROOTA,IERRTA)                      MAIN 640
      WRITE (6,62)                                                     MAIN 650
      WRITE (6,63)                                                     MAIN 660
      WRITE (6,68) NROOTA,IERRTA                                       MAIN 670
      WRITE (6,63)                                                     MAIN 680
      WRITE (6,62)                                                     MAIN 690
    8 GO TO (9,12,16,19), KOUNT                                        MAIN 700
C                                                                      MAIN 710
C   MULTIPLY PLANT NUMERATOR COEFFICIENTS BY PLANT GAIN AND LOAD       MAIN 720
C   PLANT NUMERATOR ARRAY.                                             MAIN 730
C                                                                      MAIN 740
    9 DO 10 I=1,NP                                                     MAIN 750
      A(I) = CO(I)*GAIN                                                MAIN 760
   10 CONTINUE                                                         MAIN 770
C                                                                      MAIN 780
      NTEN = N                                                         MAIN 790
      NP = NP                                                          MAIN 800
      WRITE (6,69)                                                     MAIN 810
C                                                                      MAIN 820
C   WRITE PLANT NUMERATOR COEFFICIENTS                                 MAIN 830
C                                                                      MAIN 840
      WRITE (6,70) (CO(I),I=1,NP)                                      MAIN 850
      IF (N.LE.0) GO TO 1                                              MAIN 860
      WRITE (6,71)                                                     MAIN 870
C                                                                      MAIN 880
C   WRITE PLANT NUMERATOR ROOTS.                                       MAIN 890
C                                                                      MAIN 900
      DO 11 I=1,N                                                      MAIN 910
      WRITE (6,72) RTR(I),RTI(I)                                       MAIN 920
   11 CONTINUE                                                         MAIN 930
C                                                                      MAIN 940
      GO TO 1                                                          MAIN 950
C                                                                      MAIN 960
```

```
C  LOAD PLANT DENOMINATOR ARRAY WITH COEFFICIENTS.                    MAIN 970
C                                                                    MAIN 980
   12 DO 13 I=1,NP                                                   MAIN 990
      B(I) = CO(I)                                                   MAIN1000
   13 CONTINUE                                                       MAIN1010
C                                                                    MAIN1020
      WRITE (6,73)                                                   MAIN1030
C                                                                    MAIN1040
C  WRITE COEFFICIENTS OF PLANT DENOMINATOR.                          MAIN1050
C                                                                    MAIN1060
      WRITE (6,70) (B(I),I=1,NP)                                     MAIN1070
      IF (N.LE.0) GO TO 15                                           MAIN1080
      WRITE (6,74)                                                   MAIN1090
C                                                                    MAIN1100
C  WRITE ROOTS OF PLANT DENOMINATOR.                                 MAIN1110
C                                                                    MAIN1120
      DO 14 I=1,N                                                    MAIN1130
      WRITE (6,72) RTR(I),RTI(I)                                     MAIN1140
   14 CONTINUE                                                       MAIN1150
C                                                                    MAIN1160
   15 NTFD = N                                                       MAIN1170
      N4 = NP                                                        MAIN1180
      WRITE (6,62)                                                   MAIN1190
C                                                                    MAIN1200
C  READ IN ASSUMED COMPENSATOR GAIN.                                 MAIN1210
C                                                                    MAIN1220
      READ (5,64) GAINCO                                             MAIN1230
      WRITE (6,75) GAINCO                                            MAIN1240
      GO TO 1                                                        MAIN1250
C                                                                    MAIN1260
C  MULTIPLY COMPENSATOR NUMERATOR COEFFICIENTS BY COMPENSATOR GAIN.  MAIN1270
C                                                                    MAIN1280
   16 DO 17 I=1,NP                                                   MAIN1290
      C(I) = CO(I)*GAINCO                                            MAIN1300
   17 CONTINUE                                                       MAIN1310
C                                                                    MAIN1320
      NCN = N                                                        MAIN1330
      N1 = NP                                                        MAIN1340
      WRITE (6,76)                                                   MAIN1350
C                                                                    MAIN1360
C  WRITE ASSUMED COMPENSATOR NUMERATOR COEFFICIENTS                  MAIN1370
C                                                                    MAIN1380
      WRITE (6,70) (CO(I),I=1,NP)                                    MAIN1390
      IF (N.LE.0) GO TO 1                                            MAIN1400
      WRITE (6,77)                                                   MAIN1410
C                                                                    MAIN1420
C WRITE ROOTS OF ASSUMED COMPENSATOR NUMERATOR.                      MAIN1430
C                                                                    MAIN1440
```

```
      DO 18 I=1,N                                                       MAIN1450
      WRITE (6,72) RTR(I),RTI(I)                                        MAIN1460
   18 CONTINUE                                                          MAIN1470
C                                                                       MAIN1480
      GO TO 1                                                           MAIN1490
C                                                                       MAIN1500
C  LOAD COMPENSATOR DENOMINATOR COEFFICIENT ARRAY WITH ASSUMED STARTING MAIN1510
C  VALUES.                                                              MAIN1520
C                                                                       MAIN1530
   19 DO 20 I=1,NP                                                      MAIN1540
      D(I) = CO(I)                                                      MAIN1550
   20 CONTINUE                                                          MAIN1560
C                                                                       MAIN1570
      WRITE (6,78)                                                      MAIN1580
C                                                                       MAIN1590
C  WRITE COEFFICIENTS OF ASSUMED COMPENSATOR DENOMINATOR POLYNOMIAL.    MAIN1600
C                                                                       MAIN1610
      WRITE (6,70) (D(I),I=1,NP)                                        MAIN1620
      WRITE (6,79)                                                      MAIN1630
C                                                                       MAIN1640
C  WRITE ROOTS OF ASSUMED COMPENSATOR DENOMINATOR POLYNOMIAL.           MAIN1650
C                                                                       MAIN1660
      DO 21 I=1,N                                                       MAIN1670
      WRITE (6,72) RTR(I),RTI(I)                                        MAIN1680
   21 CONTINUE                                                          MAIN1690
C                                                                       MAIN1700
      NCO = N                                                           MAIN1710
      N2 = NP                                                           MAIN1720
      WRITE (6,62)                                                      MAIN1730
C                                                                       MAIN1740
C  READ IN PROGRAM CONTROL DATA.                                        MAIN1750
C                                                                       MAIN1760
      READ (5,80) WMIN,WMAX,NOMEG,KNOW,NBODE,NYQST,IZOH,NICHOL,NMINFS,ICMAIN1770
     1B,IPLOT,ICOST                                                     MAIN1780
      WRITE (6,62)                                                      MAIN1790
      IF (NMINFS.EQ.0) WRITE (6,81)                                     MAIN1800
      IF (NMINFS.EQ.1) WRITE (6,82)                                     MAIN1810
      WRITE (6,62)                                                      MAIN1820
      IF (IZOH.NE.1) GO TO 22                                           MAIN1830
      READ (5,64) T                                                     MAIN1840
      WS = (2.0*PI)/T                                                   MAIN1850
      WRITE (6,62)                                                      MAIN1860
      WRITE (6,83) T,WS                                                 MAIN1870
      WRITE (6,62)                                                      MAIN1880
   22 KNCW = KNCW+1                                                     MAIN1890
      WFREQ(1) = WMIN                                                   MAIN1900
      IF (NOMEG-2) 31,31,23                                             MAIN1910
   23 XOMEG = NOMEG                                                     MAIN1920
```

```
      GO TO (29,26,24), KNOW                                          MAIN1930
   24 DWFQ = (WMAX-WMIN)/(XOMEG-1.0)                                  MAIN1940
C                                                                     MAIN1950
      DO 25 I=2,NOMEG                                                 MAIN1960
   25 WFREQ(I) = WFREQ(I-1)+DWFQ                                      MAIN1970
C                                                                     MAIN1980
C                                                                     MAIN1990
C  READ DISCRETE FREQUENCY VALUES AND DESIRED GAIN AND PHASE.         MAIN2000
      GO TO 31                                                        MAIN2010
   26 READ (5,64) (WFREQ(I),I=1,NOMEG)                                MAIN2020
      READ (5,64) (DMAG(I),I=1,NOMEG)                                 MAIN2030
      IF (ICB.NE.1) GO TO 28                                          MAIN2040
C                                                                     MAIN2050
C  IF DESIRED GAIN IS READ IN IN DB CONVERT TO A MAGNITUDE.           MAIN2060
C                                                                     MAIN2070
      DO 27 I=1,NOMEG                                                 MAIN2080
      DMAG(I) = DMAG(I)/20.0                                          MAIN2090
      DMAG(I) = 10.0**DMAG(I)                                         MAIN2100
   27 CONTINUE                                                        MAIN2110
C                                                                     MAIN2120
   28 READ (5,64) (DQPHSD(I),I=1,NOMEG)                               MAIN2130
      GO TO 31                                                        MAIN2140
   29 Y = (ALOG10(WMAX)-ALOG10(WMIN))/(XOMEG-1.0)                     MAIN2150
      Z = 10.0**Y                                                     MAIN2160
C                                                                     MAIN2170
      DO 30 I=2,NOMEG                                                 MAIN2180
      J = I-1                                                         MAIN2190
   30 WFREQ(I) = WFREQ(J)*Z                                           MAIN2200
C                                                                     MAIN2210
   31 R = 9./13.                                                      MAIN2220
C                                                                     MAIN2230
C  SET UP INITIAL GUESS, UPPER, & LOWER BOUNDS FOR SEARCH AREA.       MAIN2240
C                                                                     MAIN2250
      DO 32 J=1,N1                                                    MAIN2260
      XS(J) = C(J)                                                    MAIN2270
      XU(J) = 1.E+06                                                  MAIN2280
      XL(J) = 0.0                                                     MAIN2290
      IF (ANINFS.EQ.1) XL(J)=-XU(J)                                   MAIN2300
   32 CONTINUE                                                        MAIN2310
C                                                                     MAIN2320
C                                                                     MAIN2330
      DO 33 J=1,N2                                                    MAIN2340
      XS(N1+J) = D(J)                                                 MAIN2350
      XU(N1+J) = 1.E+06                                               MAIN2360
      XL(N1+J) = 0.0                                                  MAIN2370
   33 CONTINUE                                                        MAIN2380
C                                                                     MAIN2390
      READ (5,84) NTA,NPR                                             MAIN2400
```

```
      WRITE (6,62)                                                      MAIN2410
      WRITE (6,85) NTA                                                  MAIN2420
      WRITE (6,62)                                                      MAIN2430
      WRITE (6,62)                                                      MAIN2440
      WRITE (6,86) ICOST                                                MAIN2450
      WRITE (6,62)                                                      MAIN2460
      NAV = 0                                                           MAIN2470
      NV = N1+N2                                                        MAIN2480
      IP = 0                                                            MAIN2490
C                                                                       MAIN2500
C  CALL OPTIMIZATION ROUTINE.                                           MAIN2510
C                                                                       MAIN2520
      CALL BOXPLX (NV,NAV,NPR,NTA,R,XS,IP,XU,XL,YMIN,IERBXP)            MAIN2530
      WRITE (6,62)                                                      MAIN2540
      WRITE (6,87)                                                      MAIN2550
      WRITE (6,70) (XS(I),I=1,NV)                                       MAIN2560
      WRITE (6,88) YMIN,IERBXP                                          MAIN2570
      WRITE (6,62)                                                      MAIN2580
      WRITE (6,62)                                                      MAIN2590
C                                                                       MAIN2600
C  LOAD COMPENSATOR NUMERATOR ARRAY WITH THE OPTIMIZED POLYNOMIAL       MAIN2610
C  COEFFICIENTS.                                                        MAIN2620
C                                                                       MAIN2630
      DO 34 I=1,N1                                                      MAIN2640
      C(I) = XS(I)                                                      MAIN2650
   34 CONTINUE                                                          MAIN2660
C                                                                       MAIN2670
      WRITE (6,89)                                                      MAIN2680
C                                                                       MAIN2690
C  WRITE THE OPTIMIZED COMPENSATOR NUMERATOR COEFFICIENTS IN            MAIN2700
C  UN-NORMALIZED FORM.                                                  MAIN2710
C                                                                       MAIN2720
      WRITE (6,70) (C(I),I=1,N1)                                        MAIN2730
C                                                                       MAIN2740
      DO 35 I=1,N1                                                      MAIN2750
      CC(I) = C(I)/C(N1)                                                MAIN2760
   35 CONTINUE                                                          MAIN2770
C                                                                       MAIN2780
      IF (NCN.EQ.0) GO TO 37                                            MAIN2790
C                                                                       MAIN2800
C  COMPUTE THE ROOTS OF THE OPTIMIZED COMPENSATOR NUMERATOR.            MAIN2810
C                                                                       MAIN2820
      CALL PROD (CO,N1,RTR,RTI,COF,NROOT2,IERRT2)                       MAIN2830
      IF (IERRT2.EQ.0) GO TO 36                                         MAIN2840
      CALL PRBM (CO,N1,RTR,RTI,COF,NROOTB,IERRTB)                       MAIN2850
      WRITE (6,62)                                                      MAIN2860
      WRITE (6,63)                                                      MAIN2870
      WRITE (6,90) NROOTB,IERRTB                                        MAIN2880
```

```
      WRITE (6,63)                                                      MAIN2890
      WRITE (6,62)                                                      MAIN2900
   36 WRITE (6,91)                                                      MAIN2910
C                                                                       MAIN2920
C  WRITE THE ROOTS OF THE OPTIMIZED COMPENSATOR NUMERATOR.              MAIN2930
C                                                                       MAIN2940
      DO 37 I=1,NCN                                                     MAIN2950
      WRITE (6,92) RTR(I),RTI(I)                                        MAIN2960
   37 CONTINUE                                                          MAIN2970
C                                                                       MAIN2980
      WRITE (6,62)                                                      MAIN2990
C                                                                       MAIN3000
C  LOAD COMPENSATOR DENOMINATOR ARRAY WITH THE OPTIMIZED POLYNOMIAL     MAIN3010
C  COEFFICIENTS.                                                        MAIN3020
C                                                                       MAIN3030
      DO 38 I=1,N2                                                      MAIN3040
      D(I) = XS(N1+I)                                                   MAIN3050
   38 CONTINUE                                                          MAIN3060
C                                                                       MAIN3070
      WRITE (6,93)                                                      MAIN3080
C                                                                       MAIN3090
C  WRITE OPTIMIZED DENOMINATOR COEFFICIENTS IN UN-NORMALIZED FORM.      MAIN3100
C                                                                       MAIN3110
      WRITE (6,70) (D(I),I=1,N2)                                        MAIN3120
C                                                                       MAIN3130
      DO 39 I=1,N2                                                      MAIN3140
      CC(I) = D(I)/D(N2)                                                MAIN3150
   39 CONTINUE                                                          MAIN3160
C                                                                       MAIN3170
      IF (NCC.EQ.0) GO TO 41                                            MAIN3180
C                                                                       MAIN3190
C  COMPUTE THE ROOTS OF THE OPTIMIZED COMPENSATOR DENOMINATOR.          MAIN3200
C                                                                       MAIN3210
      CALL PROD (CO,N2,RTR,RTI,COF,NROOT3,IERRT3)                       MAIN3220
      IF (IERRT3.EQ.0) GO TO 40                                         MAIN3230
      CALL PROM (CO,N2,RTR,RTI,COF,NROOTC,IERRTC)                       MAIN3240
      WRITE (6,62)                                                      MAIN3250
      WRITE (6,63)                                                      MAIN3260
      WRITE (6,94) NROOTC,IERRTC                                        MAIN3270
      WRITE (6,63)                                                      MAIN3280
      WRITE (6,62)                                                      MAIN3290
   40 WRITE (6,95)                                                      MAIN3300
C                                                                       MAIN3310
C  WRITE THE ROOTS OF THE OPTIMIZED COMPENSATOR DENOMINATOR.            MAIN3320
C                                                                       MAIN3330
      DO 41 I=1,NCD                                                     MAIN3340
      WRITE (6,92) RTR(I),RTI(I)                                        MAIN3350
   41 CONTINUE                                                          MAIN3360
```

```
C                                                                       MAIN3370
      WRITE (6,62)                                                      MAIN3380
C                                                                       MAIN3390
C     COMPUTE AND WRITE THE OPTIMIZED COMPENSATOR GAIN.                 MAIN3400
C                                                                       MAIN3410
      GAINC = C(N1)/D(N2)                                               MAIN3420
      WRITE (6,96) GAINC                                                MAIN3430
      WRITE (6,97) NROOT2,IERRT2,NROOT3,IERRT3                          MAIN3440
      CALL PMPY (COFASN,N7,A,N3,C,N1)                                   MAIN3450
      CALL PMPY (COFASD,N8,B,N4,D,N2)                                   MAIN3460
      NSN = N7-1                                                        MAIN3470
      NSD = N8-1                                                        MAIN3480
C                                                                       MAIN3490
C     SET UP AND EVALUATE SYSTEM OPEN LOOP FREQUENCY RESPONSE AT THE    MAIN3500
C     DISCRETE FREQUENCIES SPECIFIED USING THE OPTIMIZED COMPENSATOR    MAIN3510
C     COEFFICIENT VALUES.                                               MAIN3520
C                                                                       MAIN3530
      DO 52 K=1,NOMEG                                                   MAIN3540
      CALL PVAL (COFASN,NSN,0.0,WFREQ(K),QNUMR,QNUMI)                   MAIN3550
      CALL PVAL (COFASD,NSD,0.0,WFREQ(K),QDENR,QDENI)                   MAIN3560
      IF (SQRT(QDENI**2+QDENR**2)) 43,42,43                             MAIN3570
   42 QMAG(K) = 1.E+20                                                  MAIN3580
      QR(K) = 1.E+20                                                    MAIN3590
      QI(K) = 1.E+20                                                    MAIN3600
      GO TO 44                                                          MAIN3610
   43 QMAG(K) = SQRT(QNUMI**2+QNUMR**2)/SQRT(QDENI**2+QDENR**2)         MAIN3620
      IF (IZCH.EQ.1) QMAG(K)=QMAG(K)*ABS((SIN(PI*WFREQ(K)/WS))/(PI*WFREQMAIN3630
     1(K)/WS))                                                          MAIN3640
      QR(K) = (QNUMR*QDENR+QNUMI*QDENI)/(QDENR**2+QDENI**2)             MAIN3650
      QI(K) = (QNUMI*QDENR-QNUMR*QDENI)/(QDENR**2+QDENI**2)             MAIN3660
   44 ANGNUR = ATAN2(QNUMI,QNUMR)                                       MAIN3670
      ANGNUD = ANGNUR*57.29578                                          MAIN3680
      IF (ANGNUD.LT.0.0) ANGNUD=360.0+ANGNUD                            MAIN3690
      DELPHI = ANGNUD-PHI                                               MAIN3700
      IF (IDELNU.EQ.0) GO TO 47                                         MAIN3710
      IF (DELPHI.GE.0.0.AND.IDELNU.EQ.1) GO TO 47                       MAIN3720
      IF (DELPHI.LT.0.0.AND.IDELNU.EQ.1) GO TO 45                       MAIN3730
      IF (DELPHI.GE.0.0.AND.IDELNU.EQ.-1) GO TO 46                      MAIN3740
      IF (DELPHI.LT.0.0.AND.IDELNU.EQ.-1) GO TO 47                      MAIN3750
   45 IF (ABS(DELPHI).LT.180.0) GO TO 47                                MAIN3760
      DELPHI = ANGNUD+360.0-PHI                                         MAIN3770
      GO TO 47                                                          MAIN3780
   46 IF (ABS(DELPHI).LT.180.0) GO TO 47                                MAIN3790
      DELPHI = ANGNUD-360.0-PHI                                         MAIN3800
   47 PHICHK = PHICHK+DELPHI                                            MAIN3810
      IPHI = PHICHK/360.0                                               MAIN3820
      PHI = ANGNUD                                                      MAIN3830
      ANGNUD = ANGNUD+IPHI*360.0                                        MAIN3840
```

```
      ANGDER = ATAN2(QDENI,QDENR)                                       MAIN3850
      ANGDED = ANGDER*57.29578                                          MAIN3860
      IF (ANGDED.LT.0.0) ANGDED=360.0+ANGDED                            MAIN3870
      DELPSI = ANGDED-PSI                                               MAIN3880
      IF (IDELDE.EQ.0) GO TO 50                                         MAIN3890
      IF (DELPSI.GE.0.0.AND.IDELDE.EQ.1) GO TO 50                       MAIN3900
      IF (DELPSI.LT.0.0.AND.IDELDE.EQ.1) GO TO 48                       MAIN3910
      IF (DELPSI.GE.0.0.AND.IDELDE.EQ.-1) GO TO 49                      MAIN3920
      IF (DELPSI.LT.0.0.AND.IDELDE.EQ.-1) GO TO 50                      MAIN3930
   48 IF (ABS(DELPSI).LT.180.0) GO TO 50                                MAIN3940
      DELPSI = ANGDED+360.0-PSI                                         MAIN3950
      GO TO 50                                                          MAIN3960
   49 IF (ABS(DELPSI).LT.180.0) GO TO 50                                MAIN3970
      DELPSI = ANGDED-360.0-PSI                                         MAIN3980
   50 PSICHK = PSICHK+DELPSI                                            MAIN3990
      IPSI = PSICHK/360.0                                               MAIN4000
      PSI = ANGDED                                                      MAIN4010
      ANGDED = ANGDED+IPSI*360.0                                        MAIN4020
      IF (DELPHI.GE.0.0) IDELNU=1                                       MAIN4030
      IF (DELPHI.LT.0.0) IDELNU=-1                                      MAIN4040
      IF (DELPSI.GE.0.0) IDELDE=1                                       MAIN4050
      IF (DELPSI.LT.0.0) IDELDE=-1                                      MAIN4060
      QPHSD(K) = ANGNUD-ANGDED                                          MAIN4070
      QPHSR(K) = ANGNUR-ANGDER                                          MAIN4080
      IF (IZOH.NE.1) GO TO 51                                           MAIN4090
      IWS = WFREQ(K)/WS                                                 MAIN4100
      QPHSD(K) = QPHSD(K)-(PI*WFREQ(K)/WS)*57.29578-IWS*180.0           MAIN4110
C                                                                       MAIN4120
C  CALCULATE THE DIFFERENCE BETWEEN THE ACTUAL AND DESIRED RESPONSE AT  MAIN4130
C  THE DISCRETE FREQUENCY VALUES ORIGINALLY SPECIFIED.                  MAIN4140
C                                                                       MAIN4150
   51 DIFF1(K) = (20.0*ALOG10(QMAG(K)))-(20.0*ALOG10(DMAG(K)))          MAIN4160
      DIFF2(K) = QPHSD(K)-DQPHSD(K)                                     MAIN4170
   52 CONTINUE                                                          MAIN4180
C                                                                       MAIN4190
      CALL SIMULA (WMIN,WMAX)                                           MAIN4200
      IF (NBODE) 55,53,55                                               MAIN4210
C                                                                       MAIN4220
C  PREPARE DISCRETE FREQUENCY POINT DATA FOR GRAPHING.                  MAIN4230
C                                                                       MAIN4240
   53 DO 54 MA=1,NOMEG                                                  MAIN4250
      FREQ(MA) = ALOG10(WFREQ(MA))                                      MAIN4260
   54 CONTINUE                                                          MAIN4270
C                                                                       MAIN4280
   55 IF (NBODE.EQ.1.AND.NICHOL.EQ.1) GO TO 57                          MAIN4290
C                                                                       MAIN4300
      DO 56 MA=1,NOMEG                                                  MAIN4310
      AMAG(MA) = 20.0*ALOG10(QMAG(MA))                                  MAIN4320
```

```
      ADMAG(MA) = 20.0*ALOG10(DMAG(MA))                                 MAIN4330
   56 CONTINUE                                                          MAIN4340
C                                                                       MAIN4350
C                                                                       MAIN4360
C  OUTPUT RESULTS ON GRAPHS SPECIFIED.                                  MAIN4370
C                                                                       MAIN4380
   57 CALL GRAPH (NBODE,NYQST,NICHOL)                                   MAIN4390
      WRITE (6,98)                                                      MAIN4400
      WRITE (6,99)                                                      MAIN4410
C                                                                       MAIN4420
      DO 58 IJK=1,NCMEG                                                 MAIN4430
      WRITE (6,100) WFREQ(IJK),AMAG(IJK),ADMAG(IJK),CPHSD(IJK),DCPHSD(IJMAIN4440
     1K),DIFF1(IJK),DIFF2(IJK)                                          MAIN4450
   58 CONTINUE                                                          MAIN4460
C                                                                       MAIN4470
C SYSTEM STABILITY CHECK USING ROUTH CRITERION ON CHARACTERISTIC EQUA.   MAIN4480
C                                                                       MAIN4490
      CALL PADD (COFWRK,IWRK,COFASN,N7,COFASD,NE)                       MAIN4500
      CALL FINVRT (COFWRK,IWRK)                                         MAIN4510
      CALL ROUTH (COFWRK,IWRK,ISYS)                                     MAIN4520
      CALL FINVRT (COFWRK,IWRK)                                         MAIN4530
      IF (ISYS.EQ.1) WRITE (6,101)                                      MAIN4540
      IF (ISYS.EQ.0) WRITE (6,102)                                      MAIN4550
   59 STOP                                                              MAIN4560
C                                                                       MAIN4570
   60 FORMAT (12A4)                                                     MAIN4580
   61 FORMAT ('1',6X,'TITLE --- ',12A4)                                 MAIN4590
   62 FORMAT (' ',72('-'))                                              MAIN4600
   63 FORMAT (' ',8('*WARNING*'))                                       MAIN4610
   64 FORMAT (8E10.0)                                                   MAIN4620
   65 FORMAT ('0',6X,'UNCOMPENSATED TRANSFER FUNCTION GAIN = ',1PE13.6) MAIN4630
   66 FORMAT (A1,I2)                                                    MAIN4640
   67 FORMAT ('0','NROOT1 = ',I3,10X,'IERRT1 = ',I3)                    MAIN4650
   68 FORMAT ('0','THE FIRST CALL TO PROD IN THE INPUT SECTION RESULTED'MAIN4660
     1,/,' IN AN UNSATISFACTORY DETERMINATION OF POLYNOMIAL ROOTS.',/,  MAIN4670
     2 ' SUBROUTINE PROM WAS CALLED TO TRY RESOLVING PROBLEM.',/,' NROOTMAIN4680
     3A = ',I3,10X,'IERRTA = ',I3)                                      MAIN4690
   69 FORMAT ('0',6X,'UNCOMPENSATED TRANSFER FUNCTION NUMERATOR',/,2X,  MAIN4700
     1 'COEFFICIENTS IN ASCENDING POWERS OF S',/)                       MAIN4710
   70 FORMAT ('0',5(3X,1PE13.6))                                        MAIN4720
   71 FORMAT ('0',6X,'UNCOMPENSATED TRANSFER FUNCTION NUMERATOR ROOTS', MAIN4730
     1 /,3X,'ARE:',5X,'REAL PART',8X,'IMAGINARY PART')                  MAIN4740
   72 FORMAT ('0',9X,1PE13.6,6X,1PE13.6)                                MAIN4750
   73 FORMAT ('0',6X,'UNCOMPENSATED TRANSFER FUNCTION DENOMINATOR',/,2X,MAIN4760
     1 'COEFFICIENTS IN ASCENDING POWERS OF S',/)                       MAIN4770
   74 FORMAT ('0',6X,'UNCOMPENSATED TRANSFER FUNCTION DENOMINATOR ROOTS'MAIN4780
     1,/,3X,'ARE:',5X,'REAL PART',8X,'IMAGINARY PART')                  MAIN4790
   75 FORMAT ('0',6X,'COMPENSATOR TRANSFER FUNCTION GAIN = ',1PE13.6)   MAIN4800
```

```
76 FORMAT ('0',6X,'COMPENSATOR TRANSFER FUNCTION NUMERATOR',/2X,      MAIN4810
  1 'COEFFICIENTS IN ASCENDING POWERS OF S',/)                       MAIN4820
77 FORMAT ('0',6X,'COMPENSATOR TRANSFER FUNCTION NUMERATOR ROOTS',/,3MAIN4830
  1X'ARE:',5X,'REAL PART',8X,'IMAGINARY PART')                       MAIN4840
78 FORMAT ('0',6X,'COMPENSATOR TRANSFER FUNCTION DENOMINATOR',/2X,   MAIN4850
  1 'COEFFICIENTS IN ASCENDING POWERS OF S',/)                       MAIN4860
79 FORMAT ('0',6X,'COMPENSATOR TRANSFER FUNCTION DENOMINATOR ROOTS', MAIN4870
  1 /,3X,'ARE:',5X,'REAL PART',8X,'IMAGINARY PART')                  MAIN4880
80 FORMAT (2E10.0,10I3)                                              MAIN4890
81 FORMAT ('0',5X,'THE COMPENSATOR TRANSFER FUNCTION IS OF THE MINIMUMAIN4900
  1M PHASE',/,' TYPE, THEREFORE NO RIGHT HALF PLANE ZEROS WILL BE ALLMAIN4910
  2OWED IN',/,' THE SOLUTION FOR THE COMPENSATOR TRANSFER FUNCTION',/MAIN4920
  3)                                                                 MAIN4930
82 FORMAT ('0',5X,'THE COMPENSATOR TRANSFER FUNCTION IS OF THE NON-MIMAIN4940
  1NIMUM',/,' PHASE TYPE, THEREFORE RIGHT HALF PLANE ZEROS WILL BE ALMAIN4950
  2LOWED IN',/,' THE SOLUTION FOR THE COMPENSATOR TRANSFER FUNCTION',MAIN4960
  3/)                                                                MAIN4970
83 FORMAT ('0',5X,'THE SYSTEM HAS A ZERO ORDER HOLD IN THE LOOP.',//,MAIN4980
  1 ' THE SAMPLING PERIOD  T = ',1PE15.6,' (SECS)',//,               MAIN4990
  2 ' THE SAMPLING FREQUENCY  WS = ',1PE15.6,' (RADIANS)')           MAIN5000
84 FORMAT (2I5)                                                      MAIN5010
85 FORMAT ('0',5X,'THE TOTAL NUMBER OF TRIALS CALLED FOR = ',I5,/)   MAIN5020
86 FORMAT ('0',5X,'THE COST FUNCTION TO BE USED IS THE TYPE',2X,I2,/)MAIN5030
87 FORMAT (///,' THE BEST VERTEX VALUES ARE:')                       MAIN5040
88 FORMAT (///,' THE MINIMUM COST FUNCTION VALUE = ',1PE13.6,//,' THEMAIN5050
  1 ERROR RETURN CODE FROM BOXPLX = ',I3,/)                          MAIN5060
89 FORMAT ('0',6X,'OPTIMIZED COMPENSATOR TRANSFER FUNCTION NUMERATOR'MAIN5070
  1,/,2X,'COEFFICIENTS IN ASCENDING POWERS OF S')                    MAIN5080
90 FORMAT ('0','THE CALL TO PROD FOR FINDING OPTIMIZED COMPENSATOR',/MAIN5090
  1,' NUMERATOR ROOTS RESULTED IN UNSATISFACTORY SOLUTION. ',/,      MAIN5100
  2 ' SUBROUTINE PRBM WAS CALLED TO TRY RESOLVING PROBLEM.',/,' NROOTMAIN5110
  3D = ',I3,10X,'IERRTD = ',I3)                                      MAIN5120
91 FORMAT ('0',6X,'OPTIMIZED COMPENSATOR TRANSFER FUNCTION NUMERATOR'MAIN5130
  1,/,3X,'ROOTS ARE:',5X,'REAL PART',8X,'IMAGINARY PART')            MAIN5140
92 FORMAT ('0',15X,1PE13.6,6X,1PE13.6)                               MAIN5150
93 FORMAT ('0',6X,'OPTIMIZED COMPENSATOR TRANSFER FUNCTION DENOMINATOMAIN5160
  1R',/,2X,'COEFFICIENTS IN ASCENDING POWERS OF S',/)                MAIN5170
94 FORMAT ('0','THE CALL TO PROD FOR FINDING OPTIMIZED COMPENSATOR',/MAIN5180
  1,' DENOMINATOR ROOTS RESULTED IN UNSATISFACTORY SOLUTION.',/,     MAIN5190
  2 ' SUBROUTINE PRBM WAS CALLED TO ATTEMPT RECTIFYING PROBLEM.',/,  MAIN5200
  3 ' NROOTC = ',I3,10X,'IERRTC = ',I3)                              MAIN5210
95 FORMAT ('0',6X,'OPTIMIZED COMPENSATOR TRANSFER FUNCTION DENOMINATOMAIN5220
  1R',/,3X,'ROOTS ARE:',5X,'REAL PART',8X,'IMAGINARY PART')          MAIN5230
96 FORMAT ('0',6X,'OPTIMIZED COMPENSATOR TRANSFER FUNCTION GAIN = ',  MAIN5240
  1 1PE13.6)                                                         MAIN5250
97 FORMAT ('0','NROOT2 = ',I3,10X,'IERRT2 = ',I3,///,' ','NROOT3 = ',MAIN5260
  1I3,10X,'IERRT3 = ',I3)                                            MAIN5270
98 FORMAT ('1')                                                      MAIN5280
```

```
 99 FORMAT (' ',3X,'FREQUENCY',7X,'MAGNITUDE(DB)',3X,'DESIRED MAG(DB)'MAIN5250
   1,2X,'PHASE(DEG)',6X,'DESIRED PHASE',4X,'MAG DIFF(DB)',4X,'PHASE DIMAIN5300
   2FF(DEG)')                                                        MAIN5310
100 FORMAT (' ',8(3X,1PE13.6))                                       MAIN5320
101 FORMAT ('0',72('-'),/,2(' ********* W A R N I N G ********* '),//,MAIN5330
   1' THE ROUTH TEST OF THE CHARACTERISTIC EQUATION INDICATES SYSTEM',MAIN5340
   2/,' INSTABILITY',//,2(' ********* W A R N I N G ********* '),/,' 'MAIN5350
   3,72('-'))                                                        MAIN5360
102 FORMAT ('0',72('-'),/,5X,' THE ROUTH TEST OF THE CHARACTERISTIC EQMAIN5370
   1UATION INDICATES',/,' THAT THE SYSTEM IS STABLE',/,' ',72('-'))  MAIN5380
   END                                                               MAIN5390
```

```
C++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++CPVAL   10
C++++++++++++++++++++        SUBROUTINE PVAL        ++++++++++++++++++++++++++CPVAL   20
C++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++CPVAL   30
C++++                                                                         ++++CPVAL   40
C++++  PURPOSE: TO EVALUATE A POLYNOMIAL A(S) WITH REAL COEFFICIENTS +++CPVAL   50
C++++           FOR WHICH THE SUBSTITUTION S=PR + JRI HAS BEEN MADE  ++++CPVAL   60
C++++           FOR THE COMPLEX VARIABLE.                            ++++CPVAL   70
C++++                                                                ++++CPVAL   80
C++++  CALLING SEQUENCE:                                            ++++CPVAL   90
C++++  CALL PVAL(A,NN,PR,PI,VR,VI)                                   ++++CPVAL  100
C++++                                                                ++++CPVAL  110
C++++  DESCRIPTION OF PARAMETERS:                                    ++++CPVAL  120
C++++  A       = VECTOR OF REAL COEFFICIENTS, ORDERED FROM LOWEST TO ++++CPVAL  130
C++++            HIGHEST POWER OF THE INDEPENDENT VARIABLE.         ++++CPVAL  140
C++++  NN      = THE ORDER OF THE POLYNOMIAL.                       ++++CPVAL  150
C++++  PR      = THE REAL PART OF THE COMPLEX VARIAELE.             ++++CPVAL  160
C++++  PI      = THE IMAGINARY PART OF THE COMPLEX VARIABLE.        ++++CPVAL  170
C++++  VR      = THE REAL PART OF THE RESULTANT VALUE OF THE        ++++CPVAL  180
C++++            POLYNOMIAL.                                        ++++CPVAL  190
C++++  VI      = THE IMAGINARY PART OF THE RESULTANT VALUE OF THE   ++++CPVAL  200
C++++            POLYNOMIAL.                                        ++++CPVAL  210
C++++                                                               ++++CPVAL  220
C++++  SUBROUTINES AND FUNCTION SUB-PROGRAMS REQUIRED:              ++++CPVAL  230
C++++      NONE                                                     ++++CPVAL  240
C++++                                                               ++++CPVAL  250
C++++  METHOD:                                                      ++++CPVAL  260
C++++  EVALUATION IS PERFORMED BY MEANS OF NESTED MULTIPLICATION    ++++CPVAL  270
C++++                                                               ++++CPVAL  280
C++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++CPVAL  290
C++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++CPVAL  300
      SUBROUTINE PVAL (A,NN,PR,PI,VR,VI)                             PVAL  310
      DIMENSION A(1)                                                 PVAL  320
      COMPLEX S,P                                                    PVAL  330
      S = CMPLX(PR,PI)                                               PVAL  340
      P = CMPLX(A(NN+1),0.)                                          PVAL  350
      IF (NN) 4,3,1                                                  PVAL  360
C                                                                   CPVAL  370
C  DETERMINE THE COMPLEX VALUE OF THE POLYNOMIAL                    CPVAL  380
C                                                                    PVAL  390
    1 DO 2 J=1,NN                                                    PVAL  400
    2 P = P*S+A(NN+1-J)                                              PVAL  410
C                                                                    PVAL  420
C  FIND THE REAL AND IMAGINARY PARTS AND RETURN TO CALLING PROGRAM  CPVAL  430
C                                                                   CPVAL  440
    3 VR = REAL(P)                                                   PVAL  450
      VI = AIMAG(P)                                                  PVAL  460
    4 RETURN                                                         PVAL  470
      END                                                            PVAL  480
```

```
C++++++
```

```
      J(1) = 1                                                          SEMB 490
      GO TO 3                                                           SEMB 500
    2 J(L) = J(L)+1                                                     SEMB 510
    3 IF (L-M) 4,6,10                                                   SEMB 520
    4 MM = M-1                                                          SEMB 530
C                                                                       SEMB 540
      DO 5 I=L,MM                                                       SEMB 550
      II = I+1                                                          SEMB 560
    5 J(II) = J(I)+1                                                    SEMB 570
C                                                                       SEMB 580
    6 PR = CMPLX(1.0,0.0)                                               SEMB 590
C                                                                       SEMB 600
      DO 7 I=1,M                                                        SEMB 610
      ICK = J(I)                                                        SEMB 620
    7 PR = -PR*R(ICK)                                                   SEMB 630
C                                                                       SEMB 640
      SUM = SUM+PR                                                      SEMB 650
C                                                                       SEMB 660
      DO 8 I=1,M                                                        SEMB 670
      L = M-I+1                                                         SEMB 680
      IF (J(L)-N+M-L) 2,8,10                                            SEMB 690
    8 CONTINUE                                                          SEMB 700
C                                                                       SEMB 710
      MP = N-M+1                                                        SEMB 720
    9 CP(MP) = REAL(SUM)                                                SEMB 730
C                                                                       SEMB 740
      RETURN                                                            SEMB 750
   10 WRITE (6,11)                                                      SEMB 760
      RETURN                                                            SEMB 770
C                                                                       SEMB 780
   11 FORMAT (/,4X,14HERROR IN SEMBL)                                   SEMB 790
      END                                                               SEMB 800
```

```
C*******************************************************************PRCD   10
C                                                                   PRCD   20
C     SUBROUTINE PRCD                                               PRCD   30
C                                                                   PRCD   40
C     PURPOSE                                                       PRCD   50
C        CALCULATE ALL REAL AND COMPLEX ROOTS OF A GIVEN POLYNOMIAL PRCD   60
C        WITH REAL COEFFICIENTS.                                    PRCD   70
C                                                                   PRCD   80
C     USAGE                                                         PRCD   90
C        CALL PRCD(C,IC,Q,E,POL,IR,IER)                             PRCD  100
C                                                                   PRCD  110
C     DESCRIPTION OF PARAMETERS                                     PRCD  120
C        C      - COEFFICIENT VECTOR OF GIVEN POLYNOMIAL            PRCD  130
C                 COEFFICIENTS ARE ORDERED FROM LOW TO HIGH         PRCD  140
C                 THE GIVEN COEFFICIENT VECTOR GETS DIVIDED BY THE  PRCD  150
C                 LAST NONZERO TERM                                 PRCD  160
C        IC     - DIMENSION OF VECTOR C                             PRCD  170
C        Q      - WORKING STORAGE OF DIMENSION IC                   PRCD  180
C                 ON RETURN Q CONTAINS REAL PARTS OF ROOTS          PRCD  190
C        E      - WORKING STORAGE OF DIMENSION IC                   PRCD  200
C                 ON RETURN E CONTAINS COMPLEX PARTS OF ROOTS       PRCD  210
C        POL    - WORKING STORAGE OF DIMENSION IC                   PRCD  220
C                 ON RETURN POL CONTAINS THE COEFFICIENTS OF THE    PRCD  230
C                 POLYNOMIAL WITH CALCULATED ROOTS                  PRCD  240
C                 THIS RESULTING COEFFICIENT VECTOR HAS DIMENSION IR+1PRCD  250
C                 COEFFICIENTS ARE ORDERED FROM LOW TO HIGH         PRCD  260
C        IR     - NUMBER OF CALCULATED ROOTS                        PRCD  270
C                 NORMALLY IR IS EQUAL TO DIMENSION IC MINUS ONE    PRCD  280
C        IER    - RESULTING ERROR PARAMETER. SEE REMARKS            PRCD  290
C                                                                   PRCD  300
C     REMARKS                                                       PRCD  310
C        THE REAL PART OF THE ROOTS IS STORED IN Q(1) UP TO Q(IR)   PRCD  320
C        CORRESPONDING COMPLEX PARTS ARE STORED IN E(1) UP TO E(IR). PRCD  330
C        IER = 0 MEANS NO ERRORS                                    PRCD  340
C        IER = 1 MEANS NO CONVERGENCE WITH FEASIBLE TOLERANCE       PRCD  350
C        IER = 2 MEANS POLYNOMIAL IS DEGENERATE (CONSTANT OR ZERO)  PRCD  360
C        IER = 3 MEANS SUBROUTINE WAS ABANDONED DUE TO ZERO DIVISOR PRCD  370
C        IER = 4 MEANS THERE EXISTS NO S-FRACTION                   PRCD  380
C        IER =-1 MEANS CALCULATED COEFFICIENT VECTOR REVEALS POOR   PRCD  390
C                ACCURACY OF THE CALCULATED ROOTS.                  PRCD  400
C                THE CALCULATED COEFFICIENT VECTOR HAS LESS THAN    PRCD  410
C                3 CORRECT DIGITS.                                  PRCD  420
C        THE FINAL COMPARISON BETWEEN GIVEN AND CALCULATED          PRCD  430
C        COEFFICIENT VECTOR IS PERFORMED ONLY IF ALL ROOTS HAVE BEEN PRCD  440
C        CALCULATED.                                                PRCD  450
C        THE MAXIMAL RELATIVE ERROR OF THE COEFFICIENT VECTOR IS    PRCD  460
C        RECORDED IN Q(IR+1).                                       PRCD  470
C                                                                   PRCD  480
```

```
C        SUBROUTINES AND FUNCTION SUBPROGRAMS REQUIRED                  PRQD 490
C           NONE                                                        PRQD 500
C                                                                       PRQD 510
C        METHOD                                                         PRQD 520
C           THE ROOTS OF THE POLYNOMIAL ARE CALCULATED BY MEANS OF      PRQD 530
C           THE QUOTIENT-DIFFERENCE ALGORITHM WITH DISPLACEMENT.        PRQD 540
C           REFERENCE                                                   PRQD 550
C           H.RUTISHAUSER, DER QUOTIENTEN-DIFFERENZEN-ALGORITHMUS,      PRQD 560
C           BIRKHAEUSER, BASEL/STUTTGART, 1957.                         PRQD 570
C                                                                       PRQD 580
C     ..................................................................PRQD 590
C                                                                       PRQD 600
      SUBROUTINE PRQD (C,IC,Q,E,POL,IF,IER)                             PRQD 610
C                                                                       PRQD 620
C     DIMENSIONED DUMMY VARIABLES                                       PRQD 630
      DIMENSION E(1), Q(1), C(1), POL(1)                                PRQD 640
C                                                                       PRQD 650
C        NORMALIZATION OF GIVEN POLYNOMIAL                              PRQD 660
C           TEST OF DIMENSION                                           PRQD 670
C        IR CONTAINS INDEX OF HIGHEST COEFFICIENT                       PRQD 680
      IER = 0                                                           PRQD 690
      IR = IC                                                           PRQD 700
      EPS = 1.E-6                                                       PRQD 710
      TOL = 1.E-3                                                       PRQD 720
      LIMIT = 10*IC                                                     PRQD 730
      KCONT = 0                                                         PRQD 740
    1 IF (IR-1) 79,79,2                                                 PRQD 750
C                                                                       PRQD 760
C        DROP TRAILING ZERO COEFFICIENTS                                PRQD 770
    2 IF (C(IR)) 4,3,4                                                  PRQD 780
    3 IR = IR-1                                                         PRQD 790
      GO TO 1                                                           PRQD 800
C                                                                       PRQD 810
C           REARRANGEMENT OF GIVEN POLYNOMIAL                           PRQD 820
C        EXTRACTION OF ZERO ROOTS                                       PRQD 830
    4 Q = 1./C(IR)                                                      PRQD 840
      IEND = IR-1                                                       PRQD 850
      ISTA = 1                                                          PRQD 860
      NSAV = IR+1                                                       PRQD 870
      JBEG = 1                                                          PRQD 880
C                                                                       PRQD 890
C           C(J)=1.                                                     PRQD 900
C           C(J+I)=C(IR-I)/C(IR)                                        PRQD 910
C           C(IR)=C(J)/C(IR)                                            PRQD 920
C           WHERE J IS THE INDEX OF THE LOWEST NONZERO COEFFICIENT      PRQD 930
C                                                                       PRQD 940
      DO 9 I=1,IR                                                       PRQD 950
      J = NSAV-I                                                        PRQD 960
```

```
      IF (C(I)) 7,5,7                                                   PRCD 970
    5 GO TO (6,8), JBEG                                                 PRCD 980
    6 NSAV = NSAV+1                                                     PRCD 990
      C(ISTA) = 0.                                                      PRCD1000
      E(ISTA) = 0.                                                      PRCD1010
      ISTA = ISTA+1                                                     PRCD1020
      GO TO 9                                                           PRCD1030
    7 JBEG = 2                                                          PRCD1040
    8 C(J) = C(I)*0                                                     PRCD1050
      C(I) = C(J)                                                       PRCD1060
    9 CONTINUE                                                          PRCD1070
C                                                                       PRCD1080
C                                                                       PRCD1090
C           INITIALIZATION                                              PRCD1100
      ESAV = 0.                                                         PRCD1110
      C(ISTA) = 0.                                                      PRCD1120
   10 NSAV = IR                                                         PRCD1130
C                                                                       PRCD1140
C           COMPUTATION OF DERIVATIVE                                   PRCD1150
      EXPT = IR-ISTA                                                    PRCD1160
      E(ISTA) = EXPT                                                    PRCD1170
C                                                                       PRCD1180
      DO 11 I=ISTA,IEND                                                 PRCD1190
      EXPT = EXPT-1.0                                                   PRCD1200
      POL(I+1) = EPS*ABS(C(I+1))+EPS                                    PRCD1210
   11 E(I+1) = Q(I+1)*EXPT                                              PRCD1220
C                                                                       PRCD1230
C                                                                       PRCD1240
C           TEST OF REMAINING DIMENSION                                 PRCD1250
      IF (ISTA-IEND) 12,20,60                                           PRCD1260
   12 JEND = IEND-1                                                     PRCD1270
C                                                                       PRCD1280
C           COMPUTATION OF S-FRACTION                                   PRCD1290
C                                                                       PRCD1300
      DO 19 I=ISTA,JEND                                                 PRCD1310
      IF (I-ISTA) 13,16,13                                              PRCD1320
   13 IF (ABS(E(I))-POL(I+1)) 14,14,16                                  PRCD1330
C                                                                       PRCD1340
C           THE GIVEN POLYNOMIAL HAS MULTIPLE ROOTS, THE COEFFICIENTS OF PRCD1350
C           THE COMMON FACTOR ARE STORED FROM Q(NSAV) UP TO Q(IR)       PRCD1360
   14 NSAV = I                                                          PRCD1370
C                                                                       PRCD1380
      DO 15 K=I,JEND                                                    PRCD1390
      IF (ABS(E(K))-POL(K+1)) 15,15,80                                  PRCD1400
   15 CONTINUE                                                          PRCD1410
C                                                                       PRCD1420
      GO TO 21                                                          PRCD1430
C                                                                       PRCD1440
```

```
C            EUCLIDEAN ALGORITHM                                        PRCD1450
C                                                                       PRCD1460
   16 DO 19 K=I,IEND                                                    PRCD1470
      E(K+1) = E(K+1)/E(I)                                              PRCD1480
      Q(K+1) = E(K+1)-Q(K+1)                                            PRCD1490
      IF (K-I) 18,17,18                                                 PRCD1500
C                                                                       PRCD1510
C        TEST FOR SMALL DIVISOR                                         PRCD1520
   17 IF (ABS(Q(I+1))-POL(I+1)) 80,80,19                                PRCD1530
   18 Q(K+1) = Q(K+1)/Q(I+1)                                            PRCD1540
      POL(K+1) = POL(K+1)/ABS(Q(I+1))                                   PRCD1550
      E(K) = Q(K+1)-E(K)                                                PRCD1560
   19 CONTINUE                                                          PRCD1570
C                                                                       PRCD1580
   20 Q(IR) = -Q(IR)                                                    PRCD1590
C                                                                       PRCD1600
C            THE DISPLACEMENT EXPT IS SET TO 0 AUTOMATICALLY.           PRCD1610
C            E(ISTA)=0.,Q(ISTA+1),...,E(NSAV-1),Q(NSAV),E(NSAV)=0.,     PRCD1620
C            FORM A DIAGONAL OF THE QD-ARRAY.                           PRCD1630
C        INITIALIZATION OF BOUNDARY VALUES                              PRCD1640
   21 E(ISTA) = 0.                                                      PRCD1650
      NRAN = NSAV-1                                                     PRCD1660
   22 E(NRAN+1) = 0.                                                    PRCD1670
C                                                                       PRCD1680
C            TEST FOR LINEAR OR CONSTANT FACTOR                         PRCD1690
C        NRAN-ISTA IS DEGREE-1                                          PRCD1700
      IF (NRAN-ISTA) 24,23,31                                           PRCD1710
C                                                                       PRCD1720
C        LINEAR FACTOR                                                  PRCD1730
   23 Q(ISTA+1) = Q(ISTA+1)+EXPT                                        PRCD1740
      E(ISTA+1) = 0.                                                    PRCD1750
C                                                                       PRCD1760
C        TEST FOR UNFACTORED COMMON DIVISOR                             PRCD1770
   24 E(ISTA) = ESAV                                                    PRCD1780
      IF (IR-NSAV) 60,60,25                                             PRCD1790
C                                                                       PRCD1800
C        INITIALIZE QD-ALGORITHM FOR COMMON DIVISOR                     PRCD1810
   25 ISTA = NSAV                                                       PRCD1820
      ESAV = E(ISTA)                                                    PRCD1830
      GO TO 10                                                          PRCD1840
C                                                                       PRCD1850
C        COMPUTATION OF ROOT PAIR                                       PRCD1860
   26 P = P+EXPT                                                        PRCD1870
C                                                                       PRCD1880
C            TEST FOR REALITY                                           PRCD1890
      IF (Q) 27,28,28                                                   PRCD1900
C                                                                       PRCD1910
C            COMPLEX ROOT PAIR                                          PRCD1920
```

```
   27 C(NRAN) = P                                                        PRCD1930
      C(NRAN+1) = P                                                      PRCD1940
      E(NRAN) = T                                                        PRCD1950
      E(NRAN+1) = -T                                                     PRCD1960
      GO TO 29                                                           PRCD1970
C                                                                        PRCD1980
C           REAL ROOT PAIR                                               PRCD1990
   28 C(NRAN) = P-T                                                      PRCD2000
      C(NRAN+1) = P+T                                                    PRCD2010
      E(NRAN) = 0.                                                       PRCD2020
C                                                                        PRCD2030
C           REDUCTION OF DEGREE BY 2 (DEFLATION)                         PRCD2040
   29 NRAN = NRAN-2                                                      PRCD2050
      GO TO 22                                                           PRCD2060
C                                                                        PRCD2070
C        COMPUTATION OF REAL ROOT                                        PRCD2080
   30 C(NRAN+1) = EXPT+P                                                 PRCD2090
C                                                                        PRCD2100
C           REDUCTION OF DEGREE BY 1 (DEFLATION)                         PRCD2110
      NRAN = NRAN-1                                                      PRCD2120
      GO TO 22                                                           PRCD2130
C                                                                        PRCD2140
C        START GO-ITERATION                                              PRCD2150
   31 JBEG = ISTA+1                                                      PRCD2160
      JEND = NRAN-1                                                      PRCD2170
      TEPS = EPS                                                         PRCD2180
      TDELT = 1.E-2                                                      PRCD2190
   32 KOUNT = KOUNT+1                                                    PRCD2200
      P = C(NRAN+1)                                                      PRCD2210
      R = ABS(E(NRAN))                                                   PRCD2220
C                                                                        PRCD2230
C           TEST FOR CONVERGENCE                                         PRCD2240
      IF (R-TEPS) 30,30,33                                               PRCD2250
   33 S = ABS(E(JEND))                                                   PRCD2260
C                                                                        PRCD2270
C        IS THERE A REAL ROOT NEXT                                       PRCD2280
      IF (S-R) 38,38,34                                                  PRCD2290
C                                                                        PRCD2300
C        IS DISPLACEMENT SMALL ENOUGH                                    PRCD2310
   34 IF (R-TDELT) 36,35,35                                              PRCD2320
   35 P = 0.                                                             PRCD2330
   36 C = P                                                              PRCD2340
C                                                                        PRCD2350
      DO 37 J=JBEG,NRAN                                                  PRCD2360
      Q(J) = C(J)+E(J)-E(J-1)-0                                          PRCD2370
C                                                                        PRCD2380
C           TEST FOR SMALL DIVISOR                                       PRCD2390
      IF (ABS(Q(J))-POL(J)) 81,81,37                                     PRCD2400
```

```
   37 E(J) = C(J+1)*E(J)/Q(J)                                                PRCD2410
C                                                                            PRCD2420
      C(NRAN+1) = -E(NRAN)+C(NRAN+1)-C                                       PRCD2430
      GO TO 54                                                               PRCD2440
C                                                                            PRCD2450
C        CALCULATE DISPLACEMENT FOR DOUBLE ROOTS                             PRCD2460
C           CUADRATIC EQUATION FOR DOUBLE ROOTS                              PRCD2470
C           X**2-(Q(NRAN)+Q(NRAN+1)+E(NRAN))*X+C(NRAN)*C(NRAN+1)=0           PRCD2480
   38 P = 0.5*(Q(NRAN)+E(NRAN)+Q(NRAN+1))                                    PRCD2490
      Q = P*P-C(NRAN)*Q(NRAN+1)                                              PRCD2500
      T = SQRT(ABS(Q))                                                       PRCD2510
C                                                                            PRCD2520
C        TEST FOR CONVERGENCE                                                PRCD2530
      IF (S-TEPS) 26,26,39                                                   PRCD2540
C                                                                            PRCD2550
C        ARE THERE COMPLEX ROOTS                                             PRCD2560
   39 IF (Q) 43,40,40                                                        PRCD2570
   40 IF (P) 42,41,41                                                        PRCD2580
   41 T = -T                                                                 PRCD2590
   42 P = P+T                                                                PRCD2600
      R = S                                                                  PRCD2610
      GO TO 34                                                               PRCD2620
C                                                                            PRCD2630
C        MODIFICATION FOR COMPLEX ROOTS                                      PRCD2640
C        IS DISPLACEMENT SMALL ENOUGH                                        PRCD2650
   43 IF (S-TOELT) 44,35,35                                                  PRCD2660
C                                                                            PRCD2670
C        INITIALIZATION                                                      PRCD2680
   44 C = C(JBEG)+E(JBEG)-P                                                  PRCD2690
C                                                                            PRCD2700
C        TEST FOR SMALL DIVISOR                                              PRCD2710
      IF (ABS(C)-POL(JBEG)) 81,81,45                                         PRCD2720
   45 T = (T/C)**2                                                           PRCD2730
      U = E(JBEG)*Q(JBEG+1)/(Q*(1.+T))                                       PRCD2740
      V = Q+U                                                                PRCD2750
      KOUNT = KOUNT+2                                                        PRCD2760
C                                                                            PRCD2770
C        THREEFOLD LOOP FOR COMPLEX DISPLACEMENT                             PRCD2780
C                                                                            PRCD2790
      DO 53 J=JBEG,NRAN                                                      PRCD2800
      C = Q(J+1)+E(J+1)-U-P                                                  PRCD2810
C                                                                            PRCD2820
C        TEST FOR SMALL DIVISOR                                              PRCD2830
      IF (ABS(V)-POL(J)) 46,46,49                                            PRCD2840
   46 IF (J-NRAN) 81,47,81                                                   PRCD2850
   47 EXPT = EXPT+P                                                          PRCD2860
      IF (ABS(E(JEND))-TOL) 48,48,81                                         PRCD2870
   48 P = 0.5*(V+Q-E(JEND))                                                  PRCD2880
```

```
      C = P*P-(V-U)*(O-U*T-O*W*(1.+T)/C(JEND))                          PRCD2890
      T = SQRT(ABS(O))                                                  PRCD2900
      GO TO 26                                                          PRCD2910
C                                                                       PRCD2920
C           TEST FOR SMALL DIVISOR                                      PRCD2930
   49 IF (ABS(O)-POL(J+1)) 46,46,50                                     PRCD2940
   50 W = U*C/V                                                         PRCD2950
      T = T*(V/O)**2                                                    PRCD2960
      Q(J) = V+W-E(J-1)                                                 PRCD2970
      U = O.                                                            PRCD2980
      IF (J-NRAN) 51,52,52                                              PRCD2990
   51 U = Q(J+2)*E(J+1)/(C*(1.+T))                                      PRCD3000
   52 V = O+U-W                                                         PRCD3010
C                                                                       PRCD3020
C           TEST FOR SMALL DIVISOR                                      PRCD3030
      IF (ABS(Q(J))-POL(J)) 81,81,53                                    PRCD3040
   53 E(J) = W*V*(1.+T)/Q(J)                                            PRCD3050
C                                                                       PRCD3060
      C(NRAN+1) = V-E(NRAN)                                             PRCD3070
   54 EXPT = EXPT+P                                                     PRCD3080
      TEPS = TEPS*1.1                                                   PRCD3090
      TDELT = TDELT*1.1                                                 PRCD3100
      IF (KOUNT-LIMIT) 32,55,55                                         PRCD3110
C                                                                       PRCD3120
C           NO CONVERGENCE WITH FEASIBLE TOLERANCE                      PRCD3130
C              ERROR RETURN IN CASE OF UNSATISFACTORY CONVERGENCE       PRCD3140
   55 IER = 1                                                           PRCD3150
C                                                                       PRCD3160
C           REARRANGE CALCULATED ROOTS                                  PRCD3170
   56 IEND = NSAV-NRAN-1                                                PRCD3180
      E(ISTA) = ESAV                                                    PRCD3190
      IF (IEND) 59,59,57                                                PRCD3200
C                                                                       PRCD3210
   57 DO 58 I=1,IEND                                                    PRCD3220
      J = ISTA+I                                                        PRCD3230
      K = NRAN+1+I                                                      PRCD3240
      E(J) = E(K)                                                       PRCD3250
   58 C(J) = C(K)                                                       PRCD3260
C                                                                       PRCD3270
   59 IR = ISTA+IEND                                                    PRCD3280
C                                                                       PRCD3290
C           NORMAL RETURN                                               PRCD3300
   60 IR = IR-1                                                         PRCD3310
      IF (IR) 78,78,61                                                  PRCD3320
C                                                                       PRCD3330
C           REARRANGE CALCULATED ROOTS                                  PRCD3340
C                                                                       PRCD3350
   61 DO 62 I=1,IR                                                      PRCD3360
```

```
      C(I) = C(I+1)                                                     PRCD3370
   62 E(I) = E(I+1)                                                     PRCD3380
C                                                                       PRCD3390
C                                                                       PRCD3400
C        CALCULATE COEFFICIENT VECTOR FROM ROOTS                        PRCD3410
      POL(IR+1) = 1.                                                    PRCD3420
      IEND = IR-1                                                       PRCD3430
      JBEG = 1                                                          PRCD3440
C                                                                       PRCD3450
      DO 69 J=1,IR                                                      PRCD3460
      ISTA = IR+1-J                                                     PRCD3470
      Q = 0.                                                            PRCD3480
      P = Q(ISTA)                                                       PRCD3490
      T = E(ISTA)                                                       PRCD3500
      IF (T) 65,63,65                                                   PRCD3510
C                                                                       PRCD3520
C        MULTIPLY WITH LINEAR FACTOR                                    PRCD3530
C                                                                       PRCD3540
   63 DO 64 I=ISTA,IR                                                   PRCD3550
      POL(I) = Q-P*POL(I+1)                                             PRCD3560
   64 Q = POL(I+1)                                                      PRCD3570
C                                                                       PRCD3580
      GO TO 69                                                          PRCD3590
   65 GO TO (66,67), JBEG                                               PRCD3600
   66 JBEG = 2                                                          PRCD3610
      POL(ISTA) = 0.                                                    PRCD3620
      GO TO 69                                                          PRCD3630
C                                                                       PRCD3640
C        MULTIPLY WITH QUADRATIC FACTOR                                 PRCD3650
   67 JBEG = 1                                                          PRCD3660
      U = P*P+T*T                                                       PRCD3670
      P = P+P                                                           PRCD3680
C                                                                       PRCD3690
      DO 68 I=ISTA,IEND                                                 PRCD3700
      POL(I) = Q-P*POL(I+1)+U*POL(I+2)                                  PRCD3710
   68 Q = POL(I+1)                                                      PRCD3720
C                                                                       PRCD3730
      POL(IR) = Q-P                                                     PRCD3740
   69 CONTINUE                                                          PRCD3750
C                                                                       PRCD3760
      IF (IER) 78,70,78                                                 PRCD3770
C                                                                       PRCD3780
C        COMPARISON OF COEFFICIENT VECTORS, IE. TEST OF ACCURACY        PRCD3790
   70 P = 0.                                                            PRCD3800
C                                                                       PRCD3810
      DO 75 I=1,IR                                                      PRCD3820
      IF (C(I)) 72,71,72                                                PRCD3830
   71 Q = ABS(POL(I))                                                   PRCD3840
```

```
      GO TO 73                                                          PRQD3850
   72 C = ABS((POL(I)-C(I))/C(I))                                       PRQD3860
   73 IF (P-C) 74,75,75                                                 PRQD3870
   74 P = C                                                             PRQD3880
   75 CONTINUE                                                          PRQD3890
C                                                                       PRQD3900
      IF (P-TOL) 77,76,76                                               PRQD3910
   76 IER = -1                                                          PRQD3920
   77 C(IR+1) = P                                                       PRQD3930
      E(IR+1) = 0.                                                      PRQD3940
   78 RETURN                                                            PRQD3950
C                                                                       PRQD3960
C        ERROR RETURNS                                                  PRQD3970
C           ERROR RETURN FOR POLYNOMIALS OF DEGREE LESS THAN 1          PRQD3980
   79 IER = 2                                                           PRQD3990
      IR = 0                                                            PRQD4000
      RETURN                                                            PRQD4010
C                                                                       PRQD4020
C           ERROR RETURN IF THERE EXISTS NO S-FRACTION                  PRQD4030
   80 IER = 4                                                           PRQD4040
      IR = ISTA                                                         PRQD4050
      GO TO 60                                                          PRQD4060
C                                                                       PRQD4070
C           ERROR RETURN IN CASE OF INSTABLE QD-ALGORITHM               PRQD4080
   81 IER = 3                                                           PRQD4090
      GO TO 56                                                          PRQD4100
      END                                                               PRQD4110
```

```
C     ..................................................................PRBM   10
C                                                                       PRBM   20
C        SUBROUTINE PRBM                                                PRBM   30
C                                                                       PRBM   40
C        PURPOSE                                                        PRBM   50
C           TO CALCULATE ALL REAL AND COMPLEX ROOTS OF A GIVEN          PRBM   60
C           POLYNOMIAL WITH REAL COEFFICIENTS.                          PRBM   70
C                                                                       PRBM   80
C        USAGE                                                          PRBM   90
C           CALL PRBM (C,IC,RR,RC,POL,IR,IER)                           PRBM  100
C                                                                       PRBM  110
C        DESCRIPTION OF PARAMETERS                                      PRBM  120
C           C       - INPUT VECTOR CONTAINING THE COEFFICIENTS OF THE   PRBM  130
C                     GIVEN POLYNOMIAL. COEFFICIENTS ARE ORDERED FROM   PRBM  140
C                     LOW TO HIGH. ON RETURN COEFFICIENTS ARE DIVIDED   PRBM  150
C                     BY THE LAST NONZERO TERM.                         PRBM  160
C           IC      - DIMENSION OF VECTORS C, RR, RC, AND POL.          PRBM  170
C           RR      - RESULTANT VECTOR OF REAL PARTS OF THE ROOTS.      PRBM  180
C           RC      - RESULTANT VECTOR OF COMPLEX PARTS OF THE ROOTS.   PRBM  190
C           POL     - RESULTANT VECTOR OF COEFFICIENTS OF THE POLYNOMIAL PRBM 200
C                     WITH CALCULATED ROOTS. COEFFICIENTS ARE ORDERED   PRBM  210
C                     FROM LOW TO HIGH (SEE REMARK 4).                  PRBM  220
C           IR      - OUTPUT VALUE SPECIFYING THE NUMBER OF CALCULATED  PRBM  230
C                     ROOTS. NORMALLY IR IS EQUAL TO IC-1.              PRBM  240
C           IER     - RESULTANT ERROR PARAMETER CODED AS FOLLOWS        PRBM  250
C                       IER=0   - NO ERROR,                             PRBM  260
C                       IER=1   - SUBROUTINE PQFB RECORDS POOR CONVERGENCE PRBM 270
C                                 AT SOME QUADRATIC FACTORIZATION WITHIN PRBM 280
C                                 50 ITERATION STEPS,                   PRBM  290
C                       IER=2   - POLYNOMIAL IS DEGENERATE, I.E. ZERO OR PRBM 300
C                                 CONSTANT,                             PRBM  310
C                                 OR OVERFLOW IN NORMALIZATION OF GIVEN PRBM  320
C                                 POLYNOMIAL,                           PRBM  330
C                       IER=3   - THE SUBROUTINE IS BYPASSED DUE TO     PRBM  340
C                                 SUCCESSIVE ZERO DIVISORS OR OVERFLOWS PRBM  350
C                                 IN QUADRATIC FACTORIZATION OR DUE TO  PRBM  360
C                                 COMPLETELY UNSATISFACTORY ACCURACY,   PRBM  370
C                       IER=-1  - CALCULATED COEFFICIENT VECTOR HAS LESS PRBM 380
C                                 THAN THREE CORRECT SIGNIFICANT DIGITS.PRBM  390
C                                 THIS REVEALS POOR ACCURACY OF CALCULATED PRBM 400
C                                 ROOTS.                                PRBM  410
C                                                                       PRBM  420
C        REMARKS                                                        PRBM  430
C           (1) REAL PARTS OF THE ROOTS ARE STORED IN RR(1) UP TO RR(IR)PRBM  440
C               AND CORRESPONDING COMPLEX PARTS IN RC(1) UP TO RC(IR).  PRBM  450
C           (2) ERROR MESSAGE IER=1 INDICATES POOR CONVERGENCE WITHIN   PRBM  460
C               50 ITERATION STEPS AT SOME QUADRATIC FACTORIZATION      PRBM  470
C               PERFORMED BY SUBROUTINE PQFB.                           PRBM  480
```

```
C          (3) NO ACTION BESIDES ERROR MESSAGE IER=2 IN CASE OF A ZERO   PRBM 490
C              OR CONSTANT POLYNOMIAL. THE SAME ERROR MESSAGE IS GIVEN   PRBM 500
C              IN CASE OF AN OVERFLOW IN NORMALIZATION OF GIVEN          PRBM 510
C              POLYNOMIAL.                                               PRBM 520
C          (4) ERROR MESSAGE IER=3 INDICATES SUCCESSIVE ZERO DIVISORS    PRBM 530
C              OR OVERFLOWS OR COMPLETELY UNSATISFACTORY ACCURACY AT     PRBM 540
C              ANY QUADRATIC FACTORIZATION PERFORMED BY                  PRBM 550
C              SUBROUTINE PQFB. IN THIS CASE CALCULATION IS BYPASSED.    PRBM 560
C              IR RECORDS THE NUMBER OF CALCULATED ROOTS.                PRBM 570
C              POL(1),...,POL(J-IR) ARE THE COEFFICIENTS OF THE          PRBM 580
C              REMAINING POLYNOMIAL, WHERE J IS THE ACTUAL NUMBER OF     PRBM 590
C              COEFFICIENTS IN VECTOR C (NORMALLY J=IC).                 PRBM 600
C          (5) IF CALCULATED COEFFICIENT VECTOR HAS LESS THAN THREE      PRBM 610
C              CORRECT SIGNIFICANT DIGITS THOUGH ALL QUADRATIC           PRBM 620
C              FACTORIZATIONS SHOWED SATISFACTORY ACCURACY, THE ERROR    PRBM 630
C              MESSAGE IER=-1 IS GIVEN.                                  PRBM 640
C          (6) THE FINAL COMPARISON BETWEEN GIVEN AND CALCULATED         PRBM 650
C              COEFFICIENT VECTOR IS PERFORMED ONLY IF ALL ROOTS HAVE     PRBM 660
C              BEEN CALCULATED. IN THIS CASE THE NUMBER OF ROOTS IR IS    PRBM 670
C              EQUAL TO THE ACTUAL DEGREE OF THE POLYNOMIAL (NORMALLY     PRBM 680
C              IR=IC-1). THE MAXIMAL RELATIVE ERROR OF THE COEFFICIENT    PRBM 690
C              VECTOR IS RECORDED IN RR(IR+1).                           PRBM 700
C                                                                        PRBM 710
C      SUBROUTINES AND FUNCTION SUBPROGRAMS REQUIRED                     PRBM 720
C         SUBROUTINE PQFB      QUADRATIC FACTORIZATION OF A POLYNOMIAL   PRBM 730
C                              BY BAIRSTOW ITERATION.                    PRBM 740
C                                                                        PRBM 750
C      METHOD                                                            PRBM 760
C         THE ROOTS OF THE POLYNOMIAL ARE CALCULATED BY MEANS OF         PRBM 770
C         SUCCESSIVE QUADRATIC FACTORIZATION PERFORMED BY BAIRSTOW       PRBM 780
C         ITERATION. X**2 IS USED AS INITIAL GUESS FOR THE FIRST         PRBM 790
C         QUADRATIC FACTOR, AND FURTHER EACH CALCULATED QUADRATIC        PRBM 800
C         FACTOR IS USED AS INITIAL GUESS FOR THE NEXT ONE. AFTER        PRBM 810
C         COMPUTATION OF ALL ROOTS THE COEFFICIENT VECTOR IS             PRBM 820
C         CALCULATED AND COMPARED WITH THE GIVEN ONE.                    PRBM 830
C         FOR REFERENCE, SEE J. H. WILKINSON, THE EVALUATION OF THE      PRBM 840
C         ZEROS OF ILL-CONDITIONED POLYNOMIALS (PART ONE AND TWO),       PRBM 850
C         NUMERISCHE MATHEMATIK, VOL.1 (1959), PP.150-180.               PRBM 860
C                                                                        PRBM 870
      SUBROUTINE PRBM (C,IC,RR,RC,POL,IR,IER)                           PRBM 880
C                                                                        PRBM 890
C                                                                        PRBM 900
      DIMENSION C(1), RR(1), RC(1), POL(1), Q(4)                        PRBM 910
C                                                                        PRBM 920
C     TEST ON LEADING ZERO COEFFICIENTS                                  PRBM 930
      EPS = 1.E-3                                                       PRBM 940
      LIM = 50                                                          PRBM 950
      IR = IC+1                                                         PRBM 960
```

```
    1 IR = IR-1                                                          PRBM 970
      IF (IR-1) 42,42,2                                                  PRBM 980
    2 IF (C(IR)) 3,1,3                                                   PRBM 990
C                                                                        PRBM1000
C        WORK UP ZERO ROOTS AND NORMALIZE REMAINING POLYNOMIAL           PRBM1010
    3 IER = 0                                                            PRBM1020
      J = IR                                                             PRBM1030
      L = 0                                                              PRBM1040
      A = C(IR)                                                          PRBM1050
C                                                                        PRBM1060
      DO 8 I=1,IR                                                        PRBM1070
      IF (L) 4,4,7                                                       PRBM1080
    4 IF (C(I)) 6,5,6                                                    PRBM1090
    5 RR(I) = 0.                                                         PRBM1100
      RC(I) = 0.                                                         PRBM1110
      POL(J) = 0.                                                        PRBM1120
      J = J-1                                                            PRBM1130
      GO TO 8                                                            PRBM1140
    6 L = 1                                                              PRBM1150
      IST = I                                                            PRBM1160
      J = 0                                                              PRBM1170
    7 J = J+1                                                            PRBM1180
      C(I) = C(I)/A                                                      PRBM1190
      POL(J) = C(I)                                                      PRBM1200
      CALL OVERFL (N)                                                    PRBM1210
      IF (N-2) 42,8,8                                                    PRBM1220
    8 CONTINUE                                                           PRBM1230
C                                                                        PRBM1240
C                                                                        PRBM1250
C        START BAIRSTOW ITERATION                                        PRBM1260
      Q1 = 0.                                                            PRBM1270
      Q2 = 0.                                                            PRBM1280
    9 IF (J-2) 33,10,14                                                  PRBM1290
C                                                                        PRBM1300
C        DEGREE OF RESTPOLYNOMIAL IS EQUAL TO ONE                        PRBM1310
   10 A = POL(1)                                                         PRBM1320
      RR(IST) = -A                                                       PRBM1330
      RC(IST) = 0.                                                       PRBM1340
      IR = IR-1                                                          PRBM1350
      Q2 = 0.                                                            PRBM1360
      IF (IR-1) 13,13,11                                                 PRBM1370
C                                                                        PRBM1380
   11 DO 12 I=2,IR                                                       PRBM1390
      Q1 = Q2                                                            PRBM1400
      Q2 = POL(I+1)                                                      PRBM1410
   12 POL(I) = A*Q2+Q1                                                   PRBM1420
C                                                                        PRBM1430
   13 POL(IR+1) = A+Q2                                                   PRBM1440
```

```
      GO TO 34                                                          PRBM1450
C        THIS IS BRANCH TO COMPARISON OF COEFFICIENT VECTORS C AND POL  PRBM1460
C                                                                       PRBM1470
CCC      DEGREE OF RESTPOLYNOMIAL IS GREATER THAN ONE                   PRBM1480
C                                                                       PRBM1490
   14 DO 22 L=1,10                                                      PRBM1500
      N = 1                                                             PRBM1510
   15 C(1) = C1                                                         PRBM1520
      C(2) = C2                                                         PRBM1530
      CALL PDFB (POL,J,C,LIM,I)                                         PRBM1540
      IF (I) 16,24,23                                                   PRBM1550
   16 IF (C1) 18,17,18                                                  PRBM1560
   17 IF (C2) 18,21,18                                                  PRBM1570
   18 GO TO (19,20,19,21), N                                            PRBM1580
   19 C1 = -C1                                                          PRBM1590
      N = N+1                                                           PRBM1600
      GO TO 15                                                          PRBM1610
   20 C2 = -C2                                                          PRBM1620
      N = N+1                                                           PRBM1630
      GO TO 15                                                          PRBM1640
   21 C1 = 1.+C1                                                        PRBM1650
   22 C2 = 1.-C2                                                        PRBM1660
C                                                                       PRBM1670
C                                                                       PRBM1680
C        ERROR EXIT DUE TO UNSATISFACTORY RESULTS OF FACTORIZATION      PRBM1690
      IER = 2                                                           PRBM1700
      IR = IR-J                                                         PRBM1710
      RETURN                                                            PRBM1720
C                                                                       PRBM1730
C        WORK UP RESULTS OF QUADRATIC FACTORIZATION                     PRBM1740
   23 IER = 1                                                           PRBM1750
   24 C1 = C(1)                                                         PRBM1760
      C2 = C(2)                                                         PRBM1770
C                                                                       PRBM1780
C        PERFORM DIVISION OF FACTORIZED POLYNOMIAL BY QUADRATIC FACTOR  PRBM1790
      B = 0.                                                            PRBM1800
      A = 0.                                                            PRBM1810
      I = J                                                             PRBM1820
   25 H = -C1*B-C2*A+POL(I)                                             PRBM1830
      POL(I) = B                                                        PRBM1840
      B = A                                                             PRBM1850
      A = H                                                             PRBM1860
      I = I-1                                                           PRBM1870
      IF (I-2) 26,26,25                                                 PRBM1880
   26 POL(2) = B                                                        PRBM1890
      POL(1) = A                                                        PRBM1900
C                                                                       PRBM1910
C        MULTIPLY POLYNOMIAL WITH CALCULATED ROOTS BY QUADRATIC FACTOR  PRBM1920
```

```
      L = IR-1                                                          PRBM1930
      IF (J-L) 27,27,29                                                 PRBM1940
C                                                                       PRBM1950
   27 DO 28 I=J,L                                                       PRBM1960
   28 POL(I-1) = POL(I-1)+POL(I)*C2+POL(I+1)*C1                         PRBM1970
C                                                                       PRBM1980
   29 POL(L) = POL(L)+POL(L+1)*C2+C1                                    PRBM1990
      POL(IR) = POL(IR)+C2                                              PRBM2000
C                                                                       PRBM2010
C        CALCULATE ROOT-PAIR FROM QUADRATIC FACTOR X*X+C2*X+C1          PRBM2020
      P = -.5*C2                                                        PRBM2030
      A = H*P-C1                                                        PRBM2040
      B = SQRT(ABS(A))                                                  PRBM2050
      IF (A) 30,30,31                                                   PRBM2060
   30 RR(IST) = P                                                       PRBM2070
      RC(IST) = B                                                       PRBM2080
      IST = IST+1                                                       PRBM2090
      RR(IST) = P                                                       PRBM2100
      RC(IST) = -B                                                      PRBM2110
      GO TO 32                                                          PRBM2120
   31 B = H+SIGN(B,H)                                                   PRBM2130
      RR(IST) = C1/B                                                    PRBM2140
      RC(IST) = 0.                                                      PRBM2150
      IST = IST+1                                                       PRBM2160
      RR(IST) = B                                                       PRBM2170
      RC(IST) = 0.                                                      PRBM2180
   32 IST = IST+1                                                       PRBM2190
      J = J-2                                                           PRBM2200
      GO TO 9                                                           PRBM2210
C                                                                       PRBM2220
C        SHIFT BACK ELEMENTS OF POL BY 1 AND COMPARE VECTORS POL AND C  PRBM2230
   33 IR = IR-1                                                         PRBM2240
   34 A = 0.                                                            PRBM2250
C                                                                       PRBM2260
      DO 38 I=1,IR                                                      PRBM2270
      C1 = C(I)                                                         PRBM2280
      C2 = POL(I+1)                                                     PRBM2290
      POL(I) = C2                                                       PRBM2300
      IF (C1) 35,36,35                                                  PRBM2310
   35 C2 = (C1-C2)/C1                                                   PRBM2320
   36 C2 = ABS(C2)                                                      PRBM2330
      IF (C2-A) 38,38,37                                                PRBM2340
   37 A = C2                                                            PRBM2350
   38 CONTINUE                                                          PRBM2360
C                                                                       PRBM2370
      I = IR+1                                                          PRBM2380
      POL(I) = 1.                                                       PRBM2390
      RR(I) = A                                                         PRBM2400
```

```
      R(I) = 0.                                                          PRBM2410
      IF (IER) 39,39,41                                                  PRBM2420
   39 IF (A-EPS) 41,41,40                                                PRBM2430
C                                                                        PRBM2440
C        WARNING DUE TO POOR ACCURACY OF CALCULATED COEFFICIENT VECTOR   PRBM2450
   40 IER = -1                                                           PRBM2460
   41 RETURN                                                             PRBM2470
C                                                                        PRBM2480
C        ERROR EXIT DUE TO DEGENERATE POLYNOMIAL OR OVERFLOW IN          PRBM2490
C        NORMALIZATION                                                   PRBM2500
   42 IER = 2                                                            PRBM2510
      IR = 0                                                             PRBM2520
      RETURN                                                             PRBM2530
      END                                                                PRBM2540
```

```
C ..........................................................PQFB   10
C                                                            PQFB   20
C     SUBROUTINE PQFB                                        PQFB   30
C                                                            PQFB   40
C     PURPOSE                                                PQFB   50
C        TO FIND AN APPROXIMATION Q(X)=Q1+Q2*X+X*X TO A QUADRATIC PQFB   60
C        FACTOR OF A GIVEN POLYNOMIAL P(X) WITH REAL COEFFICIENTS. PQFB   70
C                                                            PQFB   80
C     USAGE                                                  PQFB   90
C        CALL PQFB(C,IC,Q,LIM,IER)                           PQFB  100
C                                                            PQFB  110
C     DESCRIPTION OF PARAMETERS                              PQFB  120
C        C   - INPUT VECTOR CONTAINING THE COEFFICIENTS OF P(X) - PQFB  130
C              C(1) IS THE CONSTANT TERM (DIMENSION IC)      PQFB  140
C        IC  - DIMENSION OF C                                PQFB  150
C        Q   - VECTOR OF DIMENSION 4 - ON INPUT Q(1) AND Q(2) MUST PQFB  160
C              CONTAIN INITIAL GUESSES FOR Q1 AND Q2 - ON RETURN Q(1)PQFB  170
C              AND Q(2) CONTAIN THE REFINED COEFFICIENTS Q1 AND Q2 OFPQFB  180
C              Q(X), WHILE Q(3) AND Q(4) CONTAIN THE COEFFICIENTS A PQFB  190
C              AND B OF A+B*X, WHICH IS THE REMAINDER OF THE QUOTIENTPQFB  200
C              OF P(X) BY Q(X)                               PQFB  210
C        LIM - INPUT VALUE SPECIFYING THE MAXIMUM NUMBER OF  PQFB  220
C              ITERATIONS TO BE PERFORMED                    PQFB  230
C        IER - RESULTING ERROR PARAMETER (SEE REMARKS)       PQFB  240
C              IER= 0 - NO ERROR                             PQFB  250
C              IER= 1 - NO CONVERGENCE WITHIN LIM ITERATIONS PQFB  260
C              IER=-1 - THE POLYNOMIAL P(X) IS CONSTANT OR UNDEFINED PQFB  270
C                     - OR OVERFLOW OCCURRED IN NORMALIZING P(X) PQFB  280
C              IER=-2 - THE POLYNOMIAL P(X) IS OF DEGREE 1   PQFB  290
C              IER=-3 - NO FURTHER REFINEMENT OF THE APPROXIMATION TOPQFB  300
C                       A QUADRATIC FACTOR IS FEASIBLE, DUE TO EITHERPQFB  310
C                       DIVISION BY 0, OVERFLOW OR AN INITIAL GUESS PQFB  320
C                       THAT IS NOT SUFFICIENTLY CLOSE TO A FACTOR OFPQFB  330
C                       P(X)                                 PQFB  340
C                                                            PQFB  350
C     REMARKS                                                PQFB  360
C        (1)  IF IER=-1 THERE IS NO COMPUTATION OTHER THAN THE PQFB  370
C             POSSIBLE NORMALIZATION OF C.                   PQFB  380
C        (2)  IF IER=-2 THERE IS NO COMPUTATION OTHER THAN THE PQFB  390
C             NORMALIZATION OF C.                            PQFB  400
C        (3)  IF IER =-3  IT IS SUGGESTED THAT A NEW INITIAL GUESS BEPQFB  410
C             MADE FOR A QUADRATIC FACTOR.  Q, HOWEVER, WILL CONTAIN PQFB  420
C             THE VALUES ASSOCIATED WITH THE ITERATION THAT YIELDED PQFB  430
C             THE SMALLEST NORM OF THE MODIFIED LINEAR REMAINDER. PQFB  440
C        (4)  IF IER=1, THEN, ALTHOUGH THE NUMBER OF ITERATIONS LIM PQFB  450
C             WAS TOO SMALL TO INDICATE CONVERGENCE, NO OTHER PROB- PQFB  460
C             LEMS HAVE BEEN DETECTED, AND Q WILL CONTAIN THE VALUES PQFB  470
C             ASSOCIATED WITH THE ITERATION THAT YIELDED THE SMALLESTPQFB  480
```

```
C             NORM OF THE MODIFIED LINEAR REMAINDER.                    PQFB 490
C          (5) FOR COMPLETE DETAIL SEE THE DOCUMENTATION FOR            PQFB 500
C              SUBROUTINES PQFB AND DPQFB.                              PQFB 510
C                                                                       PQFB 520
C       SUBROUTINES AND FUNCTION SUBPROGRAMS REQUIRED                   PQFB 530
C          NONE                                                         PQFB 540
C                                                                       PQFB 550
C       METHOD                                                          PQFB 560
C          COMPUTATION IS BASED ON BAIRSTOW'S ITERATIVE METHOD.  (SEE   PQFB 570
C          WILKINSON, J.H., THE EVALUATION OF THE ZEROS OF ILL-CON-     PQFB 580
C          DITIONED POLYNOMIALS (PART ONE AND TWO), NUMERISCHE MATHE-   PQFB 590
C          MATIK, VOL.1 (1959), PP. 150-180, OR HILDEBRAND, F.B.,       PQFB 600
C          INTRODUCTION TO NUMERICAL ANALYSIS, MC GRAW-HILL, NEW YORK/  PQFB 610
C          TORONTO/LONDON, 1956, PP. 472-476.)                          PQFB 620
C                                                                       PQFB 630
C  .....PQFB 640
C                                                                       PQFB 650
      SUBROUTINE PQFB (C,IC,Q,LIM,IER)                                  PQFB 660
C                                                                       PQFB 670
C                                                                       PQFB 680
      DIMENSION C(1), Q(1)                                              PQFB 690
C                                                                       PQFB 700
C        TEST ON LEADING ZERO COEFFICIENTS                              PQFB 710
      IER = 0                                                           PQFB 720
      J = IC+1                                                          PQFB 730
    1 J = J-1                                                           PQFB 740
      IF (J-1) 40,40,2                                                  PQFB 750
    2 IF (C(J)) 3,1,3                                                   PQFB 760
C                                                                       PQFB 770
C        NORMALIZATION OF REMAINING COEFFICIENTS                        PQFB 780
    3 A = C(J)                                                          PQFB 790
      IF (A-1.) 4,6,4                                                   PQFB 800
C                                                                       PQFB 810
    4 DO 5 I=1,J                                                        PQFB 820
      C(I) = C(I)/A                                                     PQFB 830
      CALL OVERFL (N)                                                   PQFB 840
      IF (N-2) 40,5,5                                                   PQFB 850
    5 CONTINUE                                                          PQFB 860
C                                                                       PQFB 870
C                                                                       PQFB 880
C        TEST ON NECESSITY OF BAIRSTOW ITERATION                        PQFB 890
    6 IF (J-3) 41,38,7                                                  PQFB 900
C                                                                       PQFB 910
C        PREPARE BAIRSTOW ITERATION                                     PQFB 920
    7 EPS = 1.E-6                                                       PQFB 930
      EPS1 = 1.E-3                                                      PQFB 940
      L = 0                                                             PQFB 950
      LL = 0                                                            PQFB 960
```

```
      C1 = C(1)                                                        PQFB 970
      C2 = Q(2)                                                        PQFB 980
      CC1 = 0.                                                         PQFB 990
      CC2 = 0.                                                         PQFB1000
      AA = C(1)                                                        PQFB1010
      BE = C(2)                                                        PQFB1020
      CE = ABS(AA)                                                     PQFB1030
      CA = ABS(BB)                                                     PQFB1040
      IF (CE-CA) 8,9,10                                                PQFB1050
    8 CC = CB+CB                                                       PQFB1060
      CE = CB/CA                                                       PQFB1070
      CA = 1.                                                          PQFB1080
      GO TO 11                                                         PQFB1090
    9 CC = CA+CA                                                       PQFB1100
      CA = 1.                                                          PQFB1110
      CE = 1.                                                          PQFB1120
      GO TO 11                                                         PQFB1130
   10 CC = CA+CA                                                       PQFB1140
      CA = CA/CB                                                       PQFB1150
      CE = 1.                                                          PQFB1160
   11 CE = CC*.1                                                       PQFB1170
C                                                                      PQFB1180
C        START BAIRSTOW ITERATION                                      PQFB1190
C        PREPARE NESTED MULTIPLICATION                                 PQFB1200
   12 A = 0.                                                           PQFB1210
      B = A                                                            PQFB1220
      A1 = A                                                           PQFB1230
      B1 = A                                                           PQFB1240
      I = J                                                            PQFB1250
      CCC1 = C1                                                        PQFB1260
      CCC2 = C2                                                        PQFB1270
      DC1 = HH                                                         PQFB1280
      DC2 = H                                                          PQFB1290
C                                                                      PQFB1300
C        START NESTED MULTIPLICATION                                   PQFB1310
   13 H = -Q1*B-Q2*A+C(I)                                              PQFB1320
      CALL OVERFL (N)                                                  PQFB1330
      IF (N-2) 42,14,14                                                PQFB1340
   14 B = A                                                            PQFB1350
      A = H                                                            PQFB1360
      I = I-1                                                          PQFB1370
      IF (I-1) 18,15,16                                                PQFB1380
   15 H = 0.                                                           PQFB1390
   16 H = -Q1*B1-Q2*A1+H                                               PQFB1400
      CALL OVERFL (N)                                                  PQFB1410
      IF (N-2) 42,17,17                                                PQFB1420
   17 C1 = B1                                                          PQFB1430
      B1 = A1                                                          PQFB1440
```

```
      A1 = H                                                                PQFB1450
      GO TO 13                                                              PQFB1460
C        END OF NESTED MULTIPLICATION                                       PQFB1470
CC                                                                          PQFB1480
C        TEST ON SATISFACTORY ACCURACY                                      PQFB1490
   18 H = CA*ABS(A)+CB*ABS(B)                                               PQFB1500
      IF (LL) 19,19,39                                                      PQFB1510
   19 L = L+1                                                               PQFB1520
      IF (ABS(A)-EPS*ABS(C(1))) 20,20,21                                    PQFB1530
   20 IF (ABS(B)-EPS*ABS(C(2))) 39,39,21                                    PQFB1540
C                                                                           PQFB1550
C        TEST ON LINEAR REMAINDER OF MINIMUM NORM                           PQFB1560
   21 IF (H-CC) 22,22,23                                                    PQFB1570
   22 AA = A                                                                PQFB1580
      BB = B                                                                PQFB1590
      CC = H                                                                PQFB1600
      CC1 = C1                                                              PQFB1610
      CC2 = C2                                                              PQFB1620
C                                                                           PQFB1630
C        TEST ON LAST ITERATION STEP                                        PQFB1640
   23 IF (L-LIM) 28,28,24                                                   PQFB1650
C                                                                           PQFB1660
C        TEST ON RESTART OF BAIRSTOW ITERATION WITH ZERO INITIAL GUESS      PQFB1670
   24 IF (H-CD) 43,43,25                                                    PQFB1680
   25 IF (Q(1)) 27,26,27                                                    PQFB1690
   26 IF (Q(2)) 27,42,27                                                    PQFB1700
   27 Q(1) = 0.                                                             PQFB1710
      Q(2) = 0.                                                             PQFB1720
      GO TO 7                                                               PQFB1730
C                                                                           PQFB1740
C        PERFORM ITERATION STEP                                             PQFB1750
   28 HH = AMAX1(ABS(A1),ABS(B1),ABS(C1))                                   PQFB1760
      IF (HH) 42,42,29                                                      PQFB1770
   29 A1 = A1/HH                                                            PQFB1780
      B1 = B1/HH                                                            PQFB1790
      C1 = C1/HH                                                            PQFB1800
      H = A1*C1-B1*B1                                                       PQFB1810
      IF (H) 30,42,30                                                       PQFB1820
   30 A = A/HH                                                              PQFB1830
      B = B/HH                                                              PQFB1840
      HH = (B*A1-A*B1)/H                                                    PQFB1850
      H = (A*C1-B*B1)/H                                                     PQFB1860
      Q1 = Q1+HH                                                            PQFB1870
      Q2 = Q2+H                                                             PQFB1880
C        END OF ITERATION STEP                                              PQFB1890
C                                                                           PQFB1900
C        TEST ON SATISFACTORY RELATIVE ERROR OF ITERATED VALUES             PQFB1910
      IF (ABS(HH)-EPS*ABS(Q1)) 31,31,33                                     PQFB1920
```

```
   31 IF (ABS(H)-EPS*ABS(Q2)) 32,32,33                                  PQFB1930
   32 LL = 1                                                            PQFB1940
      GO TO 12                                                          PQFB1950
C                                                                       PQFB1960
C        TEST ON DECREASING RELATIVE ERRORS                             PQFB1970
   33 IF (L-1) 12,12,34                                                 PQFB1980
   34 IF (ABS(HH)-EPS1*ABS(Q1)) 35,35,12                                PQFB1990
   35 IF (ABS(H)-EPS1*ABS(Q2)) 36,36,12                                 PQFB2000
   36 IF (ABS(QQQ1*HH)-ABS(C1*DQ1)) 37,44,44                            PQFB2010
   37 IF (ABS(QQQ2*H)-ABS(C2*DQ2)) 12,44,44                             PQFB2020
C        END OF BAIRSTOW ITERATION                                      PQFB2030
C                                                                       PQFB2040
C        EXIT IN CASE OF QUADRATIC POLYNOMIAL                           PQFB2050
   38 Q(1) = C(1)                                                       PQFB2060
      Q(2) = C(2)                                                       PQFB2070
      Q(3) = 0.                                                         PQFB2080
      Q(4) = 0.                                                         PQFB2090
      RETURN                                                            PQFB2100
C                                                                       PQFB2110
C        EXIT IN CASE OF SUFFICIENT ACCURACY                            PQFB2120
   39 Q(1) = C1                                                         PQFB2130
      Q(2) = C2                                                         PQFB2140
      Q(3) = A                                                          PQFB2150
      Q(4) = B                                                          PQFB2160
      RETURN                                                            PQFB2170
C                                                                       PQFB2180
C        ERROR EXIT IN CASE OF ZERO OR CONSTANT POLYNOMIAL              PQFB2190
   40 IER = -1                                                          PQFB2200
      RETURN                                                            PQFB2210
C                                                                       PQFB2220
C        ERROR EXIT IN CASE OF LINEAR POLYNOMIAL                        PQFB2230
   41 IER = -2                                                          PQFB2240
      RETURN                                                            PQFB2250
C                                                                       PQFB2260
C        ERROR EXIT IN CASE OF NONREFINED QUADRATIC FACTOR              PQFB2270
   42 IER = -3                                                          PQFB2280
      GO TO 44                                                          PQFB2290
C                                                                       PQFB2300
C        ERROR EXIT IN CASE OF UNSATISFACTORY ACCURACY                  PQFB2310
   43 IER = 1                                                           PQFB2320
   44 Q(1) = QQ1                                                        PQFB2330
      Q(2) = QQ2                                                        PQFB2340
      Q(3) = AA                                                         PQFB2350
      Q(4) = BB                                                         PQFB2360
      RETURN                                                            PQFB2370
      END                                                               PQFB2380
```

```
C++++++
```

```
    5 FORMAT ('0',72('*'),//,' WARNING----COEFFICIENT OF HIGHEST ORDER TCONO 490
     1ERM IS ZERO.',/,' EXECUTION OF SUBROUTINE CONORM TERMINATING WITHCCONO 500
     2UT NORMALIZING',/,' THE COEFFICIENT VECTOR.',//,72('*'))          CONO 510
       END                                                              CONO 520
```

```
C++++                                                                  ++++CGRAP  10
C                                                                             GRAP  20
C                                                                             GRAP  30
      SUBROUTINE GRAPH (NBODE,NYQST,NICHOL)                                   GRAP  40
      INTEGER *4ITB(12)/12*0/                                                 GRAP  50
      REAL *4NTITLE                                                           GRAP  60
      REAL *4TITLE1(12),TITLE2(12),TITLE3(12),TITLE4(12)                      GRAP  70
      REAL *4TITLE5(12),TITLE6(12)                                            GRAP  80
      REAL *4SCALE(2)/2*0.0/,SCALE1(2)/2*-120./,SCALE2(2)/2*0.C/,RTE(28)GRAP  90
     1/28*0.0/                                                                GRAP 100
      DATA TITLE1/'BODE',' PLC','T --','- GA','IN(D','B)  ','VS. ',' FREGRAP 110
     1','CUEN','CY(R','ACIA','NS) '/                                          GRAP 120
      DATA TITLE2/'BODE',' PLC','T --','- PH','ASE(','DEG)',' VS.',' FREGRAP 130
     1','CUEN','CY(R','ACIA','NS) '/                                          GRAP 140
      DATA TITLE3/'NICH','OLS ','PLOT',' ---',' GAI','N(DB',')  V','S.  GRAP 150
     1','PHAS','E(DE','GREE','S)  '/                                          GRAP 160
      DATA TITLE4/'   ','   ','   ',' NY','QUIS','T PL','OT O','F AC','TUALGRAP 170
     1',' SYS','TEM ','   ','   ','   '/                                     GRAP 180
      DATA TITLE5/'MAGN','ITUD','E DI','FFER','ENCE','(DB)',' VS.',' FREGRAP 190
     1','CUEN','CY(R','ACIA','NS) '/                                          GRAP 200
      DATA TITLE6/'PHAS','E DI','FFER','ENCE','(DEG','REES',') VS','. FRGRAP 210
     1','EQUE','NCY(','RADI','ANS)'/                                          GRAP 220
      COMMON NCN,NCD,NTFN,NTFD,NOMEG,A(20),B(20),CMAG(500),DQPHSD(500),WGRAP 230
     1FREQ(500),NSN,NSD,COFASN(40),COFASD(40),CMAG(500),CR(500),CI(500),GRAP 240
     2CPHSR(500),QPHSD(500),N1,N2,N3,N4,PI,T,WS,IZCF,ADMAG(500),NTITLE(1GRAP 250
     32),FREQ(500),AMAG(500),NMINFS,CCFWRK(40),IPLCT,WFREQS(500),SAPHSD(GRAP 260
     45C0),SAMAG(500),DIFF1(500),DIFF2(500),ICCST,CFWRK1(40)                  GRAP 270
      IF (IPLCT.EQ.1) GC TO 13                                                GRAP 280
      IF (NBODE) 3,1,2                                                        GRAP 290
    1 WRITE (6,34)                                                            GRAP 300
      WRITE (6,35)                                                            GRAP 310
      WRITE (6,36)                                                            GRAP 320
      WRITE (6,37) NTITLE                                                     GRAP 330
      WRITE (6,35)                                                            GRAP 340
      CALL PLCTP (FREQ,AMAG,NOMEG,1)                                          GRAP 350
      CALL PLCTP (WFREQS,SAMAG,500,2)                                         GRAP 360
      CALL PLCTP (FREQ,ADMAG,NOMEG,3)                                         GRAP 370
      WRITE (6,34)                                                            GRAP 380
      WRITE (6,35)                                                            GRAP 390
      WRITE (6,38)                                                            GRAP 400
      WRITE (6,37) NTITLE                                                     GRAP 410
      WRITE (6,35)                                                            GRAP 420
      CALL PLCTP (FREQ,CPHSD,NOMEG,1)                                         GRAP 430
      CALL PLCTP (WFREQS,SAPHSD,500,2)                                        GRAP 440
      CALL PLCTP (FREQ,DQPHSD,NOMEG,3)                                        GRAP 450
      GC TO 4                                                                 GRAP 460
    2 WRITE (6,35)                                                            GRAP 470
      WRITE (6,39)                                                            GRAP 480
```

```
      WRITE (6,35)                                                      GRAP 490
      GO TO 4                                                           GRAP 500
    3 WRITE (6,35)                                                      GRAP 510
      WRITE (6,40)                                                      GRAP 520
      WRITE (6,35)                                                      GRAP 530
    4 CONTINUE                                                          GRAP 540
      IF (NICHOL) 7,5,6                                                 GRAP 550
    5 WRITE (6,34)                                                      GRAP 560
      WRITE (6,35)                                                      GRAP 570
      WRITE (6,41)                                                      GRAP 580
      WRITE (6,37) NTITLE                                               GRAP 590
      WRITE (6,35)                                                      GRAP 600
      CALL PLOTP (QPHSD,AMAG,NOMEG,1)                                   GRAP 610
      CALL PLOTP (SAPHSD,SAMAG,500,2)                                   GRAP 620
      CALL PLOTP (DQPHSD,ADMAG,NOMEG,3)                                 GRAP 630
      GO TO 8                                                           GRAP 640
    6 WRITE (6,35)                                                      GRAP 650
      WRITE (6,42)                                                      GRAP 660
      WRITE (6,35)                                                      GRAP 670
      GO TO 8                                                           GRAP 680
    7 WRITE (6,35)                                                      GRAP 690
      WRITE (6,43)                                                      GRAP 700
    8 CONTINUE                                                          GRAP 710
      IF (NYQST) 11,9,10                                                GRAP 720
    9 WRITE (6,34)                                                      GRAP 730
      WRITE (6,35)                                                      GRAP 740
      WRITE (6,44)                                                      GRAP 750
      WRITE (6,37) NTITLE                                               GRAP 760
      WRITE (6,35)                                                      GRAP 770
      CALL PLOTP (QR,QI,500,0)                                          GRAP 780
      GO TO 12                                                          GRAP 790
   10 WRITE (6,35)                                                      GRAP 800
      WRITE (6,45)                                                      GRAP 810
      WRITE (6,35)                                                      GRAP 820
      GO TO 12                                                          GRAP 830
   11 WRITE (6,35)                                                      GRAP 840
      WRITE (6,46)                                                      GRAP 850
      WRITE (6,35)                                                      GRAP 860
   12 CONTINUE                                                          GRAP 870
      WRITE (6,34)                                                      GRAP 880
      WRITE (6,35)                                                      GRAP 890
      WRITE (6,47)                                                      GRAP 900
      WRITE (6,37) NTITLE                                               GRAP 910
      WRITE (6,35)                                                      GRAP 920
      CALL PLOTP (FREQ,DIFF1,NOMEG,0)                                   GRAP 930
      WRITE (6,34)                                                      GRAP 940
      WRITE (6,35)                                                      GRAP 950
      WRITE (6,48)                                                      GRAP 960
```

```
      WRITE (6,37) NTITLE                                                GRAP 970
      WRITE (6,35)                                                       GRAP 980
      CALL PLOTP (FREQ,DIFF2,NOMEG,0)                                    GRAP 990
      RETURN                                                             GRAP1000
C                                                                        GRAP1010
   13 DO 14 I=1,NOMEG                                                    GRAP1020
      X1 = SCALE(1)                                                      GRAP1030
      X2 = SCALE(2)                                                      GRAP1040
      XX1 = SCALE1(1)                                                    GRAP1050
      XX2 = SCALE1(2)                                                    GRAP1060
      XXX1 = SCALE2(1)                                                   GRAP1070
      XXX2 = SCALE2(2)                                                   GRAP1080
      Z1 = AMAG(I)                                                       GRAP1090
      Z2 = ADMAG(I)                                                      GRAP1100
      Z3 = OPHSD(I)                                                      GRAP1110
      Z4 = DOPHSD(I)                                                     GRAP1120
      Z5 = FREQ(I)                                                       GRAP1130
      SCALE(1) = AMAX1(X1,Z1,Z2)                                         GRAP1140
      SCALE(2) = AMIN1(X2,Z1,Z2)                                         GRAP1150
      SCALE1(1) = AMAX1(XX1,Z3,Z4)                                       GRAP1160
      SCALE1(2) = AMIN1(XX2,Z3,Z4)                                       GRAP1170
      SCALE2(1) = AMAX1(XXX1,Z5)                                         GRAP1180
      SCALE2(2) = AMIN1(XXX2,Z5)                                         GRAP1190
   14 CONTINUE                                                           GRAP1200
C                                                                        GRAP1210
C                                                                        GRAP1220
      DO 15 J=1,500                                                      GRAP1230
      SCALE(1) = AMAX1(SCALE(1),SAMAG(J))                                GRAP1240
      SCALE(2) = AMIN1(SCALE(2),SAMAG(J))                                GRAP1250
      SCALE1(1) = AMAX1(SCALE1(1),SAPHSE(J))                             GRAP1260
      SCALE1(2) = AMIN1(SCALE1(2),SAPHSE(J))                             GRAP1270
   15 CONTINUE                                                           GRAP1280
C                                                                        GRAP1290
      IF (NBODE) 20,16,19                                                GRAP1300
C                                                                        GRAP1310
   16 DO 17 I=1,12                                                       GRAP1320
      RTE(I+4) = NTITLE(I)                                               GRAP1330
      RTE(I+16) = TITLE1(I)                                              GRAP1340
   17 CONTINUE                                                           GRAP1350
C                                                                        GRAP1360
C                                                                        GRAP1370
C    SET UP AND PLOT GAIN(DB) VS. FREQUENCY                              GRAP1380
C                                                                        GRAP1390
      ITE(1) = 1                                                         GRAP1400
      ITE(2) = 2                                                         GRAP1410
      ITE(3) = 5                                                         GRAP1420
      ITE(4) = 6                                                         GRAP1430
      CALL DRAWP (2,SCALE2,SCALE,ITB,RTE)                                GRAP1440
```

```
      ITB(1) = 2                                                        GRAP1450
      ITB(2) = 4                                                        GRAP1460
      CALL DRAWP (NOMEG,FREQ,ADMAG,ITB,RTB)                             GRAP1470
      ITB(1) = 2                                                        GRAP1480
      ITB(2) = 1                                                        GRAP1490
      CALL DRAWP (NOMEG,FREQ,AMAG,ITB,RTB)                              GRAP1500
      ITB(1) = 3                                                        GRAP1510
      ITB(2) = 0                                                        GRAP1520
      CALL DRAWP (500,WFREQS,SAMAG,ITB,RTB)                             GRAP1530
C                                                                       GRAP1540
      DO 18 I=1,12                                                      GRAP1550
      RTB(I+16) = TITLE2(I)                                             GRAP1560
   18 CONTINUE                                                          GRAP1570
C                                                                       GRAP1580
      ITB(1) = 1                                                        GRAP1590
      ITB(2) = 2                                                        GRAP1600
      ITB(3) = 9                                                        GRAP1610
      ITB(4) = 6                                                        GRAP1620
      CALL DRAWP (2,SCALE2,SCALE1,ITB,RTB)                              GRAP1630
      ITB(1) = 2                                                        GRAP1640
      ITB(2) = 4                                                        GRAP1650
      CALL DRAWP (NOMEG,FREQ,DQPHSD,ITB,RTB)                            GRAP1660
      ITB(1) = 2                                                        GRAP1670
      ITB(2) = 1                                                        GRAP1680
      CALL DRAWP (NOMEG,FREQ,QPHSD,ITB,RTB)                             GRAP1690
      ITB(1) = 3                                                        GRAP1700
      ITB(2) = 0                                                        GRAP1710
      CALL DRAWP (500,WFREQS,SAPHSD,ITB,RTB)                            GRAP1720
      WRITE (6,35)                                                      GRAP1730
      WRITE (6,49)                                                      GRAP1740
      WRITE (6,35)                                                      GRAP1750
      GO TO 21                                                          GRAP1760
   19 WRITE (6,35)                                                      GRAP1770
      WRITE (6,39)                                                      GRAP1780
      WRITE (6,35)                                                      GRAP1790
      GO TO 21                                                          GRAP1800
   20 WRITE (6,35)                                                      GRAP1810
      WRITE (6,40)                                                      GRAP1820
      WRITE (6,35)                                                      GRAP1830
   21 IF (NICHOL) 25,22,24                                              GRAP1840
C                                                                       GRAP1850
   22 DO 23 I=1,12                                                      GRAP1860
      RTB(I+16) = TITLE3(I)                                             GRAP1870
   23 CONTINUE                                                          GRAP1880
C                                                                       GRAP1890
      ITB(1) = 1                                                        GRAP1900
      ITB(2) = 2                                                        GRAP1910
      ITB(3) = 6                                                        GRAP1920
```

```
      ITE(4) = 9                                                        GRAP1930
      CALL DRAWP (2,SCALE1,SCALE,ITB,RTE)                               GRAP1940
      ITE(1) = 2                                                        GRAP1950
      ITE(2) = 4                                                        GRAP1960
      CALL DRAWP (NOMEG,DCPHSD,ADMAG,ITE,PTB)                           GRAP1970
      ITE(1) = 2                                                        GRAP1980
      ITE(2) = 1                                                        GRAP1990
      CALL DRAWP (NOMEG,CPHSD,AMAG,ITB,RTB)                             GRAP2000
      ITE(1) = 3                                                        GRAP2010
      ITE(2) = 0                                                        GRAP2020
      CALL DRAWP (500,SAPHSD,SAMAG,ITB,RTB)                             GRAP2030
      WRITE (6,35)                                                      GRAP2040
      WRITE (6,50)                                                      GRAP2050
      WRITE (6,35)                                                      GRAP2060
      GO TO 26                                                          GRAP2070
   24 WRITE (6,35)                                                      GRAP2080
      WRITE (6,42)                                                      GRAP2090
      WRITE (6,35)                                                      GRAP2100
      GO TO 26                                                          GRAP2110
   25 WRITE (6,35)                                                      GRAP2120
      WRITE (6,43)                                                      GRAP2130
      WRITE (6,35)                                                      GRAP2140
   26 IF (NYQST) 30,27,25                                               GRAP2150
C                                                                       GRAP2160
   27 DO 28 I=1,12                                                      GRAP2170
      RTE(I+16) = TITLE4(I)                                             GRAP2180
   28 CONTINUE                                                          GRAP2190
C                                                                       GRAP2200
      ITE(1) = 0                                                        GRAP2210
      ITE(2) = 0                                                        GRAP2220
      ITE(3) = 8                                                        GRAP2230
      ITE(4) = 8                                                        GRAP2240
      CALL DRAWP (500,QR,QI,ITB,RTB)                                    GRAP2250
      WRITE (6,35)                                                      GRAP2260
      WRITE (6,51)                                                      GRAP2270
      WRITE (6,35)                                                      GRAP2280
      GO TO 31                                                          GRAP2290
   29 WRITE (6,35)                                                      GRAP2300
      WRITE (6,45)                                                      GRAP2310
      WRITE (6,35)                                                      GRAP2320
      GO TO 31                                                          GRAP2330
   30 WRITE (6,35)                                                      GRAP2340
      WRITE (6,46)                                                      GRAP2350
      WRITE (6,35)                                                      GRAP2360
   31 CONTINUE                                                          GRAP2370
C                                                                       GRAP2380
      DO 32 I=1,12                                                      GRAP2390
      RTE(I+16) = TITLE5(I)                                             GRAP2400
```

```
   32 CONTINUE                                                          GRAP2410
C                                                                       GRAP2420
      ITE(1) = 0                                                        GRAP2430
      ITE(2) = 5                                                        GRAP2440
      ITE(3) = 9                                                        GRAP2450
      ITE(4) = 6                                                        GRAP2460
      CALL DRAWP (NOMEG,FREQ,DIFF1,ITE,RTB)                             GRAP2470
C                                                                       GRAP2480
      DO 33 I=1,12                                                      GRAP2490
      RTE(I+16) = TITLE6(I)                                             GRAP2500
   33 CONTINUE                                                          GRAP2510
C                                                                       GRAP2520
      CALL DRAWP (NOMEG,FREQ,DIFF2,ITE,RTB)                             GRAP2530
      RETURN                                                            GRAP2540
C                                                                       GRAP2550
   34 FORMAT ('1')                                                      GRAP2560
   35 FORMAT (' ',80('='))                                              GRAP2570
   36 FORMAT ('0',20X,'BODE PLOT --- GAIN(DB)  VS.  FREQUENCY (RADIANS)'GRAP2580
     1)                                                                 GRAP2590
   37 FORMAT ('0',10X,'TITLE --- ',12A4,/)                              GRAP2600
   38 FORMAT ('0',20X,'BODE PLOT --- PHASE(DEGREES)  VS.  FREQUENCY (RADGRAP2610
     1IANS)')                                                           GRAP2620
   39 FORMAT ('0',10X,'BODE PLOT NOT DESIRED',/)                        GRAP2630
   40 FORMAT ('0',80('*'),/,5('*'),3X,'ERROR EXISTS IN GRAPH SELECTION  GRAP2640
     1 NUMBER',/,5X,'NBODE.  THIS NUMBER SHOULD NOT BE NEGATIVE; CHECK',GRAP2650
     2/,5X,'DATA DECK FOR POSSIBLE ERRORS.',/,'0',80('*'))              GRAP2660
   41 FORMAT ('0',20X,'NICHOLS PLOT')                                   GRAP2670
   42 FORMAT ('0',10X,'NICHOLS PLOT NOT DESIRED',/)                     GRAP2680
   43 FORMAT ('0',80('*'),/,5('*'),3X,'ERROR EXISTS IN GRAPH SELECTION  GRAP2690
     1 NUMBER',/,5X,'NICHOL.  THIS NUMBER SHOULD NOT BE NEGATIVE; CHECK'GRAP2700
     2,/,5X,'DATA DECK FOR POSSIBLE ERRORS.',/,'0',80('*'))             GRAP2710
   44 FORMAT ('0',20X,'NYQUIST PLOT')                                   GRAP2720
   45 FORMAT ('0',10X,'NYQUIST PLOT NOT DESIRED',/)                     GRAP2730
   46 FORMAT ('0',80('*'),/,5('*'),3X,'ERROR EXISTS IN GRAPH SELECTION  GRAP2740
     1 NUMBER',/,5X,'NYQST.  THIS NUMBER SHOULD NOT BE NEGATIVE; CHECK',GRAP2750
     2/,5X,'DATA DECK FOR POSSIBLE ERRORS.',/,'0',80('*'))              GRAP2760
   47 FORMAT ('0',10X,'MAGNITUDE DIFFERENCE IN DB VS. FREQUENCY(RADS)') GRAP2770
   48 FORMAT ('0',10X,'PHASE DIFFERENCE(DEGREES) VS. FREQUENCY(RADS)')  GRAP2780
   49 FORMAT ('0',10X,'BODE PLOT HAS BEEN DRAWN',/)                     GRAP2790
   50 FORMAT ('0',10X,'NICHOLS PLOT HAS BEEN DRAWN',/)                  GRAP2800
   51 FORMAT ('0',10X,'NYQUIST PLOT HAS BEEN DRAWN',/)                  GRAP2810
      END                                                               GRAP2820
```

```
      FUNCTION KE (X)                                                    KE     10
      DIMENSION X(24), Y(12), Z(12)                                      KE     20
      COMMON NCN,NCD,NTFN,NTFD,NOMEG,A(20),B(20),CMAG(500),DQPHSD(500),WKE     30
     1FREQ(500),NSN,NSD,COFASN(40),COFASD(40),CMAG(500),CR(500),CI(500),KE     40
     2CPHSR(500),CPHSD(500),N1,N2,N3,N4,PI,T,WS,IZOF,ADMAG(500),NTITLE(1KE     50
     32),FREQ(500),AMAG(500),NMINFS,CCFWRK(40),IPLOT,WFREQS(500),SAPHSD(KE     60
     45CC),SAMAG(500),DIFF1(500),DIFF2(500),ICOST,CFWRK1(40)             KE     70
      KE = 0                                                             KE     80
C                                                                        KE     90
      DO 1 I=1,N1                                                        KE    100
      Y(I) = X(I)                                                        KE    110
    1 CONTINUE                                                           KE    120
C                                                                        KE    130
C                                                                        KE    140
      DO 2 J=1,N2                                                        KE    150
      Z(J) = X(N1+J)                                                     KE    160
    2 CONTINUE                                                           KE    170
C                                                                        KE    180
C COMPUTE THE SYSTEM OPEN LOOP NUMERATOR AND DENOMINATOR POLYNOMIALS    CKE    190
C                                                                       CKE    200
      CALL PMPY (COFASN,N7,Y,N1,A,N3)                                    KE    210
      CALL PMPY (COFASD,N8,Z,N2,B,N4)                                    KE    220
      NSN = N7-1                                                         KE    230
      NSD = N8-1                                                         KE    240
      CALL PVAL (COFASN,NSN,0.0,WFREQ(1),CNUMR,CNUMI)                    KE    250
      CALL PVAL (COFASD,NSD,0.0,WFREQ(1),CDENR,CDENI)                    KE    260
      IF (ABS(CNUMR).GT.2.9E+37) K=1                                     KE    270
      IF (ABS(CNUMI).GT.2.9E+37) K=1                                     KE    280
      IF (ABS(CDENR).GT.2.9E+37) K=1                                     KE    290
      IF (ABS(CDENI).GT.2.9E+37) K=1                                     KE    300
      IF (KE.EQ.1) WRITE (6,5)                                           KE    310
      IF (KE.EQ.1) GO TO 4                                               KE    320
      IF (NMINFS.EQ.1) GO TO 3                                           KE    330
C                                                                       CKE    340
C CHECK FOR RIGHT HALF PLANE ROOTS OF COMPENSATOR NUMERATOR             CKE    350
C                                                                       CKE    360
      CALL PINVRT (Y,N1)                                                 KE    370
      CALL ROUTH (Y,N1,ISTN)                                             KE    380
      CALL PINVRT (Y,N1)                                                 KE    390
      KE = ISTN                                                          KE    400
      IF (KE.EQ.1) GO TO 4                                               KE    410
C                                                                       CKE    420
C CHECK FOR RIGHT HALF PLANE ROOTS OF COMPENSATOR DENOMINATOR           CKE    430
C                                                                       CKE    440
    3 CALL PINVRT (Z,N2)                                                 KE    450
      CALL ROUTH (Z,N2,ISTD)                                             KE    460
      CALL PINVRT (Z,N2)                                                 KE    470
      KE = ISTD                                                          KE    480
```

```
      IF (KE.EQ.1) GO TO 4                                                  KE   490
    4 RETURN                                                                KE   500
C                                                                           KE   510
    5 FORMAT ('0',80('-'),/,' ',4(' * * * WARNING * * *'),/,'0','THE SIZKE   520
     1E OF THE REAL AND IMAGINARY PARTS OF THE NUMERATOR AND DENOMINATORKE   530
     2',/,' ','ARE CLOSE TO THE MAXIMUM VALUE THAT THE COMPUTER CAN HANDKE   540
     3LE.  FREQUENCY',/,' ','SCALING OF THE PROBLEM IS RECOMMENDED TO ALKE   550
     4LEVIATE THE PROBLEM',/,'0',4(' * * * WARNING * * *'),/,' ',80('-')KE   560
     5)                                                                     KE   570
      END                                                                   KE   580
```

```
      FUNCTION FE (X)                                                          FE    10
      DIMENSION X(24), Y(12), Z(12)                                            FE    20
      COMMON NCN,NCD,NTFN,NTFD,NOMEG,A(20),B(20),CMAG(500),DOPHSD(500),WFE     30
     1FREQ(500),NSN,NSD,COFASN(40),COFASD(40),QMAG(500),CR(500),CI(500),FE     40
     2CPHSR(500),CPHSD(500),N1,N2,N3,N4,PI,T,WS,IZOF,ADMAG(500),NTITLE(1FE     50
     32),FREQ(500),AMAG(500),NMINFS,CCFWRK(40),IPLCT,WFREQS(500),SAPHSD(FE     60
     4500),SAMAG(500),DIFF1(500),DIFF2(500),ICOST,CFWRK1(40)                   FE    70
      PHICHK = 0.0                                                             FE    80
      ICELNU = 0                                                               FE    90
      ICELDE = 0                                                               FE   100
      PHI = 0.0                                                                FE   110
      IPHI = 0                                                                 FE   120
      PSICHK = 0.0                                                             FE   130
      PSI = 0.0                                                                FE   140
      IPSI = 0                                                                 FE   150
C                                                                              FE   160
      DO 1 I=1,N1                                                              FE   170
      Y(I) = X(I)                                                              FE   180
    1 CONTINUE                                                                 FE   190
C                                                                              FE   200
C                                                                              FE   210
      DO 2 I=1,N2                                                              FE   220
      Z(I) = X(N1+I)                                                           FE   230
    2 CONTINUE                                                                 FE   240
C                                                                              FE   250
C COMPUTE SYSTEM OPEN LOOP NUMERATOR COEFFICENTS AS BOXPLX CHANGES        CFE  260
C THE COMPENSATOR PARAMETERS                                              CFE  270
C                                                                         CFE  280
      CALL PMPY (COFASN,N7,Y,N1,A,N3)                                          FE   290
      CALL PMPY (COFASD,N8,Z,N2,B,N4)                                          FE   300
      NSN = N7-1                                                               FE   310
      NSD = N8-1                                                               FE   320
      COST = 0.0                                                               FE   330
C                                                                         CFE  340
C COMPUTE OPEN LOOP FREQUENCY RESPONSE OF SYSTEM AT THE DISCRETE          CFE  350
C FREQUENCIES SPECIFIED                                                   CFE  360
C                                                                              FE   370
      DO 20 K=1,NOMEG                                                          FE   380
      CALL PVAL (COFASN,NSN,0.0,WFREQ(K),CNUMR,CNUMI)                          FE   390
      CALL PVAL (COFASD,NSD,0.0,WFREQ(K),CDENR,CDENI)                          FE   400
      IF (ABS(CNUMR).GT.3.E+37) CNUMR=SIGN(3.E+37,CNUMR)                       FE   410
      IF (ABS(CNUMI).GT.3.E+37) CNUMI=SIGN(3.E+37,CNUMI)                       FE   420
      IF (ABS(CDENR).GT.3.E+37) CDENR=SIGN(3.E+37,CDENR)                       FE   430
      IF (ABS(CDENI).GT.3.E+37) CDENI=SIGN(3.E+37,CDENI)                       FE   440
      IF (SQRT(CDENI**2+CDENR**2)) 4,3,4                                       FE   450
    3 CMAG(K) = 1.E+20                                                         FE   460
      CR(K) = 1.E+20                                                           FE   470
      CI(K) = 1.E+20                                                           FE   480
```

```
      GO TO 5                                                                   FE    490
    4 QMAG(K) = SQRT(QNUMI**2+QNUMR**2)/SQRT(QDENI**2+QDENR**2)                 FE    500
C                                                                               CFE   510
C ADJUST MAGNITUDE RESPONSE IF ZERO ORDER HOLD IS PRESENT IN THE SYSTEM         CFE   520
C                                                                               CFE   530
      IF (IZOH.EQ.1) QMAG(K)=QMAG(K)*ABS((SIN(PI*WFREQ(K)/WS))/(PI*WFREQ        FE    540
     1(K)/WS))                                                                  FE    550
      QR(K) = (QNUMR*QDENR+QNUMI*QDENI)/(QDENR**2+QDENI**2)                     FE    560
      QI(K) = (QNUMI*QDENR-QNUMR*QDENI)/(QDENR**2+QDENI**2)                     FE    570
    5 IF ((QNUMI.EQ.0.0).AND.(QNUMR.EQ.0.0)) QNUMR=1.0                          FE    580
      ANGNUR = ATAN2(QNUMI,QNUMR)                                               FE    590
      ANGNUD = ANGNUR*57.29578                                                  FE    600
      IF (ANGNUD.LT.0.0) ANGNUD=360.0+ANGNUD                                    FE    610
      DELPHI = ANGNUD-PHI                                                       FE    620
      IF (IDELNU.EQ.0) GO TO 8                                                  FE    630
      IF (DELPHI.GE.0.0.AND.IDELNU.EQ.1) GO TO 8                                FE    640
      IF (DELPHI.LT.0.0.AND.IDELNU.EQ.1) GO TO 6                                FE    650
      IF (DELPHI.GE.0.0.AND.IDELNU.EQ.-1) GO TO 7                               FE    660
      IF (DELPHI.LT.0.0.AND.IDELNU.EQ.-1) GO TO 8                               FE    670
    6 IF (ABS(DELPHI).LT.180.0) GO TO 8                                         FE    680
      DELPHI = ANGNUD+360.0-PHI                                                 FE    690
      GO TO 8                                                                   FE    700
    7 IF (ABS(DELPHI).LT.180.0) GO TO 8                                         FE    710
      DELPHI = ANGNUD-360.0-PHI                                                 FE    720
    8 PHICHK = PHICHK+DELPHI                                                    FE    730
      IPHI = PHICHK/360.0                                                       FE    740
      PHI = ANGNUD                                                              FE    750
      ANGNUD = ANGNUD+IPHI*360.0                                                FE    760
      ANGDER = ATAN2(QDENI,QDENR)                                               FE    770
      ANGDED = ANGDER*57.29578                                                  FE    780
      IF (ANGDED.LT.0.0) ANGDED=360.0+ANGDED                                    FE    790
      DELPSI = ANGDED-PSI                                                       FE    800
      IF (IDELDE.EQ.0) GO TO 11                                                 FE    810
      IF (DELPSI.GE.0.0.AND.IDELDE.EQ.1) GO TO 11                               FE    820
      IF (DELPSI.LT.0.0.AND.IDELDE.EQ.1) GO TO 9                                FE    830
      IF (DELPSI.GE.0.0.AND.IDELDE.EQ.-1) GO TO 10                              FE    840
      IF (DELPSI.LT.0.0.AND.IDELDE.EQ.-1) GO TO 11                              FE    850
    9 IF (ABS(DELPSI).LT.180.0) GO TO 11                                        FE    860
      DELPSI = ANGDED+360.0-PSI                                                 FE    870
      GO TO 11                                                                  FE    880
   10 IF (ABS(DELPSI).LT.180.0) GO TO 11                                        FE    890
      DELPSI = ANGDED-360.0-PSI                                                 FE    900
   11 PSICHK = PSICHK+DELPSI                                                    FE    910
      IPSI = PSICHK/360.0                                                       FE    920
      PSI = ANGDED                                                              FE    930
      ANGDED = ANGDED+IPSI*360.0                                                FE    940
      IF (DELPHI.GE.0.0) IDELNU=1                                               FE    950
      IF (DELPHI.LT.0.0) IDELNU=-1                                              FE    960
```

```
      IF (DELPSI.GE.0.0) IDELDE=1                                          FE    970
      IF (DELPSI.LT.0.0) IDELDE=-1                                         FE    980
      DPHSD(K) = ANGNUD-ANGDED                                             FE    990
      DPHSR(K) = ANGNUR-ANGDER                                             FE   1000
      IF (IZOH.NE.1) GO TO 12                                              FE   1010
      IWS = WFREQ(K)/WS                                                    FE   1020
C                                                                          CFE   1030
C ADJUST PHASE RESPONSE IF ZERO ORDER HOLD IS PRESENT IN THE SYSTEM        CFE   1040
C                                                                          CFE   1050
      QPHSD(K) = QPHSD(K)-(PI*WFREQ(K)/WS)*57.29578-IWS*180.0              FE   1060
   12 IF (ICOST) 14,14,13                                                  FE   1070
   13 GO TO (14,15,16,17,18,19), ICOST                                     FE   1080
   14 COST = COST+(1.0-QMAG(K)/DMAG(K))**2+(1.0-QPHSD(K)/DQPHSD(K))**2     FE   1090
      GO TO 20                                                             FE   1100
   15 COST = COST+(1.0-QMAG(K)/DMAG(K))**2                                 FE   1110
      GO TO 20                                                             FE   1120
   16 COST = COST+(1.0-QPHSD(K)/DQPHSD(K))**2                              FE   1130
      GO TO 20                                                             FE   1140
   17 COST = COST+ABS(1.0-QMAG(K)/DMAG(K))+ABS(1.0-QPHSD(K)/DQPHSD(K))     FE   1150
      GO TO 20                                                             FE   1160
   18 COST = COST+ABS(1.0-QMAG(K)/DMAG(K))                                 FE   1170
      GO TO 20                                                             FE   1180
   19 COST = COST+ABS(1.0-QPHSD(K)/DQPHSD(K))                              FE   1190
   20 CONTINUE                                                             FE   1200
C                                                                          FE   1210
      FE = COST                                                            FE   1220
      RETURN                                                               FE   1230
C                                                                          FE   1240
      END                                                                  FE   1250
```

```
C++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++C
C++++++++++++++++++        SUBROUTINE PMPY        ++++++++++++++++++++++C
C++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++C
C++++                                                                      ++++C
C++++ PURPOSE: TO MULTIPLY THE COEFFICIENTS OF TWO POLYNOMIALS AND         ++++C
C++++          RETURN THE COEFFICIENTS OF THE RESULTING POLYNOMIAL.        ++++C
C++++          POLYNOMIALS TO BE MULTIPLIED MUST HAVE REAL                 ++++C
C++++          COEFFICIENTS, BUT NEED NOT BE OF THE SAME ORDER.            ++++C
C++++                                                                      ++++C
C++++ CALLING SEQUENCE:                                                    ++++C
C++++ CALL PMPY(Z,IDIMZ,X,IDIMX,Y,IDIMY)                                   ++++C
C++++                                                                      ++++C
C++++ DESCRIPTION OF PARAMETERS:                                           ++++C
C++++ Z       = VECTOR OF RESULTANT COEFFICIENTS, ORDERED IN                ++++C
C++++           ASCENDING POWERS OF THE INDEPENDENT VARIABLE.              ++++C
C++++ IDIMZ   = CALCULATED DIMENSION OF THE RESULTING POLYNOMIAL            ++++C
C++++           VECTOR Z.                                                  ++++C
C++++ X       = VECTOR OF COEFFICIENTS OF FIRST POLYNOMIAL TO BE            ++++C
C++++           MULTIPLIED IN ASCENDING POWERS OF THE INDEPENDENT          ++++C
C++++           VARIABLE.                                                  ++++C
C++++ IDIMX   = DIMENSION OF THE VECTOR X.                                 ++++C
C++++ Y       = VECTOR OF COEFFICIENTS OF THE SECOND POLYNOMIAL TO          ++++C
C++++           BE MULTIPLIED ORDERED IN ASCENDING POWERS OF THE            ++++C
C++++           INDEPENDENT VARIABLE.                                      ++++C
C++++ IDIMY   = DIMENSION OF THE VECTOR Y.                                 ++++C
C++++                                                                      ++++C
C++++ SUBROUTINES AND FUNCTION SUBPROGRAMS REQUIRED:                       ++++C
C++++     NONE                                                             ++++C
C++++                                                                      ++++C
C++++ METHOD:                                                              ++++C
C++++ THE COEFFICIENTS OF THE RESULTANT POLYNOMIAL ARE CALCULATED           ++++C
C++++ AS THE SUM OF PRODUCTS OF THE COEFFICIENTS OF THE INPUT               ++++C
C++++ POLYNOMIALS WHOSE EXPONENTS ADD UP TO FORM THE CORRESPONDING          ++++C
C++++ EXPONENT OF THE RESULTING COEFFICIENTS.                               ++++C
C++++                                                                      ++++C
C++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++C
C++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++C
C
      SUBROUTINE PMPY (Z,IDIMZ,X,IDIMX,Y,IDIMY)
      DIMENSION Z(1), X(1), Y(1)
C
      IF (IDIMX*IDIMY) 1,1,2
    1 IDIMZ = 0
      GO TO 5
    2 IDIMZ = IDIMX+IDIMY-1
C
      DO 3 I=1,IDIMZ
    3 Z(I) = 0.
```

```
C                                                                       490
C                                                                       500
      DO 4 I=1,IDIMX                                                    510
C                                                                       520
      DO 4 J=1,IDIMY                                                    530
      K = I+J-1                                                         540
    4 Z(K) = X(I)*Y(J)+Z(K)                                             550
C                                                                       560
    5 RETURN                                                            570
      END                                                               580
```

```
C     ..........................................................BXPL  10
CCC                                                            BXPL  20
      SUBROUTINE BOXPLX              (CATEGORY F0)             BXPL  30
CCC                                                            BXPL  40
      PURPOSE                                                  BXPL  50
CCC                                                            BXPL  60
         BOXPLX IS A SUBROUTINE USED TO SOLVE THE PROBLEM OF LOCATING   BXPL  70
         A MINIMUM (OR MAXIMUM) OF AN ARBITRARY OBJECTIVE FUNCTION      BXPL  80
         SUBJECT TO ARBITRARY EXPLICIT AND/OR IMPLICIT CONSTRAINTS BY   BXPL  90
         THE COMPLEX METHOD OF M.J. BOX.  EXPLICIT CONSTRAINTS ARE      BXPL 100
         DEFINED AS UPPER AND LOWER BOUNDS ON THE INDEPENDENT VARIABLES.BXPL 110
         IMPLICIT CONSTRAINTS MAY BE ARBITRARY FUNCTIONS OF THE VAR-    BXPL 120
         IABLES.  TWO FUNCTION SUBPROGRAMS TO EVALUATE THE OBJECTIVE    BXPL 130
         FUNCTION AND IMPLICIT CONSTRAINTS, RESPECTIVELY, MUST BE       BXPL 140
         SUPPLIED BY THE USER (SEE EXAMPLE BELOW).  BOXPLX ALSO HAS     BXPL 150
         THE OPTION TO PERFORM INTEGER PROGRAMMING, WHERE THE VALUES    BXPL 160
         OF THE INDEPENDENT VARIABLES ARE RESTRICTED TO INTEGERS.       BXPL 170
CCC                                                            BXPL 180
      USAGE                                                    BXPL 190
CCC                                                            BXPL 200
         CALL BOXPLX (NV,NAV,NPR,NTA,R,XS,IP,XU,XL,YMN,IER)    BXPL 210
CCC                                                            BXPL 220
CCC                                                            BXPL 230
      DESCRIPTION OF PARAMETERS                                BXPL 240
CCC                                                            BXPL 250
         NV    AN INTEGER INPUT DEFINING THE NUMBER OF INDEPENDENT      BXPL 260
               VARIABLES OF THE OBJECTIVE FUNCTION TO BE MINIMIZED.     BXPL 270
               NOTE:  MAXIMUM NV + NAV IS PRESENTLY 50.  MAXIMUM NV IS  BXPL 280
               25.  IF THESE LIMITS MUST BE EXCEEDED, PUNCH A SOURCE    BXPL 290
               DECK IN THE USUAL MANNER, AND CHANGE THE DIMENSION       BXPL 300
               STATEMENTS.                                              BXPL 310
CCC                                                            BXPL 320
         NAV   AN INTEGER INPUT DEFINING THE NUMBER OF AUXILIARY VAR-   BXPL 330
               IABLES THE USER WISHES TO DEFINE FOR HIS OWN CONVENIENCE. BXPL 340
               TYPICALLY HE MAY WISH TO DEFINE THE VALUE OF EACH IMPLICITBXPL 350
               CONSTRAINT FUNCTION AS AN AUXILIARY VARIABLE.  IF THIS   BXPL 360
               IS DONE, THE OPTIONAL OUTPUT FEATURE OF BOXPLX CAN BE    BXPL 370
               USED TO OBSERVE THE VALUES OF THOSE CONSTRAINTS AS THE   BXPL 380
               SOLUTION PROGRESSES.  AUXILIARY VARIABLES, IF USED,      BXPL 390
               SHOULD BE EVALUATED IN FUNCTION KE (DEFINED BELOW).      BXPL 400
               NAV MAY BE ZERO.                                         BXPL 410
CCC                                                            BXPL 420
         NPR   INPUT INTEGER CONTROLLING THE FREQUENCY OF OUTPUT DESIRED BXPL 430
               FOR DIAGNOSTIC PURPOSES.  IF NPR .LE. 0, NO OUTPUT WILL BEBXPL 440
               PRODUCED BY BOXPLX.  OTHERWISE, THE CURRENT COMPLEX OF   BXPL 450
               K= 2*NV VERTICES AND THEIR CENTROID WILL BE OUTPUT AFTER  BXPL 460
               EACH NPR PERMISSIBLE TRIALS.  THE NUMBER OF TOTAL TRIALS, BXPL 470
               NUMBER OF FEASIBLE TRIALS, NUMBER OF FUNCTION EVALUATIONS BXPL 480
```

```
C       AND NUMBER OF IMPLICIT CONSTRAINT EVALUATIONS ARE IN-      BXPL 490
C       CLUDED IN THE OUTPUT.                                      BXPL 500
C       ADDITIONALLY, (WHEN NPR .GT. 0) THE SAME INFORMATION       BXPL 510
C       WILL BE OUTPUT:                                            BXPL 520
C                                                                  BXPL 530
C         1) IF THE INITIAL POINT IS NOT FEASIBLE,                 BXPL 540
C         2) AFTER THE FIRST COMPLETE COMPLEX IS GENERATED,        BXPL 550
C         3) IF A FEASIBLE VERTEX CANNOT BE FOUND AT SOME TRIAL,   BXPL 560
C         4) IF THE OBJECTIVE VALUE OF A VERTEX CANNOT BE MADE     BXPL 570
C            NO-LONGER-WORST.                                      BXPL 580
C         5) IF THE LIMIT ON TRIALS (NTA) IS REACHED AND,          BXPL 590
C         6) WHEN THE OBJECTIVE FUNCTION HAS BEEN UNCHANGED FOR    BXPL 600
C            2*NV TRIALS, INDICATING A LOCAL MINIMUM HAS BEEN      BXPL 610
C            FOUND.                                                BXPL 620
C                                                                  BXPL 630
C       IF THE USER WISHES TO TRACE THE PROGRESS OF A SOLUTION,    BXPL 640
C       A CHOICE OF NPR = 25, 50 OR 100 IS RECOMMENDED.            BXPL 650
C                                                                  BXPL 660
C   NTA INTEGER INPUT OF LIMIT ON THE NUMBER OF TRIALS ALLOWED     BXPL 670
C       IN THE CALCULATION.  IF THE USER INPUTS NTA .LE. 0, A      BXPL 680
C       DEFAULT VALUE OF 2000 IS USED.  WHEN THIS LIMIT IS REACHEDBXPL 690
C       CONTROL RETURNS TO THE CALLING PROGRAM WITH THE BEST       BXPL 700
C       ATTAINED OBJECTIVE FUNCTION VALUE IN YMN, AND THE BEST     BXPL 710
C       ATTAINED SOLUTION POINT IN XS.                             BXPL 720
C                                                                  BXPL 730
C   R   A REAL NUMBER INPUT TO DEFINE THE FIRST RANDOM NUMBER      BXPL 740
C       USED IN DEVELOPING THE INITIAL COMPLEX OF 2*NV VERTICIES.  BXPL 750
C       (0. .GT. R .LT. 1.) IF R IS NOT WITHIN THESE BOUNDS,       BXPL 760
C       IT WILL BE REPLACED BY 1./3. .                             BXPL 770
C                                                                  BXPL 780
C   XS  INPUT REAL ARRAY DIMENSIONED AT LEAST NV+NAV. THE FIRST    BXPL 790
C       NV MUST CONTAIN A FEASIBLE ORIGIN FOR STARTING THE CAL-    BXPL 800
C       CULATION.  THE LAST NAV NEED NOT BE INITIALIZED.  UPON     BXPL 810
C       RETURN FROM BOXPLX, THE FIRST NV ELEMENTS OF THE ARRAY     BXPL 820
C       CONTAIN THE COORDINATES OF THE MINIMUM OBJECTIVE FUNCTION, BXPL 830
C       AND THE REMAINING NAV (NAV .GE. 0) CONTAIN THE VALUES OF   BXPL 840
C       THE CORRESPONDING AUXILIARY VARIABLES.                     BXPL 850
C                                                                  BXPL 860
C   IP  INTEGER INPUT FOR OPTIONAL INTEGER PROGRAMMING.  IF IP=1,  BXPL 870
C       THE VALUES OF THE INDEPENDENT VARIABLES WILL BE REPLACED   BXPL 880
C       WITH INTEGER VALUES (STILL STORED AS REAL*4).              BXPL 890
C                                                                  BXPL 900
C   XU  A REAL ARRAY DIMENSIONED AT LEAST NV INPUTTING THE UPPER   BXPL 910
C       BOUND ON EACH INDEPENDENT VARIABLE, (EACH EXPLICIT CON-    BXPL 920
C       STRAINT).  INPUT VALUES ARE SLIGHTLY ALTERED BY BOXPLX.    BXPL 930
C                                                                  BXPL 940
C   XL  A REAL ARRAY DIMENSIONED AT LEAST NV INPUTTING THE LOWER   BXPL 950
C       BOUND ON EACH INDEPENDENT VARIABLE, (EACH EXPLICIT CON-    BXPL 960
```

```
C              STRAINT).  NOTE:  FOR BOTH XU AND XL CHOOSE REASONABLE     BXPL 970
C              VALUES IF NONE ARE GIVEN, NOT VALUES WHICH ARE MAGNITUDES  BXPL 980
C              ABOVE OR BELOW THE EXPECTED SOLUTION.  INPUT VALUES ARE    BXPL 990
C              SLIGHTLY ALTERED BY BOXPLX.                                BXPL1000
C                                                                         BXPL1010
C         YMN  THIS OUTPUT IS THE VALUE (REAL*4) OF THE OBJECTIVE FUNC-   BXPL1020
C              TION, CORRESPONDING TO THE SOLUTION POINT OUTPUT IN XS.     BXPL1030
C                                                                         BXPL1040
C         IER  INTEGER ERROR RETURN.  TO BE INTERROGATED UPON RETURN      BXPL1050
C              FROM BOXPLX.  IER WILL BE ONE OF THE FOLLOWING:            BXPL1060
C                                                                         BXPL1070
C                =-1  CANNOT FIND FEASIBLE VERTEX OR FEASIBLE CENTROID    BXPL1080
C                     AT THE START OR A RESTART (SEE 'METHOD' BELOW).     BXPL1090
C                =0   FUNCTION VALUE UNCHANGED FOR 'N' TRIALS.  (WHERE    BXPL1100
C                     N=6*NV+10)  THIS IS THE NORMAL RETURN PARAMETER.    BXPL1110
C                =1   CANNOT DEVELOP FEASIBLE VERTEX.                     BXPL1120
C                =2   CANNOT DEVELOP A NO-LONGER-WORST VERTEX.            BXPL1130
C                =3   LIMIT ON TRIALS REACHED.  (NTA EXCEEDED)            BXPL1140
C                NOTE:  VALID RESULTS MAY BE RETURNED IN ANY OF THE       BXPL1150
C                     ABOVE CASES.                                        BXPL1160
C                                                                         BXPL1170
C     EXAMPLE OF USAGE                                                    BXPL1180
C                                                                         BXPL1190
C        THIS EXAMPLE MINIMIZES THE OBJECTIVE FUNCTION SHOWN IN THE       BXPL1200
C        EXTERNAL FUNCTION FE(X).  THERE ARE TWO INDEPENDENT VAR-         BXPL1210
C        IABLES X(1) & X(2), AND TWO IMPLICIT CONSTRAINT FUNCTIONS        BXPL1220
C        X(3) & X(4) WHICH ARE EVALUATED AS AUXILIARY VARIABLES (SEE      BXPL1230
C        EXTERNAL FUNCTION KE(X) ).                                       BXPL1240
C                                                                         BXPL1250
C     DIMENSION  XS(4),XU(2),XL(2)                                        BXPL1260
C                                                                         BXPL1270
CC  STARTING GUESS                                                        BXPL1280
C     XS(1) = 1.0                                                         BXPL1290
C     XS(2) = 0.5                                                         BXPL1300
CC  UPPER LIMITS                                                          BXPL1310
C     XU(1) = 6.0                                                         BXPL1320
C     XU(2) = 6.0                                                         BXPL1330
CC  LOWER LIMITS                                                          BXPL1340
C     XL(1) = 0.0                                                         BXPL1350
C     XL(2) = 0.0                                                         BXPL1360
C                                                                         BXPL1370
C     R = 9./13.                                                          BXPL1380
C     NTA = 5000                                                          BXPL1390
C     NFR = 50                                                            BXPL1400
C     NAV = 2                                                             BXPL1410
C     NV = 2                                                              BXPL1420
C     IP = 0                                                              BXPL1430
C                                                                         BXPL1440
```

```
C       CALL BCXPLX (NV,NAV,NPR,NTA,R,XS,IP,XU,XL,YMN,IER)                BXPL1450
C       WRITE(6,1) ((XS(I),I=1,4),YMN,IER)                                BXPL1460
C     1 FORMAT (////,'   THE POINT IS LOCATED AT (XS(I)=) ',4(E13.7,5X),  BXPL1470
C      1//,'   AND THE FUNCTION VALUE IS ',E13.7,' IER = ',I5)            BXPL1480
C                                                                         BXPL1490
C       STOP                                                              BXPL1500
C       END                                                               BXPL1510
C                                                                         BXPL1520
C                                                                         BXPL1530
C       FUNCTION  KE(X)                                                   BXPL1540
CC    EVALUATE CONSTRAINTS.  SET KE=0 IF NO IMPLICIT CONSTRAINT IS        BXPL1550
CC    VIOLATED, OR SET KE=1 IF ANY IMPLICIT CONSTRAINT IS VIOLATED.       BXPL1560
C       DIMENSION X(4)                                                    BXPL1570
C       X1 = X(1)                                                         BXPL1580
C       X2 = X(2)                                                         BXPL1590
C       KE = 0                                                            BXPL1600
C       X(3) = X1 + 1.732051*X2                                           BXPL1610
C       IF (X(3) .LT. 0. .OR. X(3) .GT. 6.) GO TO 1                       BXPL1620
C       X(4) = X1/1.732051 -X2                                            BXPL1630
C       IF (X(4) .GE. 0.)  RETURN                                         BXPL1640
C                                                                         BXPL1650
C     1 KE = 1                                                            BXPL1660
C       RETURN                                                            BXPL1670
C       END                                                               BXPL1680
C                                                                         BXPL1690
C                                                                         BXPL1700
C       FUNCTION  FE(X)                                                   BXPL1710
C       DIMENSION X(4)                                                    BXPL1720
C                                                                         BXPL1730
CC    THIS IS THE OBJECTIVE FUNCTION.                                     BXPL1740
C       FE= -(X(2)**3 *(9.-(X(1)-3.)**2)/(46.76538))                      BXPL1750
C       RETURN                                                            BXPL1760
C       END                                                               BXPL1770
C                                                                         BXPL1780
C       METHOD                                                            BXPL1790
C                                                                         BXPL1800
C          THE COMPLEX METHOD IS AN EXTENSION AND ADAPTION OF THE SIM-    BXPL1810
C          PLEX METHOD OF LINEAR PROGRAMMING.  STARTING WITH ANY ONE      BXPL1820
C          FEASIBLE POINT IN N-DIMENSION SPACE A "COMPLEX" OF 2*N         BXPL1830
C          VERTICES IS CONSTRUCTED BY SELECTING RANDOM POINTS WITHIN THE  BXPL1840
C          FEASIBLE REGION.  FOR THIS PURPOSE N COORDINATES ARE FIRST     BXPL1850
C          RANDOMLY CHOSEN WITHIN THE SPACE BOUNDED BY EXPLICIT CON-      BXPL1860
C          STRAINTS.  THIS DEFINES A TRIAL INITIAL VERTEX.  IT IS THEN    BXPL1870
C          CHECKED FOR POSSIBLE VIOLATION OF IMPLICIT CONSTRAINTS.  IF    BXPL1880
C          ONE OR MORE ARE VIOLATED, THE TRIAL INITIAL VERTEX IS DISPLACEDBXPL1890
C          HALF OF ITS DISTANCE FROM THE CENTROID OF PREVIOUSLY SELECTED  BXPL1900
C          INITIAL VERTICES.  IF NECESSARY THIS DISPLACEMENT PROCESS IS   BXPL1910
C          REPEATED UNTIL THE VERTEX HAS BECOME FEASIBLE.  IF THIS FAILS  BXPL1920
```

```
C      TO HAPPEN AFTER 5*N+10 DISPLACEMENTS, THE SOLUTION IS ABAND-   BXPL1930
C      ONED.  AFTER EACH VERTEX IS ADDED TO THE COMPLEX, THE CURRENT  BXPL1940
C      CENTROID IS CHECKED FOR FEASIBILITY.  IF IT IS INFEASIBLE,     BXPL1950
C      THE LAST TRIAL VERTEX IS ABANDONED AND AN EFFORT TO GENERATE   BXPL1960
C      AN ALTERNATIVE TRIAL VERTEX IS MADE.  IF 5*N+10 VERTICES ARE   BXPL1970
C      ABANDONED CONSECUTIVELY, THE SOLUTION IS TERMINATED.           BXPL1980
C                                                                     BXPL1990
C      IF AN INITIAL COMPLEX IS ESTABLISHED, THE BASIC COMPUTATION    BXPL2000
C      LOOP IS INITIATED.  THESE INSTRUCTIONS FIND THE CURRENT WORST  BXPL2010
C      VERTEX, THAT IS, THE VERTEX WITH THE LARGEST CORRESPONDING     BXPL2020
C      VALUE FOR THE OBJECTIVE FUNCTION, AND REPLACE THAT VERTEX BY   BXPL2030
C      ITS OVER-REFLECTION THROUGH THE CENTROID OF ALL OTHER VERTICES.BXPL2040
C      (IF THE VERTEX TO BE REPLACED IS CONSIDERED AS A VECTOR IN     BXPL2050
C      N-SPACE, ITS OVER-REFLECTION IS OPPOSITE IN DIRECTION, IN-     BXPL2060
C      CREASED IN LENGTH BY THE FACTOR 1.3, AND COLLINEAR WITH        BXPL2070
C      THE REPLACED VERTEX AND CENTROID OF ALL OTHER VERTICES.)       BXPL2080
C                                                                     BXPL2090
C      WHEN AN OVER-REFLECTION IS NOT FEASIBLE OR REMAINS WORST, IT   BXPL2100
C      IS CONSIDERED NOT-PERMISSIBLE AND IS DISPLACED HALFWAY TOWARD  BXPL2110
C      THE CENTROID.  AFTER FOUR SUCH ATTEMPTS ARE MADE UNSUCCESSFULLYBXPL2120
C      EVERY FIFTH ATTEMPT IS MADE BY REFLECTING THE OFFENDING VERTEX BXPL2130
C      THROUGH THE PRESENT BEST VERTEX, INSTEAD OF THROUGH THE CEN-   BXPL2140
C      TROID.  IF 5*N+10 DISPLACEMENTS AND OVER-REFLECTIONS OCCUR     BXPL2150
C      WITHOUT A SUCCESSFUL (PERMISSIBLE) RESULT, THE CURRENT BEST    BXPL2160
C      VERTEX IS TAKEN AS AN INITIAL FEASIBLE POINT FOR A RESTART     BXPL2170
C      RUN OF THE COMPLETE PROCESS.  RESTARTING IS ALSO UNDERTAKEN    BXPL2180
C      WHEN 6*NV+10 CONSECUTIVE TRIALS HAVE BEEN MADE WITH NO SIGNIF- BXPL2190
C      ICANT CHANGE IN THE VALUE OF THE OBJECTIVE FUNCTION.  IN ALL   BXPL2200
C      CASES, RESTARTING IS INHIBITED IF THE LAST RESTART DID NOT     BXPL2210
C      PRODUCE A SIGNIFICANT IMPROVEMENT IN THE MINIMUM ATTAINED.     BXPL2220
C                                                                     BXPL2230
C      IT IS RECOMMENDED THAT THE USER READ THE REFERENCE FOR         BXPL2240
C      FURTHER USEFUL INFORMATION.  IT SHOULD BE NOTED THAT THE       BXPL2250
C      ALGORITHM DEFINED THERE HAS BEEN ALTERED TO FIND THE           BXPL2260
C      CONSTRAINED MINIMUM, RATHER THAN THE MAXIMUM.                  BXPL2270
C                                                                     BXPL2280
C                                                                     BXPL2290
C  REMARKS                                                            BXPL2300
C                                                                     BXPL2310
C      THE INTEGER PROGRAMMING OPTION WAS ADDED TO THIS PROGRAM       BXPL2320
C      AS SUGGESTED IN REFERENCE (2).  A MIXED INTEGER/CONTINUOUS     BXPL2330
C      VARIABLE VERSION OF BOXPLX WOULD BE EASY TO CREATE BY DE-      BXPL2340
C      CLARING "IP" TO BE AN ARRAY OF NV CONTROL VARIABLES WHERE IP   BXPL2350
C      (I)=1 WOULD INDICATE THAT THE I-TH VARIABLE IS TO BE CONFINED  BXPL2360
C      TO INTEGER VALUES.  EACH STATEMENT OF THE FORM 'IF (IP .EQ.    BXPL2370
C      1)' ETC. WOULD THEN NEED TO BE ALTERED TO 'IF (IP(I) .EQ. 1)'  BXPL2380
C      ETC., WHERE THE SUBSCRIPT IS APPROPRIATELY CHOSEN.  NORMALLY,  BXPL2390
C      XU AND XL VALUES ARE ALTERED TO BE AN EPSILON 'WITHIN' ACTUAL  BXPL2400
```

```
C        VALUES DECLARED BY THE USER.  THIS ADJUSTMENT IS NOT MADE          BXPL2410
C        WHEN IP=1.                                                         BXPL2420
C                                                                           BXPL2430
C        NOTE:  NO NON-LINEAR PROGRAMMING ALGORITHM CAN GUARANTEE THAT      BXPL2440
C        THE ANSWER FOUND IS THE GLOBAL MINIMUM, RATHER THAN JUST A         BXPL2450
C        LOCAL MINIMUM.  HOWEVER, ACCORDING TO REF.2, THE COMPLEX           BXPL2460
C        METHOD HAS AN ADVANTAGE IN THAT IT TENDS TO FIND THE GLOBAL        BXPL2470
C        MINIMUM MORE FREQUENTLY THAN MANY OTHER NON-LINEAR PROGRAM-        BXPL2480
C        MING ALGORITHMS.                                                   BXPL2490
C                                                                           BXPL2500
C        IT SHOULD BE NOTED THAT THE AUXILIARY VARIABLE FEATURE CAN         BXPL2510
C        ALSO BE USED TO DEAL WITH PROBLEMS CONTAINING EQUALITY CON-        BXPL2520
C        STRAINTS.  ANY EQUALITY CONSTRAINT IMPLIES THAT A GIVEN VAR-       BXPL2530
C        IABLE IS NOT TRULY INDEPENDENT.  THEREFORE, IN GENERAL, ONE        BXPL2540
C        VARIABLE INVOLVED IN AN EQUALITY CONSTRAINT CAN BE RENUMBERED      BXPL2550
C        FROM THE SET OF NV INDEPENDENT VARIABLES AND ADDED TO THE SET      BXPL2560
C        OF NAV AUXILIARY VARIABLES.  THIS USUALLY INVOLVES RENUMBERING     BXPL2570
C        THE INDEPENDENT VARIABLES OF THE GIVEN PROBLEM.                    BXPL2580
C                                                                           BXPL2590
C     SUBROUTINES AND FUNCTIONS REQUIRED                                    BXPL2600
C                                                                           BXPL2610
C        SUBROUTINE 'BOUT' AND FUNCTION 'FBV' ARE INTEGRAL PARTS OF         BXPL2620
C        THE BOXPLX PACKAGE.                                                BXPL2630
C                                                                           BXPL2640
C        TWO FUNCTIONS MUST BE SUPPLIED BY THE USER.  THE FIRST, KE(X),     BXPL2650
C        IS USED TO EVALUATE THE IMPLICIT CONSTRAINTS.  SET KE=0 AT THE     BXPL2660
C        BEGINING OF THE FUNCTION, THEN EVALUATE THE IMPLICIT CON-          BXPL2670
C        STRAINTS.  IN THE EXAMPLE ABOVE, THE FIRST CONSTRAINT, X(3),       BXPL2680
C        MUST BE WITHIN THE RANGE (0. .LE. X(3) .LE. 6.).  THE SECOND       BXPL2690
C        CONSTRAINT X(4), MUST BE .GE. 0. .  IF EITHER CONSTRAINT IS        BXPL2700
C        NOT WITHIN THESE BOUNDS, CONTROL IS TRANSFERRED TO STATEMENT 1,    BXPL2710
C        AND KE IS SET TO "1" AND CONTROL IS RETURNED TO BOXPLX.            BXPL2720
C                                                                           BXPL2730
C        THE SECOND FUNCTION THE USER MUST PROVIDE EVALUATES THE OB-        BXPL2740
C        JECTIVE FUNCTION.  IT IS CALLED FE(X) AS SHOWN IN THE EXAM-        BXPL2750
C        PLE ABOVE, AND FE MUST BE SET TO THE VALUE OF THE OBJECTIVE        BXPL2760
C        FUNCTION CORRESPONDING TO CURRENT VALUES OF THE NV INDEPENDENT     BXPL2770
C        VARIABLES IN ARRAY 'X'.                                            BXPL2780
C                                                                           BXPL2790
C     REFERENCES                                                            BXPL2800
C                                                                           BXPL2810
C        BOX, M. J., "A NEW METHOD OF CONSTRAINED OPTIMIZATION AND A        BXPL2820
C        COMPARISON WITH OTHER METHODS", COMPUTER JOURNAL, 8 APR. '65,      BXPL2830
C        PP. 45-52.                                                         BXPL2840
C                                                                           BXPL2850
C        BEVERIDGE G., AND SCHECHTER R., "OPTIMIZATION: THEORY AND          BXPL2860
C        PRACTICE", MCGRAW-HILL, 1970.                                      BXPL2870
C                                                                           BXPL2880
```

```
C      PROGRAMMER                                                                BXPL2890
C                                                                                BXPL2900
C         R.R. HILLEARY 1/1966.                                                  BXPL2910
C         REVISED FOR SYSTEM 360 4/1967                                          BXPL2920
C         CORRECTED  1/1969                                                      BXPL2930
C         REVISED/EXTENDED BY L.NOLAN/R.HILLEARY  2/1975                         BXPL2940
C         MODIFIED FOR USE IN CALICO PROGRAM 1/76                                BXPL2950
C                                                                                BXPL2960
C      ..........................................................................BXPL2970
C                                                                                BXPL2980
C                                                                                BXPL2990
      SUBROUTINE BOXPLX (NV,NAV,NPR,NTZ,RZ,XS,IF,BU,BL,YMA,IER)                  BXPL3000
C                                                                                BXPL3010
      DIMENSION V(50,50), FUN(50), SUM(25), CEN(25), XS(NV), BL(NV), BL(BXPL3020
     1NV)                                                                        BXPL3030
      COMMON NCN,NCD,NTFN,NTFD,NOMEG,A(20),B(20),CMAG(500),DQPHSD(500),WBXPL3040
     1FREQ(500),NSN,NSD,COFASN(40),COFASD(40),CMAG(500),CR(500),CI(500),BXPL3050
     2CPHSR(500),QPHSD(500),N1,N2,N3,N4,PI,T,WS,IZCF,ADMAG(500),NTILE(10BXPL3060
     32),FREQ(500),AMAG(500),NMINFS,COFWRK(40),IPLOT,WFREQS(500),SAPHSD(BXPL3070
     45CC),SAMAG(500),DIFF1(500),DIFF2(500),ICOST,CFWRK1(40)                     BXPL3080
C                                                                                BXPL3090
      KV = 5                                                                     BXPL3100
      EF = 1.E-6                                                                 BXPL3110
      NTA = 2000                                                                 BXPL3120
      IF (NTZ.GT.0) NTA = NTZ                                                    BXPL3130
      R = RZ                                                                     BXPL3140
      IF (R.LE.0..OR.R.GE.1.) R=1./3.                                            BXPL3150
      NVT = NV+NAV                                                               BXPL3160
C                                                                                BXPL3170
C           TOTAL VARS, EXPLICIT PLUS IMPLICIT                                   BXPL3180
      NT = 0                                                                     BXPL3190
C           CURRENT TRIAL NO.                                                    BXPL3200
      NPT = 0                                                                    BXPL3210
C           CURRENT NO. OF PERMISSIBLE TRIALS                                    BXPL3220
      NTFS = 0                                                                   BXPL3230
C           CURRENT NO. OF TIMES F HAS BEEN ALMOST UNCHANGED                     BXPL3240
C                                                                                BXPL3250
C             CHECK FEASIBILITY OF START POINT                                   BXPL3260
C                                                                                BXPL3270
C                                                                                BXPL3280
      DO 4 I=1,NV                                                                BXPL3290
      VT = XS(I)                                                                 BXPL3300
      IF (BL(I).LE.VT) GO TO 1                                                   BXPL3310
      II = -I                                                                    BXPL3320
      VT = BL(I)                                                                 BXPL3330
      GO TO 2                                                                    BXPL3340
    1 IF (BU(I).GE.VT) GO TO 3                                                   BXPL3350
      II = I                                                                     BXPL3360
```

```
      VT = BU(I)                                                        BXPL3370
    2 IF (NPR.GT.0) WRITE (6,51) II                                     BXPL3380
    3 V(I,1) = VT                                                       BXPL3390
      CEN(I) = VT                                                       BXPL3400
      IF (IP.EQ.1) GO TO 4                                              BXPL3410
      BL(I) = BL(I)+AMAX1(EP,EP*ABS(BL(I)))                             BXPL3420
      BU(I) = BU(I)-AMAX1(EP,EP*ABS(BU(I)))                             BXPL3430
    4 SUM(I) = VT                                                       BXPL3440
C                                                                       BXPL3450
C                                                                       BXPL3460
C                                                                       BXPL3470
      NCE = 1                                                           BXPL3480
C           NUMBER OF CONSTRAINT EVALUATIONS                            BXPL3490
      I = 1                                                             BXPL3500
      IF (KE(V(1,1)).EQ.0) GO TO 5                                      BXPL3510
      IF (NPR.LE.0) GO TO 12                                            BXPL3520
      WRITE (6,52)                                                      BXPL3530
      GO TO 12                                                          BXPL3540
    5 NFE = 1                                                           BXPL3550
C                                                                       BXPL3560
C   NUMBER OF VERTICES (K) = 2 TIMES NO. OF VARIABLES.                  BXPL3570
      K = 2*NV                                                          BXPL3580
C                                                                       BXPL3590
C   NUMBER OF DISPLACEMENTS ALLOWED.                                    BXPL3600
      NLIM = 5*NV+10                                                    BXPL3610
C                                                                       BXPL3620
C   NUMBER OF CONSECUTIVE TRIALS WITH UNCHANGED FE TO TERMINATE.        BXPL3630
      NCT = NLIM+NV                                                     BXPL3640
      ALPHA = 1.3                                                       BXPL3650
      FK = K                                                            BXPL3660
      FKN = FK-1.                                                       BXPL3670
      BETA = ALPHA+1.                                                   BXPL3680
C                                                                       BXPL3690
C   INSURE SEED OF RANDOM NUMBER GENERATOR IS ODD.                      BXPL3700
      IGR = R*1.E7                                                      BXPL3710
      IF (MOD(IGR,2).EQ.0) IGR=IGR+101                                  BXPL3720
C                                                                       BXPL3730
C                         SET UP INITIAL VERTICES                       BXPL3740
      FUN(1) = FE(V(1,1))                                               BXPL3750
      YMN = FUN(1)                                                      BXPL3760
    6 FI = 1.                                                           BXPL3770
      FUNOLD = FUN(1)                                                   BXPL3780
C                                                                       BXPL3790
C                                                                       BXPL3800
      DO 17 I=2,K                                                       BXPL3810
      FI = FI+1.                                                        BXPL3820
      LIMT = 0                                                          BXPL3830
    7 LIMT = LIMT+1                                                     BXPL3840
```

```
C                                                                       BXPL3850
C    END CALCULATION IF FEASIBLE CENTROID CANNOT BE FOUND.              BXPL3860
       IF (LIMT.GE.NLIM) GO TO 11                                       BXPL3870
C                                                                       BXPL3880
C                                                                       BXPL3890
       DO 8 J=1,NV                                                      BXPL3900
C                                                                       BXPL3910
C    RANDOM NUMBER GENERATOR  (RANDU)                                   BXPL3920
       IQR = IQR*65539                                                  BXPL3930
       IF (IQR.LT.0) IQR = IQR+2147483647+1                             BXPL3940
       RQX = IQR                                                        BXPL3950
       RQX = RQX*.4656613E-9                                            BXPL3960
       V(J,I) = BL(J)+RQX*(BL(J)-BL(J))                                 BXPL3970
       IF (IP.EQ.1) V(J,I)=AINT(V(J,I)+.5)                              BXPL3980
     8 CONTINUE                                                         BXPL3990
C                                                                       BXPL4000
C                                                                       BXPL4010
C                                                                       BXPL4020
       DO 10 L=1,NLIM                                                   BXPL4030
       NCE = NCE+1                                                      BXPL4040
       IF (KE(V(1,I)).EQ.0) GO TO 13                                    BXPL4050
C                                                                       BXPL4060
C                                                                       BXPL4070
       DO 9 J=1,NV                                                      BXPL4080
       VT = .5*(V(J,I)+CEN(J))                                          BXPL4090
       IF (IP.EQ.1) VT = AINT(VT+.5)                                    BXPL4100
       V(J,I) = VT                                                      BXPL4110
     9 CONTINUE                                                         BXPL4120
C                                                                       BXPL4130
C                                                                       BXPL4140
    10 CONTINUE                                                         BXPL4150
C                                                                       BXPL4160
C                                                                       BXPL4170
    11 IF (NPR.LE.0) GO TO 12                                           BXPL4180
       WRITE (6,53) I                                                   BXPL4190
       CALL BCLT (NT,NPT,NFE,NCE,NV,NVT,V,I,FUN,CEN,I)                  BXPL4200
    12 IER = -1                                                         BXPL4210
       GO TO 50                                                         BXPL4220
C                                                                       BXPL4230
C                                                                       BXPL4240
    13 DO 14 J=1,NV                                                     BXPL4250
       SUM(J) = SUM(J)+V(J,I)                                           BXPL4260
    14 CEN(J) = SUM(J)/FI                                               BXPL4270
C                                                                       BXPL4280
C                                                                       BXPL4290
C    TRY TO ASSURE FEASIBLE CENTROID FOR STARTING.                      BXPL4300
       NCE = NCE+1                                                      BXPL4310
       IF (KE(CEN).EQ.0) GO TO 16                                       BXPL4320
```

```
C                                                                       BXPL4330
      DO 15 J=1,NV                                                      BXPL4340
   15 SUM(J) = SUM(J)-V(J,I)                                            BXPL4350
C                                                                       BXPL4360
      GO TO 7                                                           BXPL4370
   16 NFE = NFE+1                                                       BXPL4380
      FUN(I) = FE(V(1,I))                                               BXPL4390
   17 CONTINUE                                                          BXPL4400
C                                                                       BXPL4410
C                                                                       BXPL4420
C     END OF LOOP SETTING UP INITIAL COMPLEX.                           BXPL4430
      IF (NPR.LE.0) GO TO 19                                            BXPL4440
      CALL BOUT (NT,NPT,NFE,NCE,NV,NVT,V,K,FUN,CEN,0)                   BXPL4450
C                                                                       BXPL4460
C     FIND THE WORST VERTEX, THE 'J'TH.                                 BXPL4470
      J = 1                                                             BXPL4480
C                                                                       BXPL4490
C                                                                       BXPL4500
      DO 18 I=2,K                                                       BXPL4510
      IF (FUN(J).GE.FUN(I)) GO TO 18                                    BXPL4520
      J = I                                                             BXPL4530
   18 CONTINUE                                                          BXPL4540
C                                                                       BXPL4550
C                                                                       BXPL4560
C     BASIC LOOP.  ELIMINATE EACH WORST VERTEX IN TURN.  IT MUST BECOME BXPL4570
C     NO LONGER WORST, NOT MERELY IMPROVED.  FIND NEXT-TO-WORST VERTEX, BXPL4580
C     THE 'JN'TH ONE.                                                   BXPL4590
   19 JN = 1                                                            BXPL4600
      IF (J.EQ.1) JN = 2                                                BXPL4610
C                                                                       BXPL4620
C                                                                       BXPL4630
      DO 20 I=1,K                                                       BXPL4640
      IF (I.EQ.J) GO TO 20                                              BXPL4650
      IF (FUN(JN).GE.FUN(I)) GO TO 20                                   BXPL4660
      JN = I                                                            BXPL4670
   20 CONTINUE                                                          BXPL4680
C                                                                       BXPL4690
C                                                                       BXPL4700
C     LIMT = NUMBER OF MOVES DURING THIS TRIAL TOWARD THE CENTROID      BXPL4710
C      CLE TO FUNCTION VALUE.                                           BXPL4720
      LIMT = 1                                                          BXPL4730
C                                                                       BXPL4740
C     COMPUTE CENTROID AND OVER REFLECT WORST VERTEX.                   BXPL4750
C                                                                       BXPL4760
C                                                                       BXPL4770
      DO 21 I=1,NV                                                      BXPL4780
      VT = V(I,J)                                                       BXPL4790
      SUM(I) = SUM(I)-VT                                                BXPL4800
```

```
      CEN(I) = SUM(I)/FKM                                                BXPL4810
      VT = BETA*CEN(I)-ALPHA*VT                                          BXPL4820
      IF (IP.EQ.1) VT = AINT(VT+.5)                                      BXPL4830
C                                                                        BXPL4840
C     INSURE THE EXPLICIT CONSTRAINTS ARE OBSERVED.                      BXPL4850
   21 V(I,J) = AMAX1(AMIN1(VT,BU(I)),BL(I))                              BXPL4860
C                                                                        BXPL4870
CC                                                                       BXPL4880
      NT = NT+1                                                          BXPL4890
C                                                                        BXPL4900
CC    CHECK FOR IMPLICIT CONSTRAINT VIOLATION.                           BXPL4910
CC                                                                       BXPL4920
C                                                                        BXPL4930
   22 DO 27 N=1,NLIM                                                     BXPL4940
      NCE = NCE+1                                                        BXPL4950
      IF (KE(V(1,J)).EQ.0) GO TO 28                                      BXPL4960
C                                                                        BXPL4970
CC    EVERY 'KV'TH TIME, OVER-REFLECT THE OFFENDING VERTEX THROUGH THE   BXPL4980
C     BEST VERTEX.                                                       BXPL4990
      IF (MOD(N,KV).NE.0) GO TO 24                                       BXPL5000
      CALL FBV (K,FUN,M)                                                 BXPL5010
C                                                                        BXPL5020
C                                                                        BXPL5030
      DO 23 I=1,NV                                                       BXPL5040
      VT = BETA*V(I,M)-ALPHA*V(I,J)                                      BXPL5050
      IF (IP.EQ.1) VT = AINT(VT+.5)                                      BXPL5060
   23 V(I,J) = AMAX1(AMIN1(VT,BU(I)),BL(I))                              BXPL5070
C                                                                        BXPL5080
CC                                                                       BXPL5090
      GO TO 26                                                           BXPL5100
C                                                                        BXPL5110
CC    CONSTRAINT VIOLATION:  MOVE NEW POINT TOWARD CENTROID.             BXPL5120
CC                                                                       BXPL5130
C                                                                        BXPL5140
   24 DO 25 I=1,NV                                                       BXPL5150
      VT = .5*(CEN(I)+V(I,J))                                            BXPL5160
      IF (IP.EQ.1) VT = AINT(VT+.5)                                      BXPL5170
      V(I,J) = VT                                                        BXPL5180
   25 CONTINUE                                                           BXPL5190
C                                                                        BXPL5200
C                                                                        BXPL5210
   26 NT = NT+1                                                          BXPL5220
   27 CONTINUE                                                           BXPL5230
C                                                                        BXPL5240
C                                                                        BXPL5250
      IER = 1                                                            BXPL5260
C                                                                        BXPL5270
C     CANNOT GET FEASIBLE VERTEX BY MOVING TOWARD CENTROID,              BXPL5280
```

```
C    OR BY OVER-REFLECTING THRU THE BEST VERTEX.                        BXPL5290
       IF (NPR.LE.0) GO TO 44                                           BXPL5300
       WRITE (6,54) NT,J                                                BXPL5310
       CALL BOUT (NT,NPT,NFE,NCE,NV,NVT,V,K,FUN,CEN,J)                  BXPL5320
       GO TO 44                                                         BXPL5330
C                                                                       BXPL5340
C    FEASIBLE VERTEX FOUND, EVALUATE THE OBJECTIVE FUNCTION.            BXPL5350
   26  NFE = NFE+1                                                      BXPL5360
       FUNTRY = FE(V(1,J))                                              BXPL5370
C                                                                       BXPL5380
C    TEST TO SEE IF FUNCTION VALUE HAS NOT CHANGED.                     BXPL5390
       AFC = ABS(FUNTRY-FUNOLD)                                         BXPL5400
       AMX = AMAX1(ABS(EP*FUNOLD),EP)                                   BXPL5410
C                                                                       BXPL5420
C    ACTIVATE THE FOLLOWING TWO STATEMENTS FOR DIAGNOSTIC PURPOSES ONLY. BXPL5430
C      WRITE (6,99) J,AFC,AMX,FUNTRY,FUNOLD,FUN(J),FUN(JN),NTFS,N       BXPL5440
C  99  FORMAT (1X,I3,6E15.7,2I5)                                        BXPL5450
       IF (AFC.GT.AMX) GO TO 29                                         BXPL5460
       NTFS = NTFS+1                                                    BXPL5470
       IF (NTFS.LT.NCT) GO TO 30                                        BXPL5480
       IER = 0                                                          BXPL5490
       IF (NPR.LE.0) GO TO 44                                           BXPL5500
       WRITE (6,55) K                                                   BXPL5510
       GO TO 44                                                         BXPL5520
   29  NTFS = 0                                                         BXPL5530
C                                                                       BXPL5540
C    IS THE NEW VERTEX NO LONGER WORST?                                 BXPL5550
   30  IF (FUNTRY.LT.FUN(JN)) GO TO 36                                  BXPL5560
C                                                                       BXPL5570
C    TRIAL VERTEX IS STILL WORST; ADJUST TOWARD CENTROID.               BXPL5580
C    EVERY 'KV'TH TIME, OVER-REFLECT THE OFFENDING VERTEX THROUGH THE   BXPL5590
C    BEST VERTEX.                                                       BXPL5600
       LIMT = LIMT+1                                                    BXPL5610
       IF (MOD(LIMT,KV).NE.0) GO TO 32                                  BXPL5620
       CALL FBV (K,FUN,M)                                               BXPL5630
C                                                                       BXPL5640
C                                                                       BXPL5650
       DO 31 I=1,NV                                                     BXPL5660
       VT = BETA*V(I,M)-ALPHA*V(I,J)                                    BXPL5670
       IF (IP.EQ.1) VT = AINT(VT+.5)                                    BXPL5680
   31  V(I,J) = AMAX1(AMIN1(VT,BU(I)),BL(I))                            BXPL5690
C                                                                       BXPL5700
C                                                                       BXPL5710
       GO TO 34                                                         BXPL5720
C                                                                       BXPL5730
C                                                                       BXPL5740
   32  DO 33 I=1,NV                                                     BXPL5750
       VT = .5*(CEN(I)+V(I,J))                                          BXPL5760
```

```
      IF (IP.EQ.1) VT = AINT(VT+.5)                                     BXPL5770
      V(I,J) = VT                                                       BXPL5780
   33 CONTINUE                                                          BXPL5790
C                                                                       BXPL5800
C                                                                       BXPL5810
   34 IF (LIMT.LT.NLIM) GO TO 35                                        BXPL5820
C                                                                       BXPL5830
C    CANNOT MAKE THE 'J'TH VERTEX NO LONGER WORST BY DISPLACING TOWARD  BXPL5840
C    THE CENTROID OR BY OVER-REFLECTING THRU THE BEST VERTEX.           BXPL5850
      IER = 2                                                           BXPL5860
      IF (NPR.GT.0) WRITE (6,54) NT,J                                   BXPL5870
      GO TO 44                                                          BXPL5880
   35 NT = NT+1                                                         BXPL5890
      GO TO 22                                                          BXPL5900
C                                                                       BXPL5910
C    SUCCESS:  WE HAVE A REPLACEMENT FOR VERTEX J.                      BXPL5920
   36 FLN(J) = FLNTRY                                                   BXPL5930
      FLNOLD = FLNTRY                                                   BXPL5940
      NPT = NPT+1                                                       BXPL5950
C                                                                       BXPL5960
C    EVERY 100'TH PERMISSIBLE TRIAL, RECOMPUTE CENTROID SUMMATION TO    BXPL5970
C    AVOID CREEPING ERROR.                                              BXPL5980
      IF (MOD(NPT,100).NE.0) GO TO 39                                   BXPL5990
C                                                                       BXPL6000
C                                                                       BXPL6010
      DO 38 I=1,NV                                                      BXPL6020
      SUM(I) = 0.                                                       BXPL6030
C                                                                       BXPL6040
C                                                                       BXPL6050
      DO 37 N=1,K                                                       BXPL6060
   37 SUM(I) = SUM(I)+V(I,N)                                            BXPL6070
C                                                                       BXPL6080
C                                                                       BXPL6090
      CEN(I) = SUM(I)/FK                                                BXPL6100
   38 CONTINUE                                                          BXPL6110
C                                                                       BXPL6120
C                                                                       BXPL6130
      LO = 0                                                            BXPL6140
      GO TO 41                                                          BXPL6150
C                                                                       BXPL6160
C                                                                       BXPL6170
   39 DO 40 I=1,NV                                                      BXPL6180
   40 SUM(I) = SUM(I)+V(I,J)                                            BXPL6190
C                                                                       BXPL6200
C                                                                       BXPL6210
      LO = J                                                            BXPL6220
C                                                                       BXPL6230
   41 IF (NPR.LE.0) GO TO 42                                            BXPL6240
```

```
      IF (MOD(NPT,NPR).NE.0) GO TO 42                                   BXPL6250
C                                                                       BXPL6260
      CALL BOUT (NT,NPT,NFE,NCE,NV,NVT,V,K,FUN,CEN,LC)                  BXPL6270
C                                                                       BXPL6280
C   HAS THE MAX. NUMBER OF TRIALS BEEN REACHED WITHOUT CONVERGENCE?     BXPL6290
C   IF NOT, GO TO NEW TRIAL.                                            BXPL6300
   42 IF (NT.GE.NTA) GO TO 43                                           BXPL6310
C                                                                       BXPL6320
C   NEXT-TO-WORST VERTEX NOW BECOMES WORST.                             BXPL6330
      J = JN                                                            BXPL6340
      GO TO 19                                                          BXPL6350
   43 IER = 3                                                           BXPL6360
      IF (NPR.GT.0) WRITE (6,56)                                        BXPL6370
C                                                                       BXPL6380
C   COLLECTOR POINT FOR ALL ENDINGS.                                    BXPL6390
C     1)  CANNOT DEVELOP FEASIBLE VERTEX.          IER = 1              BXPL6400
C     2)  CANNOT DEVELOP A NO-LONGER-WORST VERTEX. IER = 2              BXPL6410
C     3)  FUNCTION VALUE UNCHANGED FOR K TRIALS.   IER = 0              BXPL6420
C     4)  LIMIT ON TRIALS REACHED.                 IER = 3              BXPL6430
C     5)  CANNOT FIND FEASIBLE VERTEX AT START.    IER = -1             BXPL6440
   44 CONTINUE                                                          BXPL6450
C                                                                       BXPL6460
C   FIND BEST VERTEX.                                                   BXPL6470
      CALL FBV (K,FUN,M)                                                BXPL6480
      IF (IER.GE.3) GO TO 46                                            BXPL6490
C                                                                       BXPL6500
C   RESTART IF THIS SOLUTION IS SIGNIFICANTLY BETTER THAN THE PREVIOUS, BXPL6510
C   OR IF THIS IS THE FIRST TRY.                                        BXPL6520
      IF (NPR.LE.0) GO TO 45                                            BXPL6530
      WRITE (6,57) (M,YMN,FUN(M))                                       BXPL6540
   45 IF (FUN(M).GE.YMN) GO TO 49                                       BXPL6550
      IF (ABS(FUN(M)-YMN).LE.AMAX1(EP,EP*YMN)) GO TO 49                 BXPL6560
C                                                                       BXPL6570
C   GIVE IT ANOTHER TRY UNLESS LIMIT ON TRIALS REACHED.                 BXPL6580
   46 YMN = FUN(M)                                                      BXPL6590
      FUN(1) = FUN(M)                                                   BXPL6600
C                                                                       BXPL6610
C                                                                       BXPL6620
      DO 47 I=1,NV                                                      BXPL6630
      CEN(I) = V(I,M)                                                   BXPL6640
      SUM(I) = V(I,M)                                                   BXPL6650
   47 V(I,1) = V(I,M)                                                   BXPL6660
C                                                                       BXPL6670
C                                                                       BXPL6680
C                                                                       BXPL6690
      DO 48 I=1,NVT                                                     BXPL6700
   48 XS(I) = V(I,M)                                                    BXPL6710
C                                                                       BXPL6720
```

```
C                                                                       BXPL6730
      IF (IER.LT.3) GO TO 6                                             BXPL6740
   49 IF (NPR.LE.0) GO TO 50                                            BXPL6750
      CALL BOUT (NT,NPT,NFE,NCE,NV,NVT,V,K,FUN,V(1,M),-1)               BXPL6760
      WRITE (6,58) FUN(M)                                               BXPL6770
   50 RETURN                                                            BXPL6780
C                                                                       BXPL6790
C                                                                       BXPL6800
   51 FORMAT (50HOINDEX AND DIRECTION OF OUTLYING VARIABLE AT START15)  BXPL6810
   52 FORMAT (50HOIMPLICIT CONSTRAINT VIOLATED AT START. DEAD END. )    BXPL6820
   53 FORMAT ('0CANNOT FIND FEASIBLE',I4,'TH VERTEX OR CENTROID AT START BXPL6830
     1.')                                                               BXPL6840
   54 FORMAT (10H0AT TRIAL I4,54H CANNOT FIND FEASIBLE VERTEX WHICH IS NBXPL6850
     1O LONGER WORST,I4,15X,'RESTART FROM BEST VERTEX.')                BXPL6860
   55 FORMAT (40H0FUNCTION HAS BEEN ALMOST UNCHANGED FOR 15,7H TRIALS)  BXPL6870
   56 FORMAT (27H0LIMIT ON TRIALS EXCEEDED. )                           BXPL6880
   57 FORMAT ('0BEST VERTEX IS NO.',I3,'  OLD MIN WAS ',E15.7,          BXPL6890
     1 '  NEW MIN IS ',E15.7)                                          BXPL6900
   58 FORMAT ('0MIN OBJECTIVE FUNCTION IS ',E15.7)                      BXPL6910
      END                                                               BXPL6920
```

```
      SUBROUTINE FBV (K,FUN,M)                                          FBV    10
      DIMENSION FUN(50)                                                 FBV    20
      M = 1                                                             FBV    30
C                                                                       FBV    40
C                                                                       FBV    50
      DO 1 I=2,K                                                        FBV    60
      IF (FUN(M).LE.FUN(I)) GO TO 1                                     FBV    70
      M = I                                                             FBV    80
    1 CONTINUE                                                          FBV    90
C                                                                       FBV   100
C                                                                       FBV   110
      RETURN                                                            FBV   120
      END                                                               FBV   130
```

```
      SUBROUTINE BOUT (NT,NPT,NFE,NCE,NV,NVT,V,K,FN,C,IK)                BOUT  10
      DIMENSION V(50,50), FN(50), C(25)                                  BOUT  20
      WRITE (6,4) NT,NPT,NFE,NCE                                         BOUT  30
C                                                                        BOUT  40
C                                                                        BOUT  50
      DO 1 I=1,K                                                         BOUT  60
      WRITE (6,5) FN(I),(V(J,I),J=1,NV)                                  BOUT  70
      IF (NVT.LE.NV) GO TO 1                                             BOUT  80
      NVP = NV+1                                                         BOUT  90
      WRITE (6,6) (V(J,I),J=NVP,NVT)                                     BOUT 100
    1 CONTINUE                                                           BOUT 110
C                                                                        BOUT 120
C                                                                        BOUT 130
      IF (IK.NE.0) GO TO 2                                               BOUT 140
C                                                                        BOUT 150
      WRITE (6,7) (C(I),I=1,NV)                                          BOUT 160
      RETURN                                                             BOUT 170
    2 IF (IK.GE.0) GO TO 3                                               BOUT 180
      WRITE (6,8) (C(I),I=1,NV)                                          BOUT 190
      RETURN                                                             BOUT 200
    3 WRITE (6,9) IK,(C(I),I=1,NV)                                       BOUT 210
      RETURN                                                             BOUT 220
C                                                                        BOUT 230
C                                                                        BOUT 240
    4 FORMAT ('ONO. TOTAL TRIALS = ',I5,4X,'NO. FEASIBLE TRIALS = ',     BOUT 250
     1I5,4X,'NO. FUNCTION EVALUATIONS = ',I5,4X,'NO. CONSTRAINT EVALUATIBOUT 260
     2ONS = ',I5/'0     FUNCTION VALUE',6X,'INDEPENDENT VARIABLES/DEPENCBOUT 270
     3ENT OR IMPLICIT CONSTRAINTS')                                      BOUT 280
    5 FORMAT (1H ,E18.7,2X,7E14.7/(21X,7E14.7))                          BOUT 290
    6 FORMAT (21X,7E14.7)                                                BOUT 300
    7 FORMAT (10HOCENTROID 11X,7E14.7/(21X,7E14.7))                      BOUT 310
    8 FORMAT ('0  BEST VERTEX',7X,7E14.7/(21X,7E14.7))                   BOUT 320
    9 FORMAT ('OCENTROID LESS VX',I2,2X,7E14.7/(21X,7E14.7))             BOUT 330
      END                                                                BOUT 340
```

```
C++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++CPINV   10
C++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++CPINV   20
C++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++CPINV   30
C++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++CPINV   40
C++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++CPINV   50
C++++                                                                                                                          ++++CPINV   60
C++++ PURPOSE: TO REARRANGE A VECTOR OF REAL POLYNOMIAL                                                                         ++++CPINV   70
C++++          COEFFICIENTS IN ASCENDING POWERS OF THE INDEPENDENT                                                             ++++CPINV   80
C++++          VARIABLE TO A VECTOR OF COEFFICIENTS IN DESCENDING                                                              ++++CPINV   90
C++++          POWERS OF THE INDEPENDENT VARIABLE, OR VICE VERSA.                                                              ++++CPINV  100
C++++                                                                                                                          ++++CPINV  110
C++++ CALLING SEQUENCE                                                                                                         ++++CPINV  120
C++++ CALL PINVRT(X,N)                                                                                                         ++++CPINV  130
C++++                                                                                                                          ++++CPINV  140
C++++ DESCRIPTION OF PARAMETERS:                                                                                               ++++CPINV  150
C++++ X       = A VECTOR OF REAL COEFFICIENTS, UPON RETURN FROM                                                                ++++CPINV  160
C++++           THE SUBROUTINE THIS VECTOR WILL CONTAIN THE                                                                    ++++CPINV  170
C++++           COEFFICIENTS IN REVERSE SEQUENCE FROM THAT INPUT.                                                              ++++CPINV  180
C++++                                                                                                                          ++++CPINV  190
C++++ N       = THE DIMENSION OF THE VECTOR X.                                                                                 ++++CPINV  200
C++++                                                                                                                          ++++CPINV  210
C++++ SUBROUTINES AND FUNCTION SUB-PROGRAMS REQUIRED:                                                                          ++++CPINV  220
C++++     NONE                                                                                                                 ++++CPINV  230
C++++                                                                                                                          ++++CPINV  240
C++++ METHOD:                                                                                                                  ++++CPINV  250
C++++ THE SEQUENCE OF THE INPUT VECTOR IS REVERSED BY USE OF TWO                                                                ++++CPINV  260
C++++ NESTED DO-LOOPS.  THE SIZE OF THE INPUT VECTOR IS LIMITED BY                                                              ++++CPINV  270
C++++ ITS DIMENSION IN THE CALLING PROGRAM.                                                                                    ++++CPINV  280
C++++                                                                                                                          ++++CPINV  290
C++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++CPINV  300
C++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++CPINV  310
      SUBROUTINE PINVRT (X,N)                                                                                                   PINV  340
      DIMENSION X(1)                                                                                                            PINV  350
      N2 = N-1                                                                                                                  PINV  360
C                                                                                                                               PINV  370
      DO 2 J=1,N2                                                                                                               PINV  380
      TEMP = X(1)                                                                                                               PINV  390
      N1 = N+1-J                                                                                                                PINV  400
C                                                                                                                               PINV  410
      DO 1 I=2,N1                                                                                                               PINV  420
      X(I-1) = X(I)                                                                                                             PINV  430
    1 CONTINUE                                                                                                                  PINV  440
C                                                                                                                               PINV  450
      X(N1) = TEMP                                                                                                              PINV  460
    2 CONTINUE                                                                                                                  PINV  470
C                                                                                                                               PINV  480
      RETURN                                                                                                                    PINV  490
      END                                                                                                                       PINV  500
```

```
C++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++CROUT  10
C++++++++++++++++++++                                    ++++++++++++++++++++CROUT  20
C++++++++++++++++++++        SUBROUTINE ROUTH            ++++++++++++++++++++CROUT  30
C++++++++++++++++++++                                    ++++++++++++++++++++CROUT  40
C++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++CROUT  50
C++++                                                                        ++++CROUT  60
C++++ PURPOSE: TO DETERMINE IF A POLYNOMIAL IN S HAS RIGHT HALF               ++++CROUT  70
C++++          PLANE ROOTS.                                                  ++++CROUT  80
C++++                                                                        ++++CROUT  90
C++++ CALLING SEQUENCE:                                                      ++++CROUT 100
C++++ CALL ROUTH(Y,N,ISTABL)                                                 ++++CROUT 110
C++++                                                                        ++++CROUT 120
C++++ DESCRIPTION OF PARAMETERS:                                             ++++CROUT 130
C++++ Y       = A ONE DIMENSIONAL ARRAY CONTAINING THE COEFFICIENTS          ++++CROUT 140
C++++           OF THE POLYNOMIAL IN DESCENDING POWERS OF THE               ++++CROUT 150
C++++           INDEPENDENT VARIABLE S.                                     ++++CROUT 160
C++++ N       = DIMENSION OF THE ARRAY Y.                                    ++++CROUT 170
C++++ ISTABL  = INTEGER OUTPUT;                                              ++++CROUT 180
C++++               0---INDICATES THE POLYNOMIAL HAS NO RIGHT HALF           ++++CROUT 190
C++++                   PLANE ROOTS.                                         ++++CROUT 200
C++++               1---INDICATES THE POLYNOMIAL HAS RIGHT HALF              ++++CROUT 210
C++++                   PLANE ROOTS.                                         ++++CROUT 220
C++++                                                                        ++++CROUT 230
C++++ SUBROUTINES AND FUNCTION SUB-PROGRAMS REQUIRED:                        ++++CROUT 240
C++++     NONE                                                               ++++CROUT 250
C++++                                                                        ++++CROUT 260
C++++ METHOD:                                                                ++++CROUT 270
C++++ THE POLYNOMIAL IS CHECKED FOR RIGHT HALF PLANE ROOTS BY                ++++CROUT 280
C++++ FORMING THE ROUTH ARRAY FROM THE POLYNOMIAL COEFFICIENTS               ++++CROUT 290
C++++ INPUT TO THE SUBROUTINE.                                               ++++CROUT 300
C++++                                                                        ++++CROUT 310
C++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++CROUT 320
C++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++++CROUT 330
      SUBROUTINE ROUTH (Y,N,ISTABL)                                           ROUT 340
      DIMENSION A(40,21), Y(1)                                                ROUT 350
C                                                                             ROUT 360
      DO 2 I=1,40                                                             ROUT 370
C                                                                             ROUT 380
      DO 1 J=1,21                                                             ROUT 390
      A(I,J) = 0.0                                                            ROUT 400
    1 CONTINUE                                                                ROUT 410
C                                                                             ROUT 420
    2 CONTINUE                                                                ROUT 430
C                                                                             ROUT 440
      ISTABL = 0                                                              ROUT 450
      L = 0                                                                   ROUT 460
      LL = 0                                                                  ROUT 470
      KK = N/2.0                                                              ROUT 480
```

```
      KK1 = KK+1                                                        ROUT 490
      FF = KK1                                                          ROUT 500
      K = KK*2.0                                                        ROUT 510
      IF (K.EQ.N) GO TO 5                                               ROUT 520
      N2 = N-1                                                          ROUT 530
C                                                                       ROUT 540
      DO 3 J=1,N,2                                                      ROUT 550
      L = L+1                                                           ROUT 560
      A(1,L) = Y(J)                                                     ROUT 570
    3 CONTINUE                                                          ROUT 580
C                                                                       ROUT 590
C                                                                       ROUT 600
      DO 4 J1=2,N2,2                                                    ROUT 610
      LL = LL+1                                                         ROUT 620
      A(2,LL) = Y(J1)                                                   ROUT 630
      IF (A(2,1).EQ.0.0) A(2,1)=0.0001                                  ROUT 640
    4 CONTINUE                                                          ROUT 650
C                                                                       ROUT 660
      GO TO 8                                                           ROUT 670
    5 KK1 = KK                                                          ROUT 680
C                                                                       ROUT 690
      DO 6 J=1,N,2                                                      ROUT 700
      L = L+1                                                           ROUT 710
      A(1,L) = Y(J)                                                     ROUT 720
    6 CONTINUE                                                          ROUT 730
C                                                                       ROUT 740
C                                                                       ROUT 750
      DO 7 J1=2,N,2                                                     ROUT 760
      LL = LL+1                                                         ROUT 770
      A(2,LL) = Y(J1)                                                   ROUT 780
    7 CONTINUE                                                          ROUT 790
C                                                                       ROUT 800
      IF (A(2,1).EQ.0.0) A(2,1)=0.0001                                  ROUT 810
C                                                                       ROUT 820
    8 DO 10 I=3,N                                                       ROUT 830
C                                                                       ROUT 840
      DO 9 M=1,KK                                                       ROUT 850
      A(I,M) = (A(I-1,1)*A(I-2,M+1)-A(I-2,1)*A(I-1,M+1))/A(I-1,1)       ROUT 860
    9 CONTINUE                                                          ROUT 870
C                                                                       ROUT 880
      IF (A(I,1).EQ.0.0) A(I,1)=0.0001                                  ROUT 890
      FF = FF-0.5                                                       ROUT 900
      KK = FF                                                           ROUT 910
   10 CONTINUE                                                          ROUT 920
C                                                                       ROUT 930
C                                                                       ROUT 940
      DO 11 I=1,N                                                       ROUT 950
      IF (A(I,1).LT.0.0) ISTABL=1                                       ROUT 960
```

```
   11 CONTINUE                                                          ROUT 970
C                                                                       ROUT 980
      RETURN                                                            ROUT 990
      END                                                               ROUT1000
```

```
C     ..................................................................PADD  10
C                                                                       PADD  20
C        SUBROUTINE PADD                                                PADD  30
C                                                                       PADD  40
C        PURPOSE                                                        PADD  50
C           ADD TWO POLYNOMIALS                                         PADD  60
C                                                                       PADD  70
C        USAGE                                                          PADD  80
C           CALL PADD(Z,IDIMZ,X,IDIMX,Y,IDIMY)                          PADD  90
C                                                                       PADD 100
C        DESCRIPTION OF PARAMETERS                                      PADD 110
C           Z      - VECTOR OF RESULTANT COEFFICIENTS, ORDERED FROM     PADD 120
C                    SMALLEST TO LARGEST POWER                          PADD 130
C           IDIMZ - DIMENSION OF Z (CALCULATED)                        PADD 140
C           X      - VECTOR OF COEFFICIENTS FOR FIRST POLYNOMIAL, ORDEREDPADD 150
C                    FROM SMALLEST TO LARGEST POWER                     PADD 160
C           IDIMX - DIMENSION OF X (DEGREE IS IDIMX-1)                 PADD 170
C           Y      - VECTOR OF COEFFICIENTS FOR SECOND POLYNOMIAL,      PADD 180
C                    ORDERED FROM SMALLEST TO LARGEST POWER    ,        PADD 190
C           IDIMY - DIMENSION OF Y (DEGREE IS IDIMY-1)                 PADD 200
C                                                                       PADD 210
C        REMARKS                                                        PADD 220
C           VECTOR Z MAY BE IN SAME LOCATION AS EITHER VECTOR X OR      PADD 230
C           VECTOR Y ONLY IF THE DIMENSION OF THAT VECTOR IS NOT LESS   PADD 240
C           THAN THE OTHER INPUT VECTOR                                 PADD 250
C           THE RESULTANT POLYNOMIAL MAY HAVE TRAILING ZERO COEFFICIENTSPADD 260
C                                                                       PADD 270
C        SUBROUTINES AND FUNCTION SUBPROGRAMS REQUIRED                  PADD 280
C           NONE                                                        PADD 290
C                                                                       PADD 300
C        METHOD                                                         PADD 310
C           DIMENSION OF RESULTANT VECTOR IDIMZ IS CALCULATED AS THE    PADD 320
C           LARGER OF THE TWO INPUT VECTOR DIMENSIONS. CORRESPONDING    PADD 330
C           COEFFICIENTS ARE THEN ADDED TO FORM Z.                      PADD 340
C                                                                       PADD 350
C     ..................................................................PADD 360
C                                                                       PADD 370
      SUBROUTINE PADD (Z,IDIMZ,X,IDIMX,Y,IDIMY)                         PADD 380
      DIMENSION Z(1), X(1), Y(1)                                        PADD 390
C                                                                       PADD 400
CCC   TEST DIMENSIONS OF SUMMANDS                                       PADD 410
C                                                                       PADD 420
      NDIM = IDIMX                                                      PADD 430
      IF (IDIMX-IDIMY) 1,2,2                                            PADD 440
    1 NDIM = IDIMY                                                      PADD 450
    2 IF (NDIM) 9,9,3                                                   PADD 460
C                                                                       PADD 470
    3 DO 8 I=1,NDIM                                                     PADD 480
```

```
      IF (I-IDIMX) 4,4,6                                                PADD 490
    4 IF (I-IDIMY) 5,5,7                                                PADD 500
    5 Z(I) = X(I)+Y(I)                                                  PADD 510
      GO TO 8                                                           PADD 520
    6 Z(I) = Y(I)                                                       PADD 530
      GO TO 8                                                           PADD 540
    7 Z(I) = X(I)                                                       PADD 550
    8 CONTINUE                                                          PADD 560
C                                                                       PADD 570
    9 IDIMZ = NDIM                                                      PADD 580
      RETURN                                                            PADD 590
      END                                                               PADD 600
```

```
C++++++
```

```
C AND FORM THE SUM OF THESE TO FIND THE TOTAL PHASE SHIFT INVOLVED.     CPHAS 490
C                                                                        PHAS 500
      DO 3 I=1,N                                                         PHAS 510
      VI = CMEG-RI(I)                                                    PHAS 520
      VR = -RR(I)                                                        PHAS 530
      IF ((VR.EQ.0.0).AND.(VI.EQ.0.0)) GO TO 1                           PHAS 540
      ANGR = ATAN2(VI,VR)                                                PHAS 550
      ANGD = ANGR*57.29578                                               PHAS 560
      GO TO 2                                                            PHAS 570
    1 ANGD = 0.0                                                         PHAS 580
    2 TANGD = TANGD+ANGD                                                 PHAS 590
    3 CONTINUE                                                           PHAS 600
C                                                                        PHAS 610
    4 RETURN                                                             PHAS 620
      END                                                                PHAS 630
```

```
C++++++
```

```
C                                                                       SIMU 490
      N7 = NSN+1                                                        SIMU 500
      N8 = NSD+1                                                        SIMU 510
      XCNEG = 500.0                                                     SIMU 520
      WFREQS(1) = WMIN                                                  SIMU 530
      Y = (ALOG10(WMAX)-ALOG10(WMIN))/(XCNEG-1.0)                       SIMU 540
      Z = 10.0**Y                                                       SIMU 550
C                                                                       SIMU 560
      DO 2 I=2,500                                                      SIMU 570
      J = I-1                                                           SIMU 580
    2 WFREQS(I) = WFREQS(J)*Z                                           SIMU 590
C                                                                       SIMU 600
C                                                                       SIMU 610
      DO 5 K=1,500                                                      SIMU 620
      CALL PVAL (COFASN,NSN,0.0,WFREQS(K),CNUMR,CNUMI)                  SIMU 630
      CALL PVAL (COFASD,NSD,0.0,WFREQS(K),CDENR,CDENI)                  SIMU 640
      IF (SQRT(CDENI**2+CDENR**2)) 4,3,4                                SIMU 650
    3 SAMAG(K) = 1.E+30                                                 SIMU 660
      CR(K) = 1.E+30                                                    SIMU 670
      CI(K) = 1.E+30                                                    SIMU 680
      GO TO 5                                                           SIMU 690
    4 SAMAG(K) = SQRT(CNUMI**2+CNUMR**2)/SQRT(CDENI**2+CDENR**2)        SIMU 700
      IF (IZOH.EQ.1) SAMAG(K)=SAMAG(K)*ABS((SIN(PI*WFREQS(K)/WS))/(PI*WFSIMU 710
     1REQS(K)/WS))                                                      SIMU 720
      CR(K) = (CNUMR*CDENR+CNUMI*CDENI)/(CDENR**2+CDENI**2)             SIMU 730
      CI(K) = (CNUMI*CDENR-CNUMR*CDENI)/(CDENR**2+CDENI**2)             SIMU 740
    5 CONTINUE                                                          SIMU 750
C                                                                       SIMU 760
      IF (N7.EQ.1) GO TO 7                                              SIMU 770
C                                                                       SIMU 780
      DO 6 I=1,N7                                                       SIMU 790
      COFWRK(I) = COFASN(I)                                             SIMU 800
    6 CONTINUE                                                          SIMU 810
C                                                                       SIMU 820
      CALL CONORM (COFWRK,N7,XNORM1)                                    SIMU 830
      CALL PROD (COFWRK,N7,RNR,RNI,CFWRK1,NRTSN1,IERN1)                 SIMU 840
      IF (IERN1.EQ.0) GO TO 8                                           SIMU 850
      CALL PROM (COFWRK,N7,RNR,RNI,CFWRK1,NRTSN2,IERN2)                 SIMU 860
      IF (IERN2.EQ.0) GO TO 8                                           SIMU 870
      WRITE (6,14)                                                      SIMU 880
      WRITE (6,15)                                                      SIMU 890
      WRITE (6,16)                                                      SIMU 900
      WRITE (6,15)                                                      SIMU 910
      WRITE (6,14)                                                      SIMU 920
      GO TO 12                                                          SIMU 930
    7 IF (N8.EQ.1) GO TO 10                                             SIMU 940
C                                                                       SIMU 950
    8 DO 9 J=1,N8                                                       SIMU 960
```

```
      COFWRK(J) = COFASC(J)                                                 SIMU 970
    9 CONTINUE                                                              SIMU 980
C                                                                           SIMU 990
      CALL CONCRM (COFWRK,N8,XNORM2)                                        SIMU1000
      GAINK = XNORM1/XNORM2                                                 SIMU1010
      CALL PROD (COFWRK,N8,RDR,RDI,CFWRK1,NRTSC1,IERC1)                     SIMU1020
      IF (IERC1.EQ.0) GO TO 10                                              SIMU1030
      CALL PROM (COFWRK,N8,RDR,RDI,CFWRK1,NRTSC2,IERC2)                     SIMU1040
      IF (IERC2.EQ.0) GO TO 10                                              SIMU1050
      WRITE (6,14)                                                          SIMU1060
      WRITE (6,15)                                                          SIMU1070
      WRITE (6,17)                                                          SIMU1080
      WRITE (6,15)                                                          SIMU1090
      WRITE (6,14)                                                          SIMU1100
      GO TO 12                                                              SIMU1110
C                                                                           SIMU1120
   10 DO 11 K=1,500                                                         SIMU1130
      CALL PHASE (RNR,RNI,NSN,WFREQS(K),ANGNUD)                             SIMU1140
      CALL PHASE (RDR,RDI,NSD,WFREQS(K),ANGDED)                             SIMU1150
      SAPHSD(K) = ANGNUD-ANGDED                                             SIMU1160
      IF (GAINK.LT.0.0) SAPHSD(K)=SAPHSD(K)-180.0                           SIMU1170
      IF (IZOP.NE.1) GO TO 11                                               SIMU1180
      IWS = WFREQS(K)/WS                                                    SIMU1190
      SAPHSD(K) = SAPHSD(K)-(PI*WFREQS(K)/WS)*57.29578-IWS*180.0            SIMU1200
   11 CONTINUE                                                              SIMU1210
C                                                                           SIMU1220
C                                                                           SIMU1230
   12 DO 13 J=1,500                                                         SIMU1240
      WFREQS(J) = ALOG10(WFREQS(J))                                         SIMU1250
      SAMAG(J) = 20.0*ALOG10(SAMAG(J))                                      SIMU1260
   13 CONTINUE                                                              SIMU1270
C                                                                           SIMU1280
      RETURN                                                                SIMU1290
C                                                                           SIMU1300
   14 FORMAT (' ',72('-'))                                                  SIMU1310
   15 FORMAT (' ',8('*WARNING*'))                                           SIMU1320
   16 FORMAT ('0','THE PHASE SIMULATION OF THE SYSTEM WAS ABANDONED',/,     SIMU1330
     1 ' SINCE THE CALLS TO TWO SEPARATE ROOT FINDING SUBROUTINES',/,       SIMU1340
     2 ' FAILED TO FIND THE SYSTEM NUMERATOR ROOTS',/)                      SIMU1350
   17 FORMAT ('0','THE PHASE SIMULATION OF THE SYSTEM WAS ABANDONED',/,     SIMU1360
     1 ' SINCE THE CALLS TO TWO SEPARATE ROOT FINDING SUBROUTINES',/,       SIMU1370
     2 ' FAILED TO FIND THE SYSTEM DENOMINATOR ROOTS',/)                    SIMU1380
      END                                                                   SIMU1390
```

APPENDIX C

DESCRIPTION OF FORTRAN VARIABLE NAMES

FORTRAN VARIABLE	UNIT	DESCRIPTION
A(I)	None	Array containing the coefficients of the plant transfer function numerator.
ADAMG(I)	db	Array containing the desired open loop magnitude response in db at the discrete frequencies specified by the designer.
AMAG(I)	db	Output array containing the magnitude of the open loop frequency response in db at the discrete frequencies specified.
ANGDED	Degrees	Phase angle contribution of the open loop system transfer function denominator at a specific frequency.
ANGDER	Radians	Phase angle contribution of the open loop system transfer function denominator at a specific frequency.
ANGNUD	Degrees	Phase angle contribution of the open loop system transfer function numerator at a specific frequency.
ANGNUR	Radians	Phase angle contribution of the open loop system transfer function numerator at a specific frequency.
B(I)	None	Array containing the coefficients of the plant transfer function denominator.
CO(I)	None	One dimensional working array used primarily in reading polynomial coefficients and inputing data to root finding subroutines.
COF(I)	None	One dimensional working array used primarily to store resulting coefficients used in checking accuracy of root finding subroutines.
COFASN(I)	None	Array containing the coefficients of the open loop transfer function numerator.

FORTRAN VARIABLE	UNIT	DESCRIPTION
COFASE(I)	None	Array containing the coefficients of the open loop system transfer function denominator.
COFWRK(I)	None	One dimensional working array used primarily to temporarily store polynomial coefficients in performing polynomial manipulations.
DELPHI	Degrees	Difference between two numerator phase angle contributions at successive discrete frequencies.
DELPSI	Degrees	Difference between two denominator phase angle contributions at successive discrete frequencies.
DIFF1(I)	db	Difference between the desired and actual magnitude of the open loop frequency response at the discrete frequency values specified in the input.
DIFF2(I)	Degrees	Difference between the desired and actual phase of the open loop frequency response at the discrete frequency values specified in the input.
DMAG(I)	None	Array containing the desired magnitude response at the discrete frequencies specified by the designer.
DQPHSE(I)	Degrees	Input array containing the desired phase profile of the open loop system at the discrete frequencies chosen.
DWFQ	Radians	Interval to be used if discrete frequency values are to be incremented linearly.
FREQ(I)	None	Logarithm of the discrete frequencies used in constructing abscissa for Bode plots.
GAIN	None	Gain of plant transfer function.
GAINCC	None	Gain of compensator transfer function.

FORTRAN VARIABLE	UNIT	DESCRIPTION
IDB	None	Input integer to be set equal to unity if the desired open loop magnitude response is input in db.
IERBXP	None	Output integer indicating the completion code of the minimization routine.
INFORM	None	Alphabetic input indicating if coefficients are to be read in factored or polynomial form.
IPLOT	None	Integer input, to be set to unity if CALCOMP plots of results are desired.
IZOH	None	Integer input set equal to unity if there is a zero order hold in the error signal path prior to the plant and compensator.
KNOW	None	Integer input indicating if discrete frequency values are to be read in or incremented linearly from the minimum frequency.
NBODE	None	Integer input to be set equal to unity if Bode plot is not desired.
NCD	None	Order of compensator transfer function denominator.
NCN	None	Order of compensator transfer function numerator.
NICHOL	None	Integer input to be set equal to unity if Nichol's plot is not desired.
NMINPS	None	Integer input to be set equal to unity if a nonminimum phase solution is to be allowed.
NOMEG	None	Integer specifying the total number of discrete frequency points being considered in the input frequency response profile. This number must be $\leq$ 500.
NSD	None	Order fo the system open loop transfer function denominator.

FORTRAN VARIABLE	UNIT	DESCRIPTION
NSN	None	Order of the system open loop transfer function numerator.
NTFD	None	Order of plant transfer function denominator.
NTFN	None	Order of plant transfer function numerator.
NYQST	None	Integer input to be set equal to unity if Nyquist plot is not desired.
N3	None	Dimension of array containing plant transfer function numerator coefficients.
N4	None	Dimension of array containing plant transfer function denominator coefficients.
QDENI	None	Value of the immaginary part of the system open loop transfer function denominator evaluated at a particular frequency.
QDENR	None	Value of the real part of the system open loop transfer function denominator evaluated at a particular frequency.
QMAG(I)	None	Output array containing the magnitude of the frequency response computed for the open loop system transfer function at the discrete frequencies specified.
QNUMI	None	Value of the immaginary part of the system open loop transfer function numerator evaluated at a particular frequency.
QNUMR	None	Value of the real part of the system open loop transfer function numerator evaluated at a particular frequency.
QPHSD(I)	Degrees	Output array containing the phase of the frequency response of the open loop system at the discrete frequencies specified.

FORTRAN VARIABLE	UNIT	DESCRIPTION
CPHSR(I)	Radians	Output array containing the phase of the frequency response of the open loop system transfer function at the discrete frequencies specified.
SAMAG(I)	db	Array containing the magnitude of the simulation of the resulting optimized system transfer function.
SAPHSI(I)	Degrees	Array containing the phase of the simulation of the resulting optimized system transfer function.
T	Secs	Sampling period if a zero order hold is present in the system.
WFREq(I)	Radians	Array containing the discrete frequencies specified by the designer.
WMAX	Radians	Input specifying the maximum frequency value of the range of frequencies being considered.
WMIN	Radians	Input specifying the minimum frequency value of the range of frequencies being considered.
WS	Radians	Output giving the sampling frequency if a zero order hold is present in the system.
XS(I)	None	Array in which values to be varied by the minimization routine are stored. At the start this array contains the initial guess of the coefficient values and at completion the array contains the coefficient values that yield the minimum cost function.

LIST OF REFERENCES

1. Massachusetts Institute of Technology, Electronic Systems Laboratory Report ESL-R-409, On the Design of a Digital Computer Program for the Design of Feedback Compensators in Transfer Function Form, by M. Athans, December 1969.

2. Beveridge, G. S. G. and Schechter, R. S., Optimization: Theory and Practice, p.453-456, McGraw-Hill, 1970.

3. Bode, H. W., Analysis and Feedback Amplifier Design, D. Van Nostrand Company, 1945.

4. Box, M. J., "A New Method of Constrained Optimization and a Comparison With Other Methods", Computer Journal, p.42-52, 8 April 1965.

5. Aerospace Corporation Report TR-1001(2307)-20, The Application of Modern Computing Technology to Control System Analysis and Design Problems, by T. C. Coffey, June 1967.

6. Jacoby, S. L. S., Kowalik, J. S., and Pizzo, J. T., Iterative Methods for Nonlinear Optimization Problems, p.155-157, Prentice-Hall, 1972.

7. Kuo, F. F., and Kaiser, J. F., Editors, Systems Analysis by Digital Computer, Wiley, 1966.

8. Leondes, C. T., Editor, Control and Dynamic Systems Advances in Theory and Applications, v. 11, p.25-143, Academic Press, 1974.

9. Melsa, J. L. and Jones, S. K., Computer Programs for Computational Assistance in the Study of Linear Control Theory, 2d. ed., McGraw Hill, 1973.

10. Melsa, J. L. and Schultz, D. G., Linear Control Systems, p. 513-591, McGraw Hill, 1969.

11. NASA Contractor Report CR-2248, An Innovative Approach to Compensator Design, by Jerrell A. Mitchell and Willie I. McDaniel, Jr., May 1973.

12. Oldenburger, R., Editor, Frequency Response, The MacMillian Co., 1956.

13. Page, J. A., Automated Design of Feedback Control Systems, Ph.D. Thesis, University of California, Los Angeles, 1970.

14. Rosenbrock, H. H., Computer Aided Control System Design, Academic Press, 1974.

15. Sanathanan, C. K. and Tsukui, H., "Synthesis of Transfer Function from Frequency Response Data", International Journal of Systems Science, v. 5, no. 4, p.41-54, May 1974.

16. NASA Technical Memorandum X-1443, FORMAC Program to Assist in the Analysis of Linear Control Systems Using State Variable Feedback Design Technique, by C. R. Slivinsky, L. T. Dellener, and D. J. Arpasi, October 1967.

17. Thaler, G. J., Design of Feedback Systems, Dowden, Hutchinson, and Ross, 1973.

18. Thaler, G. J. and Brown, R. G., Analysis and Design of Feedback Control Systems, 2d. ed., McGraw Hill, 1960.

19. Truxal, J. G., Introductory System Engineering, McGraw Hill, 1972.

20. Office of Naval Research London Conference Report C-20-73, Conference on "Computer Aided Control System Design", by A. H. Waynick, 10 September 1973.

21. Computer Aided Control System Design Conference Publication Number 96, A Method for Linear Systems Order Reduction, by S. C. Chuang, p.213-218, 4 April 1973.

INITIAL DISTRIBUTION LIST

		No. Copies
1.	Defense Documentation Center Cameron Station Alexandria, Virginia 22314	2
2.	Library, Code 0212 Naval Postgraduate School Monterey, California 93940	2
3.	Department Chairman, Code 62 Naval Postgraduate School Monterey, California 93940	2
4.	Professor George J. Thaler, Code 62TR Naval Postgraduate School Monterey, California 93940	5
5.	Lt. Anthony J. Mancini, USN 1514 Electric St. Scranton, Pa. 18509	3
6.	Dr. Jerrel R. Mitchell Department of Electrical Engineering Mississippi State University Mississippi State, Mississippi 39762	1
7.	Mr. Jay Cameron IBM Monterey and Cottle Roads San Jose, California 95114	1

8. Mr. Peter Gramata 1
IBM
Monterey and Cottle Roads
San Jose, California 95114

9. Mr. Robert McIntosh 1
IBM
Monterey and Cottle Roads
San Jose, California 95114

10. Mr. Martin Dost 1
IBM
Monterey and Cottle Roads
San Jose, California 95114

11. Mr. Ron Palmer 1
IBM
Monterey and Cottle Roads
San Jose, California 95114

12. Mr. W. M. Syn 1
IBM
Monterey and Cottle Roads
San Jose, California 95114

13. Professor A. G. J. MacFarlane 1
Dept. of Electrical Engineering
University of Manchester
Inst. of Science and Technology
Manchester England 067609

14. Dr. Bui-Tien Hung 1
Dept. of Applied Sciences
Universite du Quebec a Chicoutimi
930 est, rue Jacques-Cartier
Chicoutimi, Quebec
G7H 2B1

15. Mr. Dave Noble 1
IBM
Monterey and Cottle Roads
San Jose, California 95114

Thesis
M2786 Mancini
c.1
166101
Computer aided control system design using frequency domain specifications.